

Decompensated Low Noise, High Speed Precision Op Amps

FEATURES

- 100% Tested Low Voltage Noise: $2.7\text{nV}/\sqrt{\text{Hz}}$ Typ, $4.2\text{nV}/\sqrt{\text{Hz}}$ Max
- Slew Rate: $11\text{V}/\mu\text{s}$ Typ
- Gain-Bandwidth Product: 65MHz Typ
- Offset Voltage, Prime Grade: $70\mu\text{V}$ Max
Low Grade: $100\mu\text{V}$ Max
- High Voltage Gain: 5 Million Min
- Supply Current Per Amplifier: 3.1mA Max
- Common Mode Rejection: 112dB Min
- Power Supply Rejection: 116dB Min
- Available in 8-Lead SOIC, 8-Lead DIP, 16-Lead SO and 14-Lead DIP Packages

APPLICATIONS

- Two and Three Op Amp Instrumentation Amplifiers
- Low Noise Signal Processing
- Active Filters
- Microvolt Accuracy Threshold Detection
- Strain Gauge Amplifiers
- Direct Coupled Audio Gain Stages
- Tape Head Preamplifiers
- Microphone Preamplifiers
- Accelerometer Amplifiers
- Infrared Detectors

DESCRIPTION

The LT[®]1126 dual and LT1127 quad are high performance, decompensated op amps that offer higher slew rate and bandwidth than the LT1124 dual and the LT1125 quad operational amplifiers. The enhanced AC performance is available without degrading DC specs of the LT1124/LT1125. Both LT1126/LT1127 are stable in a gain of 10 or more.


In the design, processing and testing of the device, particular attention has been paid to the optimization of the entire distribution of several key parameters. Slew rate, gain-bandwidth and 1kHz noise are 100% tested for each individual amplifier. Consequently, the specifications of even the lowest cost grades (the LT1126C and the LT1127C) have been enhanced.

Power consumption of the dual LT1126 is less than one half of two OP-37s. Low power and high performance in an 8-pin SO package makes the LT1126 a first choice for surface mounted systems and where board space is restricted.

LT, LTC and LT are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners. Protected by U.S. Patents including 4775884, 4837496.

TYPICAL APPLICATION


Low Noise, Wide Bandwidth Instrumentation Amplifier



GAIN = 1000, BANDWIDTH = 480kHz
INPUT REFERRED NOISE = $4.5\text{nV}/\sqrt{\text{Hz}}$ AT 1kHz , $6\mu\text{V}_{\text{RMS}}$ OVER BANDWIDTH

1126-7 TA01

Voltage Noise vs Frequency



1126-7 TA01b

11267fa

ABSOLUTE MAXIMUM RATINGS (Note 1)

Supply Voltage $\pm 22\text{V}$
 Input Voltage Equal to Supply Voltage
 Output Short Circuit Duration Indefinite
 Differential Input Current (Note 5) $\pm 25\text{mA}$
 Lead Temperature (Soldering, 10 sec.) 300°C

Operating Temperature Range

LT1126AM/LT1126M

LT1127AM/LT1127M (**OBSOLETE**) .. -55°C to 125°C





LT1126AC/LT1126C

LT1127AC/LT1127C -40°C to 85°C

Storage Temperature Range

All Grades -65°C to 150°C

PACKAGE/ORDER INFORMATION

| | | | |
|---|--|--|--|
|  <p>S8 PACKAGE 8-LEAD PLASTIC SO $T_{JMAX} = 140^\circ\text{C}$, $\theta_{JA} = 190^\circ\text{C/W}$</p> <p>NOTE: THIS PIN CONFIGURATION DIFFERS FROM THE 8-PIN PDIP CONFIGURATION. INSTEAD, IT FOLLOWS THE INDUSTRY STANDARD LT1013DS8 SO PACKAGE PIN LOCATIONS</p> | <p>ORDER PART NUMBER</p> <p>LT1126CS8</p> <p>S8 PART MARKING</p> <p>1126</p> |  <p>N8 PACKAGE 8-LEAD PDIP $T_{JMAX} = 140^\circ\text{C}$, $\theta_{JA} = 130^\circ\text{C}$</p> <p>J8 PACKAGE 8-LEAD CERAMIC DIP $T_{JMAX} = 160^\circ\text{C}$, $\theta_{JA} = 100^\circ\text{C/W}$ OBSOLETE PACKAGE Consider the N8 for Alternate Source</p> | <p>ORDER PART NUMBER</p> <p>LT1126ACN8 LT1126CN8</p> <p>LT1126AMJ8 LT1126MJ8 LT1126CJ8</p> |
|  <p>SW PACKAGE 16-LEAD PLASTIC SO WIDE $T_{JMAX} = 140^\circ\text{C}$, $\theta_{JA} = 130^\circ\text{C/W}$</p> | <p>LT1127CSW</p> |  <p>N PACKAGE 14-LEAD PDIP $T_{JMAX} = 140^\circ\text{C}$, $\theta_{JA} = 110^\circ\text{C (N)}$</p> <p>J PACKAGE 14-LEAD CERAMIC DIP $T_{JMAX} = 160^\circ\text{C}$, $\theta_{JA} = 80^\circ\text{C/W}$ OBSOLETE PACKAGE Consider the N for Alternate Source</p> | <p>LT1127ACN LT1127CN</p> <p>LT1127AMJ LT1127MJ LT1127CJ</p> |
| <p>Order Options Tape and Reel: Add #TR Lead Free: Add #PBF Lead Free Tape and Reel: Add #TRPBF Lead Free Part Marking: http://www.linear.com/leadfree/</p> | | | |

Consult LTC Marketing for parts specified with wider operating temperature ranges.

ELECTRICAL CHARACTERISTICS $V_S = \pm 15V$, $T_A = 25^\circ C$, unless otherwise noted.

| SYMBOL | PARAMETER | CONDITIONS (Note 2) | LT1126AM/AC LT1127AM/AC | | | LT1126M/C LT1127M/C | | | UNITS |
|-------------------------------------|--|---|----------------------------|-------------|------------|------------------------|-------------|------------|----------------------------------|
| | | | MIN | TYP | MAX | MIN | TYP | MAX | |
| V_{OS} | Input Offset Voltage | LT1126 LT1127 | | 20 25 | 70 90 | | 25 30 | 100 140 | μV μV |
| $\frac{\Delta V_{OS}}{\Delta Time}$ | Long Term Input Offset Voltage Stability | | | 0.3 | | | 0.3 | | $\mu V/Mo$ |
| I_{OS} | Input Offset Current | LT1126 LT1127 | | 5 6 | 15 20 | | 6 7 | 20 30 | nA nA |
| I_B | Input Bias Current | | | ± 7 | ± 20 | | ± 8 | ± 30 | nA |
| e_n | Input Noise Voltage | 0.1Hz to 10Hz (Notes 8, 9) | | 70 | 200 | | 70 | | nVp-p |
| | Input Noise Voltage Density | $f_0 = 10Hz$ (Note 5) $f_0 = 1000Hz$ (Note 3) | | 3.0 2.7 | 5.5 4.2 | | 3.0 2.7 | 5.5 4.2 | nV/\sqrt{Hz} nV/\sqrt{Hz} |
| i_n | Input Noise Current Density | $f_0 = 10Hz$ $f_0 = 1000Hz$ | | 1.3 0.3 | | | 1.3 0.3 | | pA/\sqrt{Hz} pA/\sqrt{Hz} |
| V_{CM} | Input Voltage Range | | ± 12.0 | ± 12.8 | | ± 12.0 | ± 12.8 | | V |
| CMRR | Common Mode Rejection Ratio | $V_{CM} = \pm 12V$ | 112 | 126 | | 106 | 124 | | dB |
| PSRR | Power Supply Rejection Ratio | $V_S = \pm 4V$ to $\pm 18V$ | 116 | 126 | | 110 | 124 | | dB |
| A_{VOL} | Large Signal Voltage Gain | $R_L \geq 10k\Omega$, $V_O = \pm 10V$ $R_L \geq 2k\Omega$, $V_O = \pm 10V$ | 5.0 2.0 | 17.0 4.0 | | 3.0 1.5 | 15.0 3.0 | | $V/\mu V$ $V/\mu V$ |
| V_{OUT} | Maximum Output Voltage Swing | $R_L \geq 2k\Omega$ | ± 13.0 | ± 13.8 | | ± 12.5 | ± 13.8 | | V |
| SR | Slew Rate | $R_L \geq 2k\Omega$ (Notes 3, 7) | 8.0 | 11 | | 8.0 | 11 | | V/ μs |
| GBW | Gain-Bandwidth Product | $f_0 = 10kHz$ (Note 3) | 45 | 65 | | 45 | 65 | | MHz |
| Z_O | Open Loop Output Resistance | $V_O = 0$, $I_O = 0$ | | 75 | | | 75 | | Ω |
| I_S | Supply Current Per Amplifier | | | 2.6 | 3.1 | | 2.6 | 3.1 | mA |
| | Channel Separation | $f \leq 10Hz$ (Note 9) $V_O = \pm 10V$, $R_L = 2k\Omega$ | 134 | 150 | | 130 | 150 | | dB |

The ● denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $V_S = \pm 15V$, $-55^\circ C \leq T_A \leq 125^\circ C$, unless otherwise noted.

| SYMBOL | PARAMETER | CONDITIONS (Note 1) | | LT1126AM LT1127AM | | | LT1126M LT1127M | | | UNITS |
|-------------------------------------|------------------------------------|---|--------|----------------------|-------------|------------|--------------------|-------------|------------|------------------------|
| | | | | MIN | TYP | MAX | MIN | TYP | MAX | |
| V_{OS} | Input Offset Voltage | LT1126 LT1127 | ● ● | | 50 55 | 170 190 | | 60 70 | 250 290 | μV μV |
| $\frac{\Delta V_{OS}}{\Delta Temp}$ | Average Input Offset Voltage Drift | (Note 5) | ● | | 0.3 | 1.0 | | 0.4 | 1.5 | $\mu V/^\circ C$ |
| I_{OS} | Input Offset Current | LT1126 LT1127 | ● ● | | 18 18 | 45 55 | | 20 20 | 60 70 | nA nA |
| I_B | Input Bias Current | | ● | | ± 18 | ± 55 | | ± 20 | ± 70 | nA |
| V_{CM} | Input Voltage Range | | ● | ± 11.3 | ± 12 | | ± 11.3 | ± 12 | | V |
| CMRR | Common Mode Rejection Ratio | $V_{CM} = \pm 11.3V$ | ● | 106 | 122 | | 100 | 120 | | dB |
| PSRR | Power Supply Rejection Ratio | $V_S = \pm 4V$ to $\pm 18V$ | ● | 110 | 122 | | 104 | 120 | | dB |
| A_{VOL} | Large Signal Voltage Gain | $R_L \geq 10k\Omega$, $V_O = \pm 10V$ $R_L \geq 2k\Omega$, $V_O = \pm 10V$ | ● ● | 3.0 1.0 | 10.0 3.0 | | 2.0 0.7 | 10.0 2.0 | | $V/\mu V$ $V/\mu V$ |
| V_{OUT} | Maximum Output Voltage Swing | $R_L \geq 2k\Omega$ | ● | ± 12.5 | ± 13.6 | | ± 12.0 | ± 13.6 | | V |
| SR | Slew Rate | $R_L \geq 2k\Omega$ (Notes 3, 7) | ● | 7.2 | 10 | | 7.0 | 10 | | V/ μs |
| I_S | Supply Current Per Amplifier | | ● | | 2.8 | 3.5 | | 2.8 | 3.5 | mA |

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $V_S = \pm 15V$, $0^\circ C \leq T_A \leq 70^\circ C$, unless otherwise noted.

| SYMBOL | PARAMETER | CONDITIONS (Note 2) | | LT1126AC LT1127AC | | | LT1126C LT1127C | | | UNITS |
|--------------------------|------------------------------------|---|--------|----------------------|-------------|-----|--------------------|-------------|-----|------------------------|
| | | | | MIN | TYP | MAX | MIN | TYP | MAX | |
| V_{OS} | Input Offset Voltage | LT1126 LT1127 | ● ● | 35 40 | 120 140 | | 45 50 | 170 210 | | μV μV |
| $\Delta V_{OS}/\Delta T$ | Average Input Offset Voltage Drift | (Note 5) | ● | 0.3 | 1.0 | | 0.4 | 1.5 | | $\mu V/^\circ C$ |
| I_{OS} | Input Offset Current | LT1126 LT1127 | ● ● | 6 7 | 25 35 | | 7 8 | 35 45 | | nA nA |
| I_B | Input Bias Current | | ● | ± 8 | ± 35 | | ± 9 | ± 45 | | nA |
| V_{CM} | Input Voltage Range | | ● | ± 11.5 | ± 12.4 | | ± 11.5 | ± 12.4 | | V |
| CMRR | Common Mode Rejection Ratio | $V_{CM} = \pm 11.5V$ | ● | 109 | 125 | | 102 | 122 | | dB |
| PSRR | Power Supply Rejection Ratio | $V_S = \pm 4V$ to $\pm 18V$ | ● | 112 | 125 | | 107 | 122 | | dB |
| A_{VOL} | Large Signal Voltage Gain | $R_L \geq 10k\Omega$, $V_O = \pm 10V$ $R_L \geq 2k\Omega$, $V_O = \pm 10V$ | ● ● | 4.0 1.5 | 15.0 3.5 | | 2.5 1.0 | 14.0 2.5 | | $V/\mu V$ $V/\mu V$ |
| V_{OUT} | Maximum Output Voltage Swing | $R_L \geq 2k\Omega$ | ● | ± 12.5 | ± 13.7 | | ± 12.0 | ± 13.7 | | V |
| SR | Slew Rate | $R_L \geq 2k\Omega$ (Notes 3, 7) | ● | 7.5 | 10.5 | | 7.3 | 10.5 | | $V/\mu s$ |
| I_S | Supply Current Per Amplifier | | ● | 2.7 | 3.3 | | 2.7 | 3.3 | | mA |

The ● denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $V_S = \pm 15V$, $-40^\circ C \leq T_A \leq 85^\circ C$, unless otherwise noted. (Note 10)

| SYMBOL | PARAMETER | CONDITIONS (Note 2) | | LT1126AC LT1127AC | | | LT1126C LT1127C | | | UNITS |
|--------------------------|------------------------------------|---|--------|----------------------|-------------|-----|--------------------|-------------|-----|------------------------|
| | | | | MIN | TYP | MAX | MIN | TYP | MAX | |
| V_{OS} | Input Offset Voltage | LT1126 LT1127 | ● ● | 40 45 | 140 160 | | 50 55 | 200 240 | | μV μV |
| $\Delta V_{OS}/\Delta T$ | Average Input Offset Voltage Drift | (Note 5) | ● | 0.3 | 1.0 | | 0.4 | 1.5 | | $\mu V/^\circ C$ |
| I_{OS} | Input Offset Current | LT1126 LT1127 | ● ● | 15 15 | 40 50 | | 17 17 | 55 65 | | nA nA |
| I_B | Input Bias Current | | ● | ± 15 | ± 50 | | ± 17 | ± 65 | | nA |
| V_{CM} | Input Voltage Range | | ● | ± 11.4 | ± 12.2 | | ± 11.4 | ± 12.2 | | V |
| CMRR | Common Mode Rejection Ratio | $V_{CM} = \pm 11.4V$ | ● | 107 | 124 | | 101 | 121 | | dB |
| PSRR | Power Supply Rejection Ratio | $V_S = \pm 4V$ to $\pm 18V$ | ● | 111 | 124 | | 106 | 121 | | dB |
| A_{VOL} | Large Signal Voltage Gain | $R_L \geq 10k\Omega$, $V_O = \pm 10V$ $R_L \geq 2k\Omega$, $V_O = \pm 10V$ | ● ● | 3.5 1.2 | 12.0 3.2 | | 2.2 0.8 | 12.0 2.3 | | $V/\mu V$ $V/\mu V$ |
| V_{OUT} | Maximum Output Voltage Swing | $R_L \geq 2k\Omega$ | ● | ± 12.5 | ± 13.6 | | ± 12.0 | ± 13.6 | | V |
| SR | Slew Rate | $R_L \geq 2k\Omega$ (Note 7) | ● | 7.3 | 10.2 | | 7.1 | 10.2 | | $V/\mu s$ |
| I_S | Supply Current Per Amplifier | | ● | 2.8 | 3.4 | | 2.8 | 3.4 | | mA |

Note 1: Absolute Maximum Ratings are those values beyond which the life of a device may be impaired.

Note 2: Typical parameters are defined as the 60% yield of parameter distributions of individual amplifiers; i.e., out of 100 LT1127s (or 100 LT1126s) typically 240 op amps (or 120) will be better than the indicated specification.

Note 3: This parameter is 100% tested for each individual amplifier.

Note 4: This parameter is sample tested only.

Note 5: This parameter is not 100% tested.

Note 6: The inputs are protected by back-to-back diodes. Current limiting resistors are not used in order to achieve low noise. If differential input voltage exceeds $\pm 1.4V$, the input current should be limited to 25mA.

Note 7: Slew rate is measured in $A_V = -10$; input signal is $\pm 1V$, output measured at $\pm 5V$.

Note 8: 0.1Hz to 10Hz noise can be inferred from the 10Hz noise voltage density test. See the test circuit and frequency response curve for 0.1Hz to 10Hz tester in the Applications Information section of the LT1007 or LT1028 datasheets.

Note 9: This parameter is guaranteed but not tested.







Note 10: The LT1126/LT1127 are designed, characterized and expected to meet these extended temperature limits, but are not tested at $-40^\circ C$ and at $85^\circ C$. Guaranteed I grade parts are available. Consult factory.

TYPICAL PERFORMANCE CHARACTERISTICS

The typical behavior of many LT1126/LT1127 parameters is identical to the LT1124/LT1125. Please refer to the LT1124/LT1125 data sheet for the following performance characteristics:


0.1Hz to 10Hz Voltage Noise
0.01Hz to 1Hz Voltage Noise
Current Noise vs Frequency
Input Bias or Offset Current vs Temperature
Output Short Circuit Current vs Time

Input Bias Current Over the Common Mode Range
Voltage Gain vs Temperature
Input Offset Voltage Drift Distribution
Offset Voltage Drift with Temperature of Representative Units
Output Voltage Swing vs Load Current
Common Mode Limit vs Temperature
Channel Separation vs Frequency
Warm-Up Drift
Power Supply Rejection Ratio vs Frequency



*See LT1115 data sheet for definition of CCIF testing

TYPICAL PERFORMANCE CHARACTERISTICS



*See LT1115 data sheet for definition of CCIF testing

APPLICATIONS INFORMATION

Matching Specifications

In many applications the performance of a system depends on the matching between two op amps, rather than the individual characteristics of the two devices. The three op amp instrumentation amplifier configuration shown in this data sheet is an example. Matching characteristics are not 100% tested on the LT1126/LT1127.

Some specifications are guaranteed by definition. For example, 70μV maximum offset voltage implies that mismatch cannot be more than 140μV. 112dB (= 2.5μV/V) CMRR means that worst case CMRR match is 106dB (5μV/V). However, the following table can be used to estimate the expected matching performance between the two sides of the LT1126, and between amplifiers A and D, and between amplifiers B and C of the LT1127.

Expected Match


| PARAMETER | | LT1126AM/AC LT1127AM/AC | | LT1126M/C LT1127M/C | | UNITS |
|---|--------|----------------------------|-----------|------------------------|-----------|-------|
| | | 50% YIELD | 98% YIELD | 50% YIELD | 98% YIELD | |
| V _{OS} Match, ΔV _{OS} | LT1126 | 20 | 110 | 30 | 130 | μV |
| | LT1127 | 30 | 150 | 50 | 180 | μV |
| Temperature Coefficient Match | | 0.35 | 1.0 | 0.5 | 1.5 | μV/°C |
| Average Non-Inverting I _B | | 6 | 18 | 7 | 25 | nA |
| Match of Non-Inverting I _B | | 7 | 22 | 8 | 30 | nA |
| CMRR Match | | 126 | 115 | 123 | 112 | dB |
| PSRR Match | | 127 | 118 | 127 | 114 | dB |

APPLICATIONS INFORMATION

High Speed Operation


When the feedback around the op amp is resistive (R_F), a pole will be created with R_F , the source resistance and capacitance (R_S , C_S), and the amplifier input capacitance ($C_{IN} \approx 2\text{pF}$). In low closed loop gain configurations and

with R_S and R_F in the kilohm range, this pole can create excess phase shift and even oscillation. A small capacitor (C_F) in parallel with R_F eliminates this problem. With $R_S (C_S + C_{IN}) = R_F C_F$, the effect of the feedback pole is completely removed.



TYPICAL APPLICATIONS


Gain 1000 Amplifier with 0.01% Accuracy, DC to 5Hz



THE HIGH GAIN AND WIDE BANDWIDTH OF THE LT1126/LT1127 IS USEFUL IN LOW FREQUENCY HIGH CLOSED LOOP GAIN AMPLIFIER APPLICATIONS. A TYPICAL PRECISION OP AMP MAY HAVE AN OPEN LOOP GAIN OF ONE MILLION WITH 500kHz BANDWIDTH. AS THE GAIN ERROR PLOT SHOWS, THIS DEVICE IS CAPABLE OF 0.1% AMPLIFYING ACCURACY UP TO 0.3Hz ONLY. EVEN INSTRUMENTATION RANGE SIGNALS CAN VARY AT A FASTER RATE. THE LT1126/LT1127 "GAIN PRECISION — BANDWIDTH PRODUCT" IS 330 TIMES HIGHER, AS SHOWN.

1126-7 TA02


Gain Error vs Frequency Closed Loop Gain = 1000



1126-7 TA03


TYPICAL APPLICATIONS

Low Noise, Wideband, Gain = 100 Amplifier with High Input Impedance



PACKAGE DESCRIPTION


J8 Package 8-Lead Cerdip (Narrow .300 Inch, Hermetic) (Reference LTC DWG # 05-08-1110)



OBSOLETE PACKAGE


PACKAGE DESCRIPTION

N8 Package 8-Lead PDIP (Narrow .300 Inch) (Reference LTC DWG # 05-08-1510)




NOTE:
1. DIMENSIONS ARE IN INCHES
MILLIMETERS
*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .010 INCH (0.254mm)

S8 Package 8-Lead Plastic Small Outline (Narrow .150 Inch) (Reference LTC DWG # 05-08-1610)



NOTE:
1. DIMENSIONS IN INCHES
(MILLIMETERS)
2. DRAWING NOT TO SCALE
3. THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .006" (0.15mm)

J Package 14-Lead CERP (Narrow .300 Inch, Hermetic) (Reference LTC DWG # 05-08-1110)




NOTE: LEAD DIMENSIONS APPLY TO SOLDER DIP/PLATE
OR TIN PLATE LEADS

OBSOLETE PACKAGE

PACKAGE DESCRIPTION

N Package
14-Lead PDIP (Narrow .300 Inch)
 (Reference LTC DWG # 05-08-1510)







NOTE:
 1. DIMENSIONS ARE $\frac{\text{INCHES}}{\text{MILLIMETERS}}$

*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
 MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .010 INCH (0.254mm)

PACKAGE DESCRIPTION


SW Package 16-Lead Plastic Small Outline (Wide .300 Inch) (Reference LTC DWG # 05-08-1620)



- NOTE:
1. DIMENSIONS IN INCHES (MILLIMETERS)
 2. DRAWING NOT TO SCALE
 3. PIN 1 IDENT, NOTCH ON TOP AND CAVITIES ON THE BOTTOM OF PACKAGES ARE THE MANUFACTURING OPTIONS. THE PART MAY BE SUPPLIED WITH OR WITHOUT ANY OF THE OPTIONS
 4. THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS. MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .006" (0.15mm)

S16 (WIDE) 0502

SCHEMATIC DIAGRAM (1/2 LT1126, 1/4 LT1127)



RELATED PARTS

| PART NUMBER | DESCRIPTION | COMMENTS |
|---------------|--|----------------------------------|
| LT1124/LT1125 | Dual/Quad Low Noise High Speed Precision Op Amps | Unity Gain Stable |
| LT1037 | Low Noise, High Speed Precision Op Amps | 60MHz GBW, 11V/μs Slew Rate |
| LT1678/LT1679 | Dual/Quad Low Noise Rail-to-Rail Precision Op Amps | 20MHz GBW, 100μV V _{OS} |
| LT1028 | Ultralow Noise Precision High Speed Op Amps | 1.1nV/√Hz Max, 0.85 μV/Hz Typ |
| LT6230 | 215MHz, Rail-to-Rail Output Low Noise Op Amps | 1.1nV/√Hz, 3.5mA Supply Current |