

# AUTO/ISOLATION TRANSFORMERS

## Step-Down, Step-Up and Isolation Transformers




### Auto/Isolation Transformers

**Isolation Transformers** have two (2) separate windings with an electrostatic shield between them to provide complete electrical isolation from the source.

**Auto Transformers** have one (1) winding that is tapped to achieve specific output voltage. They provide no electrical isolation in a circuit.

Auto Transformers are typically smaller than their Isolation equivalent.

• Designed for 50/60 Hertz



Style C



Style A

— See Accessories, pages 40-41,  
for International Adapter Plugs

| Sec. | STANCOR<br>PART<br>NUMBER | Type      | Voltage<br>Step | Input<br>Voltage | Output<br>Voltage | Amps  | V.A. Cap. | RMS<br>Test<br>Voltage | Style | DIMENSIONS-INCHES |           |      |                |      | Weight<br>(lbs.) | Agency<br>Certif. |
|------|---------------------------|-----------|-----------------|------------------|-------------------|-------|-----------|------------------------|-------|-------------------|-----------|------|----------------|------|------------------|-------------------|
|      |                           |           |                 |                  |                   |       |           |                        |       | H                 | Case<br>W | D    | Mounting<br>MW | MD   |                  |                   |
| A    | P-6287                    | Auto      | Down            | 230              | 115               | 0.35  | 40        | 1500                   | C     | 3.13              | 2.50      | 2.75 | 2.00           | 1.75 | 2.20             |                   |
|      | P-8620#                   | Auto      | Down            | 230              | 115               | 0.43  | 50        | 1500                   | A     | 2.31              | 3.69      | 1.88 | 3.13           | -    | 1.50             | -                 |
|      | GSD-75                    | Auto      | Down            | 230              | 115               | 0.65  | 75        | 1500                   | C     | 3.13              | 2.50      | 2.88 | 2.00           | 1.75 | 3.00             | -                 |
|      | P-8630                    | Auto      | Down            | 230              | 115               | 0.74  | 85        | 1500                   | C     | 3.13              | 2.50      | 2.88 | 2.00           | 1.75 | 2.50             | -                 |
|      | GSD-100                   | Auto      | Down            | 230              | 115               | 0.87  | 100       | 1500                   | C     | 3.13              | 2.50      | 3.13 | 2.00           | 2.06 | 3.70             | -                 |
| B    | P-8631                    | Auto      | Down            | 230              | 115               | 1.10  | 125       | 1500                   | C     | 3.13              | 2.50      | 3.00 | 2.00           | 2.06 | 3.00             | -                 |
|      | GSD-150                   | Auto      | Down            | 230              | 115               | 1.30  | 150       | 1500                   | C     | 3.88              | 3.13      | 3.25 | 2.50           | 2.22 | 4.40             | -                 |
|      | P-8632                    | Auto      | Down            | 230              | 115               | 1.74  | 200       | 1500                   | C     | 3.88              | 3.13      | 3.25 | 2.50           | 2.22 | 4.20             | -                 |
|      | GSD-250                   | Auto      | Down            | 230              | 115               | 2.20  | 250       | 1500                   | C     | 3.88              | 3.13      | 3.63 | 2.50           | 2.22 | 5.80             | -                 |
|      | GSD-300                   | Auto      | Down            | 230              | 115               | 2.60  | 300       | 1500                   | C     | 3.88              | 3.13      | 3.63 | 2.50           | 2.22 | 5.80             | -                 |
| C    | GSD-350                   | Auto      | Down            | 230              | 115               | 3.00  | 350       | 1500                   | C     | 3.88              | 3.13      | 4.31 | 2.50           | 2.72 | 7.30             | -                 |
|      | P-8634                    | Auto      | Down            | 230              | 115               | 3.50  | 400       | 1500                   | C     | 3.88              | 3.13      | 4.25 | 2.50           | 2.72 | 7.00             | -                 |
|      | GSD-500                   | Auto      | Down            | 230              | 115               | 4.30  | 500       | 1500                   | C     | 4.63              | 3.81      | 4.44 | 3.00           | 3.19 | 10.6             | -                 |
|      | GSD-750                   | Auto      | Down            | 230              | 115               | 6.50  | 750       | 1500                   | C     | 4.63              | 3.81      | 5.38 | 3.00           | 3.94 | 14.4             | -                 |
|      | GSD-1000                  | Auto      | Down            | 230              | 115               | 8.70  | 1000      | 1500                   | C     | 4.63              | 3.81      | 6.06 | 3.00           | 4.69 | 17.0             | -                 |
| D    | GSD-1500                  | Auto      | Down            | 230              | 115               | 13.0  | 1500      | 1500                   | C     | 5.38              | 4.44      | 6.00 | 3.50           | 4.00 | 20.0             | -                 |
|      | P-8638                    | Auto      | Up              | 115              | 230               | 0.54  | 125       | 1500                   | C     | 3.13              | 2.50      | 3.00 | 2.00           | 2.06 | 3.00             | -                 |
|      | P-8639                    | Auto      | Up              | 115              | 230               | 1.30  | 300       | 1500                   | C     | 3.88              | 3.13      | 3.88 | 2.50           | 2.22 | 5.20             | -                 |
|      | P-8640                    | Auto      | Up              | 115              | 230               | 2.17  | 500       | 1500                   | C     | 4.63              | 3.75      | 4.50 | 3.00           | 3.19 | 10.3             | -                 |
|      | P-8689                    | Auto      | Up              | 115              | 230               | 4.35  | 1000      | 1500                   | C     | 4.63              | 3.75      | 6.13 | 3.00           | 4.69 | 17.0             | -                 |
| E    | P-6413#                   | Isolation | Straight        | 115              | 115               | 0.005 | 0.60      | 1500                   | A     | 1.25              | 2.13      | 1.25 | 1.75           | -    | 0.25             | -                 |
|      | P-6411#                   | Isolation | Straight        | 115              | 115               | 0.13  | 15        | 1500                   | A     | 2.00              | 3.25      | 1.88 | 2.81           | -    | 1.00             | -                 |
|      | P-6412#                   | Isolation | Straight        | 115              | 115               | 0.30  | 35        | 1500                   | A     | 2.31              | 3.75      | 2.00 | 3.13           | -    | 1.70             | -                 |
|      | P-6410                    | Isolation | Straight        | 115              | 115               | 0.43  | 50        | 1500                   | C     | 3.50              | 2.81      | 3.50 | 2.25           | 2.00 | 3.70             | -                 |
| F    | P-8622†#                  | Isolation | Straight        | 115              | ▲115/230          | 1.30  | 150       | 1500                   | C     | 3.88              | 3.13      | 4.00 | 2.50           | 2.72 | 6.20             | -                 |
|      | P-6406#                   | Isolation | Straight        | 115/230*†        | 115               | 0.43  | 50        | 1500                   | A     | 2.38              | 3.75      | 2.31 | 3.13           | -    | 1.80             | -                 |
| G    | GIS-100                   | Isolation | Straight        | 115              | 115               | 0.87  | 100       | 1500                   | C     | 3.50              | 2.81      | 3.56 | 2.25           | 2.28 | 4.50             | -                 |
|      | GIS-150                   | Isolation | Straight        | 115              | 115               | 1.30  | 150       | 1500                   | C     | 3.88              | 3.13      | 4.19 | 2.50           | 2.72 | 7.00             | -                 |
|      | GIS-250                   | Isolation | Straight        | 115              | 115               | 2.17  | 250       | 1500                   | C     | 4.69              | 3.75      | 4.38 | 3.00           | 3.19 | 9.00             | -                 |
|      | GIS-500                   | Isolation | Straight        | 115              | 115               | 4.35  | 500       | 1500                   | C     | 4.69              | 3.75      | 6.00 | 3.00           | 4.69 | 16.0             | -                 |
|      | GIS-1000                  | Isolation | Straight        | 115              | 115               | 8.70  | 1000      | 1500                   | C     | 5.38              | 4.38      | 8.13 | 3.50           | 6.50 | 31.0             | -                 |
| H    | GISD-100                  | Isolation | Down            | 230              | 115               | 0.87  | 100       | 1500                   | C     | 3.50              | 2.81      | 3.63 | 2.25           | 2.28 | 4.50             | -                 |
|      | GISD-150                  | Isolation | Down            | 230              | 115               | 1.30  | 150       | 1500                   | C     | 3.88              | 3.13      | 4.19 | 2.50           | 2.72 | 7.00             | -                 |
|      | GISD-250                  | Isolation | Down            | 230              | 115               | 2.17  | 250       | 1500                   | C     | 4.69              | 3.75      | 4.38 | 3.00           | 3.19 | 9.00             | -                 |
|      | GISD-500                  | Isolation | Down            | 230              | 115               | 4.35  | 500       | 1500                   | C     | 4.69              | 3.75      | 6.00 | 3.00           | 4.69 | 16.0             | -                 |
|      | GISD-1000                 | Isolation | Down            | 230              | 115               | 8.70  | 1000      | 1500                   | C     | 5.38              | 4.38      | 8.13 | 3.50           | 6.50 | 31.0             | -                 |

† Has electrostatic shield on separate leadwire (not grounded)



▲ Secondary is two separate 115 volt windings – can be wired independently

# Has lead wires

\* Primary is two separate 115 volt windings

For outline drawings refer to page 39

## Step-Down, Step-Up and Isolation Transformers



### GENERAL INFORMATION

#### Standard length of the input and output cords:

- Input Cord = 5 1/2 Feet minimum
- Output Cord = 8 Inches minimum

Auto/Isolation Transformers can be used in most countries by using an input adapter plug. See page 40 for STANCOR's high quality line of International Adapter Plugs.

### WHY & WHERE AUTO & ISOLATION TRANSFORMERS ARE USED

Stancor's stock Auto Transformers are connected for either step-down or step-up applications involving line voltages of 115 or 230 Volts., 50/60 Hertz. When isolation between the primary and secondary circuits is not necessary, and a direct connection between them is permissible, the Auto Transformer offers the advantages of smaller size, less weight, and lower cost. This type of unit is generally used in applications involving American appliances used abroad where our standard 115 Volt equipment must operate from a 230 Volt source. It is also used for foreign appliances designed for 230 Volt operation, which are to be used on our 115 Volt circuits. Our catalog items are designed for continuous rated output on either 50 or 60 Hertz.

**It is important to bear in mind that the Auto/Isolation Transformers change only the voltage levels and do not change the frequency from 50 to 60 Hertz or vice versa. In appliances using synchronous motors, such as clocks or phonograph record changers and players, the speed will be different when using them on a frequency which differs from the frequency they were originally designed. In these cases the manufacturer of the appliance should be consulted to obtain the proper motor.**

The VA rating is equivalent to a Wattage rating where a resistive load and/or unity power factor exists. When inductive loads such as motors are used (as in a motor driven appliance) the power factor is not unity and to be accurate the output is expressed in VA, which is the product of the output voltage and the output current (Amps).

When selecting one of these items for use with an appliance which includes a motor, allowance should be made for the starting current of the

motor which is somewhat higher than the running current. This information is generally available from the appliance manufacturer. Information pertaining to the AC Wattage or current required by an appliance is generally marked on the item by the manufacturer and should be observed. It is much better to buy a transformer with a larger VA rating than you will actually need because of larger motor starting currents and variations in the line voltage and/or frequency in some locations, which could cause overheating.

### Isolation Transformers

Used where a direct connection between primary and secondary circuits is not desired and the circuits must be isolated. This results in a larger, heavier and more costly item for a given power rating. However, in addition to the isolating advantages, an electrostatic shield is generally added to minimize capacitive coupling between primary and secondary circuits. This helps to minimize the transfer of unwanted power line transients and interference from other sources connected to the power line by capacitive coupling to the secondary circuit. The standard insulation test voltage rating between windings and between each winding and the core is 1,500 Volts R.M.S. This is normally sufficient for 115 and 230 Volt operation.

The VA rating should be selected for each specific application, with allowance for any abnormal load or environmental conditions. All catalog items have an operating temperature of 105 Degrees C. (Designed for a 65 Degrees C. maximum temperature rise above a maximum ambient temperature for 40 Degrees C., with unrestricted free air ventilation.) V-A/Amps output ratings are for continuous operation from the specified input voltage and frequency.

### General Information

All of these items have Class "A" insulation and are rated to have a maximum operating temperature of 105 Degrees C. These units may be used with rectifiers but the form factor as explained elsewhere in this catalog should be observed for various combinations of rectifier circuits and types of load following the rectifier.

These items are made with our standard N.E.M.A. plugs and receptacles, primarily for use in this country. However, if used overseas where different types of plugs are necessary, an adapter plug should be used or our plug removed and a foreign plug attached to the end of the line cord.