



Modular Power System: 1200 W per mainframe GPIB

Save rack space with 8 power supply outputs in one mainframe
Increase test throughput with advanced triggering system and
down-loadable LIST mode
Reconfigure fast with easily swappable modules

66000A (mainframe)
66001A (keyboard)

Specifications

(at 0° to 55° C unless
otherwise specified)

66101A 66102A 66103A 66104A 66105A 66106A

66000 Modular Power System

The Agilent 66000 modular power system simplifies test-system assembly, cabling, programming, debugging and operation. It is ideal for ATE and production test environments, where it can supply bias power and stimulus to sub-assemblies and final products. The modular power system saves rack space, the 7-inch-high (4-EIA units) mainframe can accommodate up to eight dc power modules.

Key Features

- GPIB-programmable voltage and current
- Programmable over-voltage and over-current protection
- Self-test initiated at power-up or from GPIB command
- Electronic calibration over GPIB or from keyboard
- Over-temperature protection
- Discrete fault indicator/remote inhibit (DFI/RI)
- Five nonvolatile store-recall states per output
- User-definable power-on state

Multiple Mainframes at One GPIB Address

The Agilent serial link feature will allow you to control up to 16 outputs at one GPIB address by connecting an auxiliary mainframe. The serial link cable comes standard with the

Output ratings at 40° C		66101A	66102A	66103A	66104A	66105A	66106A
Output voltage		0 to 8 V	0 to 20 V	0 to 35 V	0 to 60 V	0 to 120 V	0 to 200 V
Output current		0 to 16 A	0 to 7.5 A	0 to 4.5 A	0 to 2.5 A	0 to 1.25 A	0 to 0.75 A
Maximum power		128 W	150 W	150 W	150 W	150 W	150 W
Programming accuracy at 25° C ±5° C		66101A	66102A	66103A	66104A	66105A	66106A
Voltage	0.03% +	3 mV	8 mV	13 mV	27 mV	54 mV	90 mV
Current	0.03% +	6 mA	3 mA	2 mA	1.2 mA	0.6 mA	0.4 mA
Readback accuracy (via GPIB or keyboard display at 25° C ±5° C)		66101A	66102A	66103A	66104A	66105A	66106A
Voltage	0.02%+	2 mV	5 mV	8 mV	16 mV	32 mV	54 mV
Current	0.02%+	6 mA	3 mA	2 mA	1 mA	0.6 mA	0.3 mA
Ripple and noise (20 Hz to 20 MHz)		66101A	66102A	66103A	66104A	66105A	66106A
Constant Voltage rms		2 mV	3 mV	5 mV	9 mV	18 mV	30 mV
peak-peak		5 mV	7 mV	10 mV	15 mV	25 mV	50 mV
Constant Current rms		8 mA	4 mA	2 mA	1 mA	1 mA	1 mA
Line regulation		66101A	66102A	66103A	66104A	66105A	66106A
Voltage		0.5 mV	0.5 mV	1 mV	2 mV	3 mV	5 mV
Current		0.75 mA	0.5 mA	0.3 mA	0.1 mA	50 µA	30 µA
Load regulation		66101A	66102A	66103A	66104A	66105A	66106A
Voltage		1 mV	1 mV	1 mV	2 mV	4 mV	7 mV
Current		0.5 mA	0.2 mA	0.2 mA	0.1 mA	50 µA	30 µA
Transient response time		Less than 1 ms for the output voltage to recover within 100 mV of its previous level following any step change in load current up to 10 percent of rated current					
Supplemental Characteristics		(Non-warranted characteristics determined by design that are useful in applying the product)					
Average resolution		66101A	66102A	66103A	66104A	66105A	66106A
Voltage		2.4 mV	5.9 mV	10.4 mV	18.0 mV	36.0 mV	60.0 mV
Current		4.6 mA	2.3 mA	1.4 mA	0.75 mA	0.39 mA	0.23 mA
Output voltage programming (OVP)		50 mV	120 mV	200 mV	375 mV	750 mV	1.25 mV
OVP accuracy		250 mV	500 mV	800 mV	1 V	1.5 V	2.5 V



Modular Power System: 1200 W per mainframe GPIB (Continued)

66000 MPS mainframe. For applications with a broader range of power requirements, one 66000 mainframe can be connected with up to eight of the 6640, 6650, 6670, 6680, 6690 or 6030 series of system power supplies. This solution provides power ranges from 150 watts to 5000 watts at one primary GPIB address.

Output Connections

System assembly is simplified thanks to a quick-disconnect connector assembly on each module. Once your wires are connected to the load, the connector design permits the modules to be removed from the front of the mainframe without disconnecting cabling or removing the mainframe from the rack. One connector assembly is shipped with each module.

Output Sequencing

Increase test throughput by using the output sequencing feature of the 66000 MPS. This powerful feature allows you to download up to 20 voltage, current, and dwell-time parameter sets per output. This sequence can be paced by the programmed dwell times. As an alternative, triggers can be used to step through the output list. The output sequences can be executed without controller intervention, thereby increasing overall test system throughput. More detailed information on the triggering and output sequencing capabilities can be obtained by ordering the 66000 Modular Power System Product Note (p/n 5091-2497E) described below.

Key Literature

66000 Modular Power System
Product Note
p/n 5091-2497E

Specifications

(at 0° to 55° C unless otherwise specified)

66101A-J03
Special Order Option

66101A-J05
Special Order Option

66102A-J05
Special Order Option

66103A-J01
Special Order Option

66103A-J02
Special Order Option

Output ratings at 40° C

Output voltage	5.7 V	12 V	15 V	37 V	40 V
Output current	20 A	12 A	10 A	4.5 A	3.6 A
Maximum power	114 W	144 W	150 W	167 W	144 W

Programming accuracy at 25° C ±5° C

Voltage	0.03% +	2.5 mV	5 mV	8 mV	13 mV	15 mV
Current	0.03% +	8 mA	6 mA	4 mA	2 mA	2 mA

Readback accuracy (via GPIB keyboard display at 25° C ±5° C)

Voltage	0.02% +	2 mV	3 mV	5 mV	8 mV	9.2 mV
Current	0.02% +	8 mA	6 mA	4 mA	2 mA	2 mA

Ripple and noise (20 Hz to 20 MHz)

Constant Voltage rms	2 mV	3 mV	3 mV	5.3 mV	6 mV
peak-peak	5 mV	7 mV	7 mV	10.6 mV	11.5 mV
Constant Current rms	10 mA	8 mA	6 mA	2 mA	2 mA

Line regulation

Voltage	0.5 mV	0.5 mV	0.5 mV	1 mV	1 mV
Current	0.5 mA	0.75 mA	0.5 mA	0.3 mA	0.3 mA

Load regulation

Voltage	1 mV	1 mV	1 mV	1 mV	1 mV
Current	1 mA	0.5 mA	0.3 mA	0.2 mA	0.2 mA

Transient response time

Less than 1 ms for the output voltage to recover within 100 mV of its previous level following any step change in load current up to 10 percent of rated current

Supplemental Characteristics

(Non-warranted characteristics determined by design that are useful in applying the product)

Average resolution					
Voltage	2 mV	3.6 mV	4.5 mV	11 mV	12 mV
Current	6 mA	4.6 mA	3.1 mA	1.4 mA	1.2 mA
OVP	45 mV	75 mV	90 mV	200 mV	230 mV
OVP accuracy	250 mV	375 mV	375 mV	850 mV	920 mV

Supplemental Characteristics for all model numbers

dc Floating Voltage: Output terminals can be floated up to ±240 Vdc from chassis ground

Remote Sensing: Up to half the rated output voltage can be dropped across each load lead. Add 2 mV to the voltage load regulation specification for each 1-V change in the negative output lead caused by a load current change.

Command Processing Time: The average time for the output voltage to change after getting a GPIB command is 20 ms

Output Programming Response Time (with full resistive load): The rise and fall time (10% to 90% and 90% to 10%) of the output voltage is less than 20 ms. The output voltage change settles within 0.1% of the final value in less than 120 ms.



Modular Power System: 1200 W per mainframe GPIB (Continued)

Down Programming: An active down-programmer sinks approximately 10% of the rated output current

Calibration Interval: One year

ac Input of System Mainframe

Voltage	100 Vac	120 Vac	200 Vac	220 Vac	230 Vac	240 Vac
Max. Current	29 A	25 A	16 A	16 A	15 A	15 A

Input Power of System Mainframe: 3200 VA (max.), 1800 W (max.), 1600 W (typ.)

GPIB Capabilities: SH1, AH1, TE6, LE4, SR1, RL1, PP0, DC1, DT1, E1, and C0, and a command set compatible with IEEE-488.2 and SCPI

Regulatory Compliance: Listed to UL 1244; certified to CSA 22.2 No. 231; conforms to IEC 61010-1.

Weight: Net, 66000A, 15 kg (33 lb); 66001A, 1.05 kg (2.3 lb); 66101-66106A, 2.8 kg (6 lb). Shipping, 66000A, 19 kg (42 lb); 66001A, 1.34 kg (2.95 lb); 66101-66106A, 4.1 kg (9 lb).

Size: 66000A: 425.7 mm W x 192 mm H x 677.93 mm D (16.76 in x 7.28 in x 26.69 in), including feet and rear connectors (See Page 104 for more details.)

Warranty Period: One year

Ordering Information

66000A MPS Mainframe

Opt 120 for operation at 100 Vac or 120 Vac nominal

Opt 240 for operation at 200 Vac or 220-240 Vac nominal

* **Opt 908** Rack-mount Kit (p/n 5063-9215)

* **Opt 909** Rack-mount Kit with Handles (p/n 5063-9222)

Opt 0L2 Extra Standard Documentation Package

Opt 0B3 Service Manual

Opt 0B0 No documentation package

* **Note:** Options 908 and 909 require cabinet rails (E3663AC) or a slide kit (p/n 1494-0059) to support the loaded mainframe's weight.

A line cord option must be specified.

See pages 93-98.

66001A MPS Keyboard includes 2m (6 ft) cables

66002A Rack kit for 66001A keyboard

Specifications

(at 0° to 55°C unless otherwise specified)

66103A-J09
Special Order Option

66103A-J12
Special Order Option

66104A-J09
Special Order Option

66105A-J01
Special Order Option

Output ratings at 40°C

Output voltage	28.5 V	24 V	55 V	35 V
Output current	5.5 A	6 A	3 A	1.25 A
Maximum power	157 W	144 W	165 W	44 W

Programming accuracy at 25°C ±5°C

Voltage	0.03% +	13 mV	13 mV	25 mV	15 mV
Current	0.03% +	3 mA	3 mA	1.5 mA	0.6 mA

Readback accuracy (via GPIB or keyboard display at 25°C ±5°C)

Voltage	0.02% +	8 mV	8 mV	15 mV	9 mV
Current	0.02% +	3 mA	3 mA	1.2 mA	0.6 mA

Ripple and noise (20 Hz to 20 MHz)

Constant Voltage rms	5 mV	5 mV	9 mV	6 mV
peak-peak	10 mV	10 mV	15 mV	11.5 mV
Constant Current rms	4 mA	4 mA	1.2 mA	1 mA

Line regulation

Voltage	1 mV	1 mV	2 mV	1 mV
Current	0.3 mA	0.3 mA	0.1 mA	50 µA

Load regulation

Voltage	1 mV	1 mV	2 mV	1 mV
Current	0.2 mA	0.2 mA	0.1 mA	50 µA

Transient response time

Less than 1 ms for the output voltage to recover within 100 mV of its previous level following any step change in load current up to 10 percent of rated current

Supplemental Characteristics

(Non-warranted characteristics determined by design that are useful in applying the product)

Average resolution				
Voltage	10.4 mV	8 mV	16.5 mV	2 mV
Current	2 mA	2 mA	0.9 mA	1.2 mA
OVP	200 mV	150 mV	350 mV	230 mV
OVP accuracy	800 mV	600 mV	950 mV	920 mV

Module Options

Opt 760 Open/Close and Polarity Reversal Relays

Opt J17 External Imon

Opt 0L2 Extra Standard Documentation Package

Opt 0B3 Service Manual

Opt 0B0 No documentation package

Accessories

p/n 5060-3351 Field-Installable Relay Kit

p/n 5060-3386 Standard Connector Assembly

p/n 5060-3387 Standard Connector Assembly with installed relays (Option 760)

p/n 66000-90001 Mainframe Installation Guide

p/n 5959-3360 dc Power Module User's Guide

p/n 5959-3362 dc Power Module Programming Guide

p/n 66000-90003 Mainframe Service Manual

p/n 5959-3364 dc Power Module Service Manual

p/n 1252-1488 4-Pin FLT/Inhibit Connector
E3663AC Support rails for Agilent rack cabinets

Your Requested Excerpt from the Agilent Power Products Catalog

The preceding page(s) are an excerpt from the *2002-2003 Power Products Catalog*. We hope that these pages supply the information that you currently need.

If you would like to have further information about the extensive selection of Agilent dc power supplies, ac sources, and dc electronic loads, please visit www.agilent.com/find/power to print a copy of the complete Power Products catalog, or to request that a copy be sent to you. You will also find a lot of other useful information on this web site.

In the full Power Products Catalog, you will find that Agilent offers much more than basic power generation. If you need basic, clean, power for your lab bench, it's there. But in each product category, we've also integrated the capabilities that you need for a complete power solution, including extensive measurement and analysis capabilities.

Please give us a call at your local Agilent Technologies sales office, or call a regional office listed below, for assistance in choosing or using Agilent power products.

Keep up to date with Agilent's Test and Measurement Email Updates

As an Email Update subscriber, you will receive periodic customized email updates that match the areas of interest that you have specified. Your update will include products and services, applications and support information, events, and promotions. Sign up today at www.agilent.com/find/emailupdates.

Check off dc power supplies, ac power sources or electronic loads on your registration form, and we will promptly let you know what's new in power products! Our Privacy Statement at www.agilent.com/go/privacy describes our commitment to you regarding your privacy.

To see a copy of the user's guide, please visit our Web site at www.agilent.com/find/manuals

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:
www.agilent.com/find/assist

Phone or Fax

United States:
(tel) 1 800 829 4444

Canada:
(tel) 1 877 894 4414
(fax) (905) 282-6495

China:
(tel) 800-810-0189
(fax) 1-0800-650-0121

Europe:
(tel) (31 20) 547 2323
(fax) (31 20) 547 2390

Japan:
(tel) (81) 426 56 7832
(fax) (81) 426 56 7840

Korea:
(tel) (82-2) 2004-5004
(fax) (82-2) 2004-5115

Latin America:
(tel) (305) 269 7500
(fax) (305) 269 7599

Taiwan:
(tel) 080-004-7866
(fax) (886-2) 2545-6723

Other Asia Pacific Countries:
(tel) (65) 375-8100
(fax) (65) 836-0252
Email: tm_asia@agilent.com

Product specifications and descriptions in this document subject to change without notice.



Agilent Technologies