



**Agilent**  
E363xA Series  
Programmable DC Power Supplies

Data Sheet



## Reliable Power, Repeatable Results

- Single and triple output
- 80 W to 200 W output power
- Dual range output (except E3631A)
- Low noise and excellent regulation
- Remote sensing (except E3631A)
- Front and rear output terminals (E3633A/34A only)
- GPIB and RS-232 standard
- Save and recall functions
- Overvoltage protection, Overcurrent protection (except E3631A)

## Clean and stable power with programmability at an affordable price

### Affordable programmable power supplies to meet your needs

The E363xA Series of programmable DC power supplies gives you the performance of the system power supplies at a decent price. All models provide clean power, excellent regulation and a fast transient response with built-in GPIB and RS-232 interfaces. The E363xA Series is designed to meet the requirements of the most demanding applications in R&D design verifications, production testing, and QA verifications with traditional quality and reliability which you can count on.



### Excellent performance you can trust

With the 0.01% load and line regulation, the E363xA Series can maintain a steady output when power line and load changes occur. The power supplies specify both normal mode voltage/current noise and common mode current noise. The low normal mode noise specification assures clean power for precision circuitry applications, and the low common mode current provides isolation from power line current injection.

### Remote Interface

If you have an IEEE-488 card or RS-232 in a PC, these power supplies will work for you. Every model comes equipped with both GPIB and RS-232 as standard. All programming is done in easy-to-use SCPI (Standard Commands for Programmable Instruments). The user's guide describes the process for the first-time programmers.

### Front Panel Operation

A knob and self-guiding keypads allow you to set the output at your desired resolution quickly and easily. You can store and recall for up to three complete setups using the internal non-volatile memory. The output on/off button sets the output to zero.

### E3631A triple-output power supply

This famous 80-watt triple output supply offers three independent outputs: 0 to 6 V/5A, 0 to +25V/1A and 0 to -25V/1A. The 6 V output is electrically isolated from the  $\pm 25$  V supply to minimize any interference between circuits under test. The  $\pm 25$  V outputs can be set to track each other.

### E3632A/33A/34A single-output dual range power supplies

These single output power supplies give you the flexibility to select from a dual output range. The output load is protected against overvoltage and overcurrent, which are easily monitored and adjusted from the front panel and remote interface. Remote sensing is available to eliminate the errors caused by voltage drops on the load leads. The E3633A/34A offer front and rear output terminals for easy wiring.

## E3631A/32A/33A/34A Programmable DC Power Supply Specifications

| Model Number   | E3631A   |                         |                         | E3632A   | E3633A                             | E3634A                            |
|--|--|-------------------------|-------------------------|--|------------------------------------|-----------------------------------|
|  | 1  | 2                       | 3                       |  |                                    |                                   |
| <b>DC Output</b><br>Rating (0 °C to 40 °C)                                     | 0 to +6 V,<br>0 to 5 A   | 0 to +25 V,<br>0 to 1 A | 0 to -25 V,<br>0 to 1 A | 0 to 15 V/7 A or<br>0 to 30 V/4 A                          | 0 to 8 V/20 A or<br>0 to 20 V/10 A | 0 to 25 V/7 A or<br>0 to 50 V/4 A |
| <b>Load Regulation</b><br>± (% of output + offset)                             | < 0.01% + 2 mV<br>< 0.01% + 250 µA   |                         |                         |  |                                    |                                   |
| <b>Line Regulation</b><br>± (% of output + offset)                             | < 0.01% + 2 mV<br>< 0.01% + 250 µA   |                         |                         |  |                                    |                                   |
| <b>Ripple and Noise</b> (20 Hz to 20 MHz)                                      |  |                         |                         |  |                                    |                                   |
| Normal Mode Voltage  | < 350 µVrms/2 mVpp   |                         |                         | < 350 µVrms/3<br>mVpp                                      | < 500 µVrms/ 3 mVpp                |                                   |
| Normal Mode Current  | < 2 mArms  | < 500 µArms             |                         | < 2 mArms  |                                    |                                   |
| Common Mode Current  | < 1.5 µArms  |                         |                         |  |                                    |                                   |
| <b>Accuracy<sup>1</sup> 12 Months</b> (25 °C + 5 °C), ± (% output + offset)    |  |                         |                         |  |                                    |                                   |
| Programming  |  |                         |                         |  |                                    |                                   |
| Voltage  | 0.1% + 5 mV  | 0.05% + 20 mV           |                         | 0.05% + 10 mV  |                                    |                                   |
| Current  | 0.2% + 10 mA   | 0.15% + 4 mA            |                         | 0.2% + 10 mA   |                                    |                                   |
| Readback <sup>2</sup>  |  |                         |                         |  |                                    |                                   |
| Voltage  | 0.1% + 5 mV  | 0.05% + 10 mV           |                         | 0.05% + 10 mV  |                                    |                                   |
| Current  | 0.2% + 10 mA   | 0.15% + 4 mA            |                         | 0.15% + 4 mA   |                                    |                                   |
| <b>Resolution</b>  |  |                         |                         |  |                                    |                                   |
| Program  | 0.5 mV/0.5 mA  | 1.5 mV/0.1 mA           |                         | 1 mV/0.5 mA  | 1 mV/1 mA                          | 3 mV/0.5 mA                       |
| Readback   | 0.5 mV/0.5 mA  | 1.5 mV/0.1 mA           |                         | 0.5 mV/0.1 mA  | 0.5 mV/1 mA                        | 1.5 mV/0.5 mA                     |
| Meter  | 1 mV/1 mA  | 10 mV/1 mA              |                         | 1 mV/1 mA  | 1 mV/1 mA (< 10A), 10 mA (≥ 10 A)  |                                   |
| <b>Transient Response</b>  | Less than 50 µsec for output to recover to within 15 mV following a change in output current from full load to half load or vice versa |                         |                         |  |                                    |                                   |
| <b>Command Processing Time<sup>3</sup></b>                                     | < 50 msec  |                         |                         | < 100 msec   |                                    |                                   |
| <b>OVP/OCP</b>   |  |                         |                         |  |                                    |                                   |
| Accuracy<br>± (% output + offset)  | N/A  |                         |                         | 0.5% + 0.5 V/0.5% + 0.5 A                                  |                                    |                                   |
| Activation Time  | N/A  |                         |                         | 1.5 msec, OVP ≥ 3 V/< 10 msec, OVP < 3 V and OCP < 10 msec |                                    |                                   |
| <b>Temperature Coefficient per °C</b> (% output + offset)                      |  |                         |                         |  |                                    |                                   |
| Voltage  | 0.01% + 2 mV   | 0.01% + 3 mV            |                         |  |                                    |                                   |
| Current  | 0.02% + 3 mA   | 0.02% + 0.5 mA          |                         | 0.02% + 3 mA   |                                    |                                   |
| <b>Stability</b> , constant load & temperature ± (% of output + offset), 8 hrs |  |                         |                         |  |                                    |                                   |
| Voltage  | 0.03% + 1 mV   | 0.02% + 2 mV            |                         | 0.02% + 1 mV   |                                    |                                   |
| Current  | 0.1% + 3 mA  | 0.05% + 1 mA            |                         | 0.1% + 1 mA  |                                    |                                   |
| <b>Remote Sense</b> (max. voltage in each load lead)                           | N/A  |                         |                         | 1 V  | 0.7 V                              |                                   |
| <b>Voltage Programming Speed</b> , to within 1% of total excursion             |  |                         |                         |  |                                    |                                   |
| Up   | Full Load  | 11 msec                 | 50 msec                 | 50 msec  | 95 msec                            | 80 msec                           |
|  | No Load  | 10 msec                 | 20 msec                 | 20 msec  | 45 msec                            | 100 msec                          |
| Down   | Full Load  | 13 msec                 | 45 msec                 | 45 msec  | 30 msec                            | 30 msec                           |
|  | No Load  | 200 msec                | 400 msec                | 400 msec   | 450 msec                           | 450 msec                          |

<sup>1</sup> Accuracy specifications are valid after a 1-hour warm-up and calibration at 25 °C.

<sup>2</sup> Accuracy refers to readback over GPIB and RS-232 or front panel with respect to actual output.

<sup>3</sup> Maximum time for output to change after receipt of commands.

| Model Number             | E3631A   |   |   | E3632A                                       | E3633A | E3634A |
|--------------------------|--|---|---|--|--------|--------|
|                          | 1  | 2 | 3 |  |        |        |
| AC Input (47 Hz – 63 Hz) | 100 Vac ±10% (Opt 0E9)/115 Vac ±10% (Std)/230 Vac ±10% (0E3)   |   |   |  |        |        |
| Dimensions               | 213 x mm W x 133 mm H x 348 mm D<br>(8.4 x 5.2 x 13.7 in)  |   |   |  |        |        |
| Weight                   | 8.2 kg (18 lbs) net, 11 kg (24 lbs) shipping   |   |   | 9.5 kg (21 lbs) net, 12 kg (26 lbs) shipping |        |        |
| Warranty                 | One year for E363xA series power supplies<br>Three months for standard shipped accessories   |   |   |  |        |        |
| Product Regulation       | Certified to CSA 22.2 No. 231 (for E3631A), No. 1010.1 (for E3632A/33A/34A);<br>conforms to IEC 1010-1; carries CE marks; complies with CISPR-11, Group 1, Class A |   |   |  |        |        |

### Ordering Information

E3630 Series Power Supplies  
E3631A 80-Watt  
Triple Power Supply  
E3632A 120-Watt  
Single Power Supply  
E3633A/34A 200-Watt  
Single Power Supply

### Standard Shipped Accessories

User's & Service guide, Product  
Reference CD, AC power cord

### Power Options

Opt. 0E3 230 Vac ± 10%  
Opt. 0EM 115 Vac ± 10%  
Opt. 0E9 100 Vac ± 10%

### Other Options

Opt. 0L2 Extra manual sets  
Opt. 1CM Rackmount kit\*  
Opt. UK6 Commercial calibration  
with test result data  
E3600A-100 Test lead kit

### Rackmount Kits\*

Agilent E3631A/32A/33A/34A  
To rackmount two instruments side-  
by-side  
Lock-link Kit (P/N 5061-9694)  
Flange Kit (P/N 5063-9214)  
To rackmount one or two instruments  
in a sliding support shelf  
Support Shelf (P/N 5063-9256)  
Slide Kit (P/N 1494-0015) required  
for support shelf

\* Rackmounting with 1CM or  
lock-link/flange kit requires  
Agilent or customer support rails  
Agilent Support Rails-E3663AC



### Agilent Email Updates

[www.agilent.com/find/emailupdates](http://www.agilent.com/find/emailupdates)

Get the latest information on the products and applications you select.

### Remove all doubt

Our repair and calibration services will get your equipment back to you, performing like new, when promised. You will get full value out of your Agilent equipment through-out its lifetime. Your equipment will be serviced by Agilent-trained technicians using the latest factory calibration procedures, automated repair diagnostics and genuine parts. You will always have the utmost confidence in your measurements. For information regarding self maintenance of this product, please contact your Agilent office.

Agilent offers a wide range of additional expert test and measurement services for your equipment, including initial start-up assistance, onsite education and training, as well as design, system integration, and project management.

For more information on repair and calibration services, go to

[www.agilent.com/find/removealldoubt](http://www.agilent.com/find/removealldoubt)

[www.agilent.com](http://www.agilent.com)

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:

[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

#### Americas

|               |                |
|---------------|----------------|
| Canada        | (877) 894-4414 |
| Latin America | 305 269 7500   |
| United States | (800) 829-4444 |

#### Asia Pacific

|           |                |
|-----------|----------------|
| Australia | 1 800 629 485  |
| China     | 800 810 0189   |
| Hong Kong | 800 938 693    |
| India     | 1 800 112 929  |
| Japan     | 0120 (421) 345 |
| Korea     | 080 769 0800   |
| Malaysia  | 1 800 888 848  |
| Singapore | 1 800 375 8100 |
| Taiwan    | 0800 047 866   |
| Thailand  | 1 800 226 008  |

#### Europe & Middle East

|                |                       |
|----------------|-----------------------|
| Austria        | 43 (0) 1 360 277 1571 |
| Belgium        | 32 (0) 2 404 93 40    |
| Denmark        | 45 70 13 15 15        |
| Finland        | 358 (0) 10 855 2100   |
| France         | 0825 010 700*         |
|                | *0.125 €/minute       |
| Germany        | 49 (0) 7031 464 6333  |
| Ireland        | 1890 924 204          |
| Israel         | 972-3-9288-504/544    |
| Italy          | 39 02 92 60 8484      |
| Netherlands    | 31 (0) 20 547 2111    |
| Spain          | 34 (91) 631 3300      |
| Sweden         | 0200-88 22 55         |
| Switzerland    | 0800 80 53 53         |
| United Kingdom | 44 (0) 118 9276201    |

Other European Countries:

[www.agilent.com/find/contactus](http://www.agilent.com/find/contactus)

Product specifications and descriptions in this document subject to change without notice. October 1, 2009

© Agilent Technologies, Inc. 2010  
Printed in USA, April 23, 2010  
5968-9726EN



Agilent Technologies