

4

3

2

1

THIS DRAWING IS UNPUBLISHED. RELEASED FOR PUBLICATION DEC 2004.
 © COPYRIGHT 2004 BY TYCO ELECTRONICS CORPORATION. ALL RIGHTS RESERVED.

LOC	DIST	REV	DESCRIPTION	DATE	OWN	APPD
E	B	P	LTR			
		-	SEE SHEET 1			

COMPONENTS

ITEM NO	DESCRIPTION	ITEM NO	DESCRIPTION	ITEM NO	DESCRIPTION	ITEM NO	DESCRIPTION
HEX NUT (ITEM 4)	LOCK WASHER (ITEM 5)	GASKET (ITEM 6)	MAIN BODY (ITEM 1 & 2)	CENTRE CONTACT (ITEM 3)	PUSHER SLEEVE (ITEM 8)	CRIMP FERRULES (ITEM 7 & 9)	

ASSEMBLY INSTRUCTION

STEP	DESCRIPTION	DIAGRAM	RECOMMENDED DIMENSIONS
STEP 1	1. SLIDE METAL CRIMP FERRULE OVER CABLE		
STEP 2	1. STRIP CABLE TO DIMENSIONS AS SHOWN		
STEP 3	1. FIT CONTACT OVER CENTRE CONDUCTOR TO BUTT AGAINST DIELECTRIC. 2. CRIMP USING TOOL AS NOTES ON PAGE 1.		RECOMMENDED CENTRE CONTACT A/F HEX 1.75
STEP 4	1. PRESS SUB-ASSEMBLY INTO BODY, UNTIL CONTACT IS FULLY LOCATED BY AN AUDIBLE CLICK. 2. ENSURE THAT KNURLED HOUSING INSERTS BETWEEN THE DIELECTRIC AND CABLE BRAID.		RECOMMENDED CRIMP SLEEVE A/F HEX 6.50
STEP 5	1. SLIDE CRIMP FERRULE ALONG THE CABLE UNTIL IT BUTTS AGAINST THE HOUSING BODY. 2. CRIMP USING TOOL AS NOTED ON PAGE 1. 3. CRIMP DIMENSION AS SHOWN.		RECOMMENDED CRIMP SLEEVE A/F HEX 5.60

THIS DRAWING IS A CONTROLLED DOCUMENT.		DWN J SANDWELL 1100098 GJK S PARLOW 1100098 APPD F WHEELER-KING 1100098 NAME TNC REAR MOUNT BULKHEAD JACK 75 OHM APPLICATION SPEC SEE PAGE 2 WEIGHT CUSTOMER DRAWING	Tyco Electronics Tyco Electronics Corporation Bideford, UK, EX39 4HE SEE CASE CODE DRAWING NO A2 00779 © 1814803 RESTRICTED TO NTS SHEET 2 OF 2 REV A
DIMENSIONS: mm TO RANGE UNLESS OTHERWISE SPECIFIED 0 P.L.C. ± 1 P.L.C. ± 2 P.L.C. ± 3 P.L.C. ± 4 P.L.C. ± 5 P.L.C. ± 6 P.L.C. ± 7 P.L.C. ± 8 P.L.C. ± 9 P.L.C. ±	MATERIAL: SEE TABLE FINISH:	SCALE: NTS SHEET 2 OF 2 REV A	

AMP 1471-9 REV 31/MAR/00

1814803

A