

# □ MN101CB6 Series

Type	MN101CB6A	MN101CB6D	MN101CB6G	MN101CFB6G
Internal ROM type	Mask ROM			FLASH
ROM (byte)	32K	64K	124K	128K
RAM (byte)	1K	2K		
Package (Lead-free)	SSOP032-P-0300B			
Minimum Instruction Execution Time	0.10 $\mu$ s (at 2.7 V to 3.6 V, 10 MHz) 0.125 $\mu$ s (at 1.8 V to 3.6 V, 8 MHz) 100 $\mu$ s (at 1.8 V to 3.6 V, 20 kHz)			

## ■ Interrupts

RESET. Watchdog. External 0 to 4. Timer 0 to 3. Timer 7 (2 systems). Time base. Serial 0 (2 systems). A/D conversion finish

## ■ Timer Counter

8-bit timer  $\times$  5

Timer 0 .....Square-wave/8-bit PWM output. Event count. Simple pulse width measurement. Added pulse (2-bit) type PWM output. Square-wave/PWM output to large current terminal P35 possible

Timer 1 .....Serial 0 baud rate timer

Timer 2 .....Square-wave output. Added pulse (2-bit) type PWM output. PWM output. Event count. Simple pulse width measurement. Serial 0 baud rate timer. Square-wave/PWM output to large current terminal P34 possible

Timer 3 .....Interval timer

Timer 6 .....8-bit freerun timer

Timer 0, 1 can be cascade-connected

Timer 2, 3 can be cascade-connected

16-bit timer  $\times$  1

Timer 7 .....Square-wave output. 16-bit PWM output (cycle/duty continuous variable). Event count. Pulse width measurement. Input capture. Square-wave/PWM output to large current terminal P33 possible

Time base timer: One-minute count setting

Watchdog timer  $\times$  1

Watchdog timer 2  $\times$  1

## ■ Serial interface

Synchronous type/UART (full-duplex)  $\times$  1: Serial 0

## ■ I/O Pins

I/O 17: Common use. Specified pull-up resistor available. Input/output selectable (bit unit)

## ■ A/D converter

10-bit  $\times$  5 channels (with S/H)

## ■ Special Ports

High-current drive port

## ■ ROM Correction

Correcting address designation: Up to 3 addresses possible

## ■ Gain Amplifier

2 channels

## ■ Reference Power Supply Output

1.7 V: Output to REF17 terminal possible. Supply to A/D converter input, A/D converter reference voltage and a reference power for Double Booster Circuit possible

## ■ Double Booster Circuit

Can boost REF17 terminal input voltage or Reference Power Supply Output

## ■ Reset


Automatic Reset

## ■ Internal oscillation

High speed: 8 MHz. Low speed: 20 kHz

# MN101CB6A, MN101CB6D, MN101CB6G, MN101CFB6G

## ■ Pin Assignment SSOP032-P-0300B



## Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).  
Consult our sales staff in advance for information on the following applications:
  - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
  - Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.

20080805