

Flex 402

Two-Zone Fire Alarm Control Panel



Description

The Gamewell Flex 402 Fire Alarm Control Panel brings the latest in microprocessor technology to conventional fire controls. The Flex 402 is compatible with the new *i³*TM smoke detectors from System Sensor, and provides advanced features including drift compensation, maintenance alert, and freeze warning. Automatic synchronization of audio/visual devices is provided, selectable for three manufacturers' protocols. The NAC protocol includes the ability, using a single pair of wires, to silence audible devices while strobes continue to flash.

The Flex 402 is also compatible with conventional input devices such as two- and four-wire smoke detectors, pull stations, waterflow devices, tamper switches and other normally-open contact devices.

The Flex 402 is also compatible with conventional input devices such as two- and four-wire smoke detectors, pull stations, waterflow devices, tamper switches and other normally-open contact devices.

Operation

The activation of a compatible smoke detector or any normally-open fire alarm initiating device will: activate audible and visual signaling devices, illuminate an indicating LED, sound the piezo sounder at the FACP, activate the FACP alarm relay, and operate an optional module which notifies a remote station or initiates an auxiliary control function.

*i³*TM Technology Features

- Drift compensation automatically adjusts detector sensitivity and increases resistance to false alarms caused by dust accumulation.
- The maintenance alert LEDs (per zone) warn of excessive dirt accumulation, preventing false alarms.
- Detector sensitivity is automatically measured. The twice-yearly test requirements of NFPA 72 (7-3.2.1) are met without using a ladder or test meter.
- The wireless handheld sensitivity meter eliminates the need for voltmeters, magnets, or a physical connection to the detector. The reader displays sensitivity in terms of percent-per-foot obscuration and provides text status indication.
- The supervisory LED (per zone) provides a warning if a detector senses temperatures approaching freezing.
- Special test protocol and LED indication allow a quick test of all detectors — without a ladder.
- Electronic heat-sensing element provides thermal detection in addition to photoelectronic smoke detection.

Features

- Two Style B (Class B) Initiating Device Circuits (IDCs).
- One Style Y (Class B) Notification Appliance Circuit (NAC).
- 24 VDC.
- *NAC synchronization features:*
 - Provides synchronization of standard ANSI audible signals as required by NFPA 72 (3-8.4.1.2.3).
 - Provides synchronization of ADA compliant strobes per NFPA 72 (4-4.4.1).
 - Selectable for System Sensor, Wheelock, and Gentex protocols.
 - Selective Silence feature allows manual silencing of horns while strobes continue to flash on the same NAC.
- Silent or Audible Walk Test operation mode commanded from the front keypad, with automatic return to normal after one hour of inactivity.
- Alarm verification selectable per zone.
- Each zone may be programmed for supervisory or fire; each zone has separate red and yellow LEDs.
- Disable switches provided for each zone.
- *NACs programmable for:* Silence Inhibit, Auto Silence, Strobe Synchronization, Selective Silence (horn/strobe mute), Temporal or Steady signal, Silenceable or Nonsilenceable.
- Form-C Alarm and Trouble relays.
- 3.0 amps total usable current.
- Optional dress panel (P/N DP-FLEX).
- Piezo sounder for alarm, trouble, supervisory, and maintenance.
- *Control buttons:* ACK (Acknowledge), Alarm Silence, Reset, Walktest, Zone Enable/Disable (one per zone).
- *LED indicators:* Fire Alarm (one per zone), Supervisory (one per zone), Trouble (one per zone), Maintenance (one per zone), AC Power, NAC Disable, Zone Disable, NAC Fault, System Trouble, Power Trouble, Walktest, Alarm Silence, Earth Fault (on circuit board), Battery Fault (on circuit board), Charger Fault (on circuit board).

Listings

Listings and approvals below apply to the basic Flex 402 panel. In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- UL Listed: file S521.
- CSFM approved: file 7165-1288-180.
- MEA approved: file 366-04-E.

Gamewell 
A 150-Year Tradition
by Honeywell

Backbox Mounting

The cabinet can be surface-mounted. The door is removable during installation by opening and lifting it off the hinges. The cabinet mounts using two key slots at the top of the backbox and two additional 0.250" diameter holes at the bottom.

Ordering Information

F402	Two-zone conventional FACP.
BB-17F	Battery box, required to house two batteries greater than 7 AH, to a maximum of 18 AH.
DP-FLEX	Dress panel.
TR-1-R	Trim ring for semi-flush mounting.
52194	<i>Flex 402 Installation and Maintenance Manual.</i>

i³™ is a trademark and Gamewell® is a registered trademark of Honeywell International Inc.

Specifications

AC power, TB8

120 VAC, 50/60 Hz, 2.3 A.
Wire size: minimum 14 AWG (2.0 mm²) with 600 V insulation.

Battery (sealed lead-acid only), J8

Maximum charging circuit: normal flat charge 27.6 VDC @ 0.8 A.
Maximum battery charger capacity: 18 AH battery. Two 7 AH batteries can be housed in the FACP cabinet. Larger batteries require a separate battery box such as the **BB-17F**.

Initiating device circuits, TB3

Alarm zones 1&2. Power-limited circuitry.
Operation: all zones Style B (Class B).
Normal operating voltage: nominal 22 VDC. *Alarm current:* 15 mA minimum.
Standby current: 4 mA.
Short circuit current: 40 mA maximum.
Maximum loop resistance: 100 ohms.
End-of-line resistor: 4.7K ohm, 1/2 watt (P/N 71252).

Notification appliance circuits, TB2

One NAC on Flex 402. Power-limited circuitry.
Normal operating voltage: nominal 24 VDC.
Maximum signaling current: 2.5 A total with standard transform.
End-of-line resistor: 4.7K ohm, 1/2 watt (P/N 71252).

Form-C relays

Trouble relay TB5 (fail-safe). Alarm relay TB6.
Contact ratings: 2.0 A @ 30 VAC (resistive).

Auxiliary outputs

Resettable power, TB1

Power-limiting circuitry.
Operating voltage: nominal 24 VDC.
Maximum available current: 500 mA, appropriate for powering four-wire smoke detectors. *Note:* Total current for resettable power and one NAC must not exceed 3 A for the Flex 402.

Cabinet dimensions

Door: 15.342" (38.97 cm) high x 14.677" (37.28 cm) wide x 0.375" (0.95 cm) deep. *Backbox:* 15.0" (38.10 cm) high x 14.5" (36.83 cm) wide x 3.0" (7.62 cm) deep.



Gamewell-FCI
12 Clintonville Road
Northford, CT 06472-1610
Phone: 203-484-7161
Fax: 203-484-7118
www.gamewell-fci.com

A Honeywell Company
© 2006 Gamewell-FCI

Specifications and wiring information are provided for information only and are believed to be accurate. Gamewell-FCI assumes no responsibility for their use. Data and design are subject to change without notice. Installation and wiring instructions shipped with the product shall always be used for actual installation. For more information, contact Gamewell-FCI.