

# LMC6035, LMC6036

*LMC6035/LMC6036 Low Power 2.7V Single Supply CMOS Operational Amplifiers*



Literature Number: SNOS875E

# LMC6035/LMC6036

## Low Power 2.7V Single Supply CMOS Operational Amplifiers

### General Description

The LMC6035/6 is an economical, low voltage op amp capable of rail-to-rail output swing into loads of 600Ω. LMC6035 is available in a chip sized package (8-Bump micro SMD) using National's micro SMD package technology. Both allow for single supply operation and are guaranteed for 2.7V, 3V, 5V and 15V supply voltage. The 2.7 supply voltage corresponds to the End-of-Life voltage (0.9V/cell) for three NiCd or NiMH batteries in series, making the LMC6035/6 well suited for portable and rechargeable systems. It also features a well behaved decrease in its specifications at supply voltages below its guaranteed 2.7V operation. This provides a "comfort zone" for adequate operation at voltages significantly below 2.7V. Its ultra low input currents ( $I_{IN}$ ) makes it well suited for low power active filter application, because it allows the use of higher resistor values and lower capacitor values. In addition, the drive capability of the LMC6035/6 gives these op amps a broad range of applications for low voltage systems.

### Features

(Typical Unless Otherwise Noted)


- LMC6035 in micro SMD Package
- Guaranteed 2.7V, 3V, 5V and 15V Performance
- Specified for 2 kΩ and 600Ω Loads
- Wide Operating Range: 2.0V to 15.5V
- Ultra Low Input Current: 20fA
- Rail-to-Rail Output Swing
  - @ 600Ω: 200mV from either rail at 2.7V
  - @ 100kΩ: 5mV from either rail at 2.7V
- High Voltage Gain: 126dB
- Wide Input Common-Mode Voltage Range
  - 0.1V to 2.3V at  $V_S = 2.7V$
- Low Distortion: 0.01% at 10kHz
- LMC6035 Dual LMC6036 Quad
- See AN-1112 for micro SMD considerations

### Applications

- Filters
- High Impedance Buffer or Preamplifier
- Battery Powered Electronics
- Medical Instrumentation

### Connection Diagram

8-Bump microSMD



Top View  
(Bump Side Down)

### microSMD Connection Table

| Bump Number | LM6035IBP<br>LMC6035IBPX | LMC6035ITL<br>LMC6035ITLX |
|-------------|--------------------------|---------------------------|
| A1          | OUTPUT A                 | OUTPUT B                  |
| B1          | IN A <sup>-</sup>        | V <sup>+</sup>            |
| C1          | IN A <sup>+</sup>        | OUTPUT A                  |
| C2          | V <sup>-</sup>           | IN A <sup>-</sup>         |
| C3          | IN B <sup>+</sup>        | IN A <sup>+</sup>         |
| B3          | IN B <sup>-</sup>        | V <sup>-</sup>            |
| A3          | OUTPUT B                 | IN B <sup>+</sup>         |
| A2          | V <sup>+</sup>           | IN B <sup>-</sup>         |

**Absolute Maximum Ratings** (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

|                                       |                  |
|---------------------------------------|------------------|
| ESD Tolerance (Note 2)                |                  |
| Human Body Model                      | 3000V            |
| Machine Model                         | 300V             |
| Differential Input Voltage            | ± Supply Voltage |
| Supply Voltage ( $V^+ - V^-$ )        | 16V              |
| Output Short Circuit to $V^+$         | (Note 8)         |
| Output Short Circuit to $V^-$         | (Note 3)         |
| Lead Temperature (soldering, 10 sec.) | 260°C            |
| Current at Output Pin                 | ±18mA            |
| Current at Input Pin                  | ±5mA             |
| Current at Power Supply Pin           | 35mA             |
| Storage Temperature Range             | -65°C to +150°C  |

Junction Temperature (Note 4)

150°C

**Operating Ratings** (Note 1)

|                                      |                                |
|--------------------------------------|--------------------------------|
| Supply Voltage                       | 2.0V to 15.5V                  |
| Temperature Range                    |                                |
| LMC6035I and LMC6036I                | -40°C ≤ T <sub>J</sub> ≤ +85°C |
| Thermal Resistance ( $\theta_{JA}$ ) |                                |
| 8-pin MSOP                           | 230°C/W                        |
| 8-pin SOIC                           | 175°C/W                        |
| 14-pin SOIC                          | 127°C/W                        |
| 14-pin TSSOP                         | 137°C/W                        |
| 8-Bump (6 mil) micro SMD             | 220°C/W                        |
| 8-Bump (12 mil) Thin micro SMD       | 220°C/W                        |

**DC Electrical Characteristics**

Unless otherwise specified, all limits guaranteed for T<sub>J</sub> = 25°C, V<sup>+</sup> = 2.7V, V<sup>-</sup> = 0V, V<sub>CM</sub> = 1.0V, V<sub>O</sub> = 1.35V and R<sub>L</sub> > 1MΩ. **Boldface** limits apply at the temperature extremes.

| Symbol            | Parameter                             | Conditions  | LMC6035I/LMC6036I   |                 |                    | Units  |
|-------------------|---------------------------------------|---|---------------------|-----------------|--------------------|--------|
|                   |                                       |   | Min<br>(Note 6)     | Typ<br>(Note 5) | Max<br>(Note 6)    |        |
| V <sub>OS</sub>   | Input Offset Voltage                  |   |                     | 0.5             | 5<br><b>6</b>      | mV     |
| TCV <sub>OS</sub> | Input Offset Voltage Average Drift    |   |                     | 2.3             |                    | μV/°C  |
| I <sub>IN</sub>   | Input Current                         | (Note 11)   |                     | 0.02            | <b>90</b>          | pA     |
| I <sub>OS</sub>   | Input Offset Current                  | (Note 11)   |                     | 0.01            | <b>45</b>          | PA     |
| R <sub>IN</sub>   | Input Resistance                      |   |                     | > 10            |                    | Tera Ω |
| CMRR              | Common Mode Rejection Ratio           | 0.7V ≤ V <sub>CM</sub> ≤ 12.7V,<br>V <sup>+</sup> = 15V                   | 63<br><b>60</b>     | 96              |                    | dB     |
| +PSRR             | Positive Power Supply Rejection Ratio | 5V ≤ V <sup>+</sup> ≤ 15V,<br>V <sub>O</sub> = 2.5V                       | 63<br><b>60</b>     | 93              |                    | dB     |
| -PSRR             | Negative Power Supply Rejection Ratio | 0V ≤ V <sup>-</sup> ≤ -10V,<br>V <sub>O</sub> = 2.5V, V <sup>+</sup> = 5V | 74<br><b>70</b>     | 97              |                    | dB     |
| V <sub>CM</sub>   | Input Common-Mode Voltage Range       | V <sup>+</sup> = 2.7V<br>For CMRR ≥ 40dB                                  |                     | -0.1            | 0.3<br><b>0.5</b>  | V      |
|                   |                                       |   | 2.0<br><b>1.7</b>   | 2.3             |                    |        |
|                   |                                       | V <sup>+</sup> = 3V<br>For CMRR ≥ 40dB                                    |                     | -0.3            | 0.1<br><b>0.3</b>  | V      |
|                   |                                       |   | 2.3<br><b>2.0</b>   | 2.6             |                    |        |
|                   |                                       | V <sup>+</sup> = 5V<br>For CMRR ≥ 50dB                                    |                     | -0.5            | -0.2<br><b>0.0</b> | V      |
|                   |                                       |   | 4.2<br><b>3.9</b>   | 4.5             |                    |        |
|                   |                                       | V <sup>+</sup> = 15V<br>For CMRR ≥ 50dB                                   |                     | -0.5            | -0.2<br><b>0.0</b> | V      |
|                   |                                       |   | 14.0<br><b>13.7</b> | 14.4            |                    |        |

**DC Electrical Characteristics** (Continued)

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 2.7\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 1.0\text{V}$ ,  $V_O = 1.35\text{V}$  and  $R_L > 1\text{M}\Omega$ .

**Boldface** limits apply at the temperature extremes.

| Symbol | Parameter                             | Conditions   |          | LMC6035/LMC6036     |                 |                     | Units |
|--------|---------------------------------------|--|----------|---------------------|-----------------|---------------------|-------|
|        |                                       |  |          | Min<br>(Note 6)     | Typ<br>(Note 5) | Max<br>(Note 6)     |       |
| $A_V$  | Large Signal Voltage Gain<br>(Note 7) | $R_L = 600\Omega$  | Sourcing | 100<br><b>75</b>    | 1000            |                     | V/mV  |
|        |                                       |  | Sinking  | 25<br><b>20</b>     | 250             |                     | V/mV  |
|        |                                       | $R_L = 2\text{k}\Omega$  | Sourcing |                     | 2000            |                     | V/mV  |
|        |                                       |  | Sinking  |                     | 500             |                     | V/mV  |
| $V_O$  | Output Swing                          | $V^+ = 2.7\text{V}$<br>$R_L = 600\Omega$ to $1.35\text{V}$       |          | 2.0<br><b>1.8</b>   | 2.5             |                     | V     |
|        |                                       |  |          |                     | 0.2             | 0.5<br><b>0.7</b>   |       |
|        |                                       | $V^+ = 2.7\text{V}$<br>$R_L = 2\text{k}\Omega$ to $1.35\text{V}$ |          | 2.4<br><b>2.2</b>   | 2.62            |                     | V     |
|        |                                       |  |          |                     | 0.07            | 0.2<br><b>0.4</b>   |       |
|        |                                       | $V^+ = 15\text{V}$<br>$R_L = 600\Omega$ to $7.5\text{V}$         |          | 13.5<br><b>13.0</b> | 14.5            |                     | V     |
|        |                                       |  |          |                     | 0.36            | 1.25<br><b>1.50</b> |       |
|        |                                       | $V^+ = 15\text{V}$ ,<br>$R_L = 2\text{k}\Omega$ to $7.5\text{V}$ |          | 14.2<br><b>13.5</b> | 14.8            |                     | V     |
|        |                                       |  |          |                     | 0.12            | 0.4<br><b>0.5</b>   |       |
| $I_O$  | Output Current                        | $V_O = 0\text{V}$  | Sourcing | 4<br><b>3</b>       | 8               |                     | mA    |
|        |                                       | $V_O = 2.7\text{V}$  | Sinking  | 3<br><b>2</b>       | 5               |                     |       |
| $I_S$  | Supply Current                        | LMC6035 for Both Amplifiers<br>$V_O = 1.35\text{V}$              |          |                     | 0.65            | 1.6<br><b>1.9</b>   | mA    |
|        |                                       | LMC6036 for All Four Amplifiers<br>$V_O = 1.35\text{V}$          |          |                     | 1.3             | 2.7<br><b>3.0</b>   |       |

**AC Electrical Characteristics**

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 2.7\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 1.0\text{V}$ ,  $V_O = 1.35\text{V}$  and  $R_L > 1\text{M}\Omega$ .

**Boldface** limits apply at the temperature extremes.

| Symbol     | Parameter                    | Conditions  | Typ<br>(Note 5) | Units                  |
|------------|------------------------------|---|-----------------|------------------------|
| SR         | Slew Rate                    | (Note 9)  | 1.5             | V/ $\mu\text{s}$       |
| GBW        | Gain Bandwidth Product       | $V^+ = 15\text{V}$  | 1.4             | MHz                    |
| $\theta_m$ | Phase Margin                 |   | 48              | $^\circ$               |
| $G_m$      | Gain Margin                  |   | 17              | dB                     |
|            | Amp-to-Amp Isolation         | (Note 10)   | 130             | dB                     |
| $e_n$      | Input-Referred Voltage Noise | $f = 1\text{kHz}$<br>$V_{\text{CM}} = 1\text{V}$                                      | 27              | nV/ $\sqrt{\text{Hz}}$ |
| $i_n$      | Input Referred Current Noise | $f = 1\text{kHz}$   | 0.2             | fA/ $\sqrt{\text{Hz}}$ |
| THD        | Total Harmonic Distortion    | $f = 10\text{kHz}$ , $A_V = -10$<br>$R_L = 2\text{k}\Omega$ , $V_O = 8 V_{\text{PP}}$ | 0.01            | %                      |

## AC Electrical Characteristics (Continued)

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 2.7\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{CM} = 1.0\text{V}$ ,  $V_O = 1.35\text{V}$  and  $R_L > 1\text{M}\Omega$ . **Boldface** limits apply at the temperature extremes.

| Symbol | Parameter | Conditions         | Typ<br>(Note 5) | Units |
|--------|-----------|--------------------|-----------------|-------|
|        |           | $V^+ = 10\text{V}$ |                 |       |

**Note 1:** Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.

**Note 2:** Human body model,  $1.5\text{k}\Omega$  in series with  $100\text{pF}$ .

**Note 3:** Applies to both single-supply and split-supply operation. Continuous short circuit operation at elevated ambient temperature can result in exceeding the maximum allowed junction temperature of  $150^\circ\text{C}$ . Output currents in excess of  $30\text{mA}$  over long term may adversely affect reliability.

**Note 4:** The maximum power dissipation is a function of  $T_{J(\text{MAX})}$ ,  $\theta_{JA}$ , and  $T_A$ . The maximum allowable power dissipation at any ambient temperature is  $P_D = (T_{J(\text{MAX})} - T_A) / \theta_{JA}$ . All numbers apply for packages soldered directly onto a PC board with no air flow.

**Note 5:** Typical Values represent the most likely parametric norm or one sigma value.

**Note 6:** All limits are guaranteed by testing or statistical analysis.

**Note 7:**  $V^+ = 15\text{V}$ ,  $V_{CM} = 7.5\text{V}$  and  $R_L$  connected to  $7.5\text{V}$ . For Sourcing tests,  $7.5\text{V} \leq V_O \leq 11.5\text{V}$ . For Sinking tests,  $3.5\text{V} \leq V_O \leq 7.5\text{V}$ .

**Note 8:** Do not short circuit output to  $V^+$  when  $V^+$  is greater than  $13\text{V}$  or reliability will be adversely affected.

**Note 9:**  $V^+ = 15\text{V}$ . Connected as voltage follower with  $10\text{V}$  step input. Number specified is the slower of the positive and negative slew rates.

**Note 10:** Input referred,  $V^+ = 15\text{V}$  and  $R_L = 100\text{k}\Omega$  connected to  $7.5\text{V}$ . Each amp excited in turn with  $1\text{kHz}$  to produce  $V_O = 12\text{V}_{PP}$ .


**Note 11:** Guaranteed by design.

# Typical Performance Characteristics

Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$


25°C

**Supply Current vs. Supply Voltage (Per Amplifier)**




01283052

**Input Current vs. Temperature**




01283053

**Sourcing Current vs. Output Voltage**




01283054

**Sourcing Current vs. Output Voltage**




01283055

**Sinking Current vs. Output Voltage**



01283056


**Sinking Current vs. Output Voltage**



01283057


**Typical Performance Characteristics** Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)

**Output Voltage Swing vs. Supply Voltage**




01283058

**Input Noise vs. Frequency**




01283059

**Input Noise vs. Frequency**




01283060

**Amp to Amp Isolation vs. Frequency**




01283061

**Amp to Amp Isolation vs. Frequency**




01283062

**+PSRR vs. Frequency**




01283032


**Typical Performance Characteristics** Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)




01283033




01283034




01283035



01283036









01283014



01283015




**Typical Performance Characteristics** Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)



# Typical Performance Characteristics


Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)

### Non-Inverting Large Signal Response

TIME (1  $\mu s$ /div)


01283021

### Non-Inverting Large Signal Response

TIME (1  $\mu s$ /div)


01283022

### Non-Inverting Small Signal Response

TIME (1  $\mu s$ /div)


01283023

### Non-Inverting Small Signal Response

TIME (1  $\mu s$ /div)


01283024

### Non-Inverting Large Signal Response

TIME (1  $\mu s$ /div)

01283025


### Inverting Large Signal Response

TIME (1  $\mu s$ /div)

01283026


**Typical Performance Characteristics** Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)

**Inverting Large Signal Response**




01283027

**Inverting Large Signal Response**




01283028

**Inverting Small Signal Response**




01283029

**Inverting Small Signal Response**




01283030

**Inverting Small Signal Response**




01283031

**Stability vs. Capacitive Load**




01283038


**Typical Performance Characteristics** Unless otherwise specified,  $V_S = 2.7V$ , single supply,  $T_A = 25^\circ C$  (Continued)




01283039




01283040



01283041



01283042



01283043

# 1.0 Application Notes

## 1.1 Background

The LMC6035/6 is exceptionally well suited for low voltage applications. A desirable feature that the LMC6035/6 brings to low voltage applications is its output drive capability—a hallmark for National's CMOS amplifiers. The circuit of *Figure 1* illustrates the drive capability of the LMC6035/6 at 3V of supply. It is a differential output driver for a one-to-one audio transformer, like those used for isolating ground from the telephone lines. The transformer (T1) loads the op amps with about 600Ω of AC load, at 1 kHz. Capacitor C1 functions to block DC from the low winding resistance of T1. Although the value of C1 is relatively high, its load reactance ( $X_c$ ) is negligible compared to inductive reactance ( $X_l$ ) of T1.





FIGURE 1. Differential Driver

The circuit in *Figure 1* consists of one input signal and two output signals. U1A amplifies the input with an inverting gain of  $-2$ , while the U1B amplifies the input with a non-inverting gain of  $+2$ . Since the two outputs are  $180^\circ$  out of phase with each other, the gain across the differential output is 4. As the differential output swings between the supply rails, one of the op amps sources the current to the load, while the other op amp sinks the current.


How good a CMOS op amp can sink or source a current is an important factor in determining its output swing capability. The output stage of the LMC6035/6—like many op amps—sources and sinks output current through two complementary transistors in series. This “totem pole” arrangement translates to a channel resistance ( $R_{dson}$ ) at each supply rail which acts to limit the output swing. Most CMOS op amps are able to swing the outputs very close to the rails—except, however, under the difficult conditions of low supply voltage and heavy load. The LMC6035/6 exhibits exceptional output swing capability under these conditions.

The scope photos of *Figure 2* and *Figure 3* represent measurements taken directly at the output (relative to GND) of U1A, in *Figure 1*. *Figure 2* illustrates the output swing capability of the LMC6035, while *Figure 3* provides a benchmark comparison. (The benchmark op amp is another low voltage (3V) op amp manufactured by one of our reputable competitors.)



01283045

FIGURE 2. Output Swing Performance of the LMC6035 per the Circuit of *Figure 1*




01283046

FIGURE 3. Output Swing Performance of Benchmark Op Amp per the Circuit of *Figure 1*

Notice the superior drive capability of LMC6035 when compared with the benchmark measurement—even though the benchmark op amp uses twice the supply current.

Not only does the LMC6035/6 provide excellent output swing capability at low supply voltages, it also maintains high open loop gain ( $A_{VOL}$ ) with heavy loads. To illustrate this, the LMC6035 and the benchmark op amp were compared for their distortion performance in the circuit of *Figure 1*. The graph of *Figure 4* shows this comparison. The y-axis represents percent Total Harmonic Distortion (THD plus noise) across the loaded secondary of T1. The x-axis represents the input amplitude of a 1 kHz sine wave. (Note that T1 loses about 20% of the voltage to the voltage divider of  $R_L$  (600Ω) and T1's winding resistances—a performance deficiency of the transformer.)

# 1.0 Application Notes (Continued)



**FIGURE 4. THD+Noise Performance of LMC6035 and "Benchmark" per Circuit of Figure 1**


Figure 4 shows the superior distortion performance of LMC6035/6 over that of the benchmark op amp. The heavy loading of the circuit causes the  $A_{VOL}$  of the benchmark part to drop significantly which causes increased distortion.

## 1.2 APPLICATION CIRCUITS

### 1.2.1 Low-Pass Active Filter

A common application for low voltage systems would be active filters, in cordless and cellular phones for example. The ultra low input currents ( $I_{IN}$ ) of the LMC6035/6 makes it well suited for low power active filter applications, because it allows the use of higher resistor values and lower capacitor values. This reduces power consumption and space.

Figure 5 shows a low pass, active filter with a Butterworth (maximally flat) frequency response. Its topology is a Sallen and Key filter with unity gain. Note the normalized component values in parenthesis which are obtainable from standard filter design handbooks. These values provide a 1Hz cutoff frequency, but they can be easily scaled for a desired cutoff frequency ( $f_c$ ). The bold component values of Figure 5 provide a cutoff frequency of 3kHz. An example of the scaling procedure follows Figure 5.



**FIGURE 5. 2-Pole, 3kHz, Active, Sallen and Key, Lowpass Filter with Butterworth Response**

### 1.2.1.1 Low-Pass Frequency Scaling Procedure

The actual component values represented in bold of Figure 5 were obtained with the following scaling procedure:

1. First determine the frequency scaling factor (FSF) for the desired cutoff frequency. Choosing  $f_c$  at 3kHz, provides the following FSF computation:  

$$FSF = 2\pi \times 3\text{kHz (desired cutoff freq.)} = 18.84 \times 10^3$$
2. Then divide all of the normalized capacitor values by the FSF as follows:  $C1' = C_{(Normalized)}/FSF$   $C1' = 0.707/18.84 \times 10^3 = 37.93 \times 10^{-6}$   $C2' = 1.414/18.84 \times 10^3 = 75.05 \times 10^{-6}$  ( $C1'$  and  $C2'$ : prior to impedance scaling)
3. Last, choose an impedance scaling factor ( $Z$ ). This  $Z$  factor can be calculated from a standard value for  $C2$ . Then  $Z$  can be used to determine the remaining component values as follows:

$$Z = C2'/C2(\text{chosen}) = 75.05 \times 10^{-6}/6.8\text{nF} = 8.4\text{k}$$


$$C1 = C1'/Z = 37.93 \times 10^{-6}/8.4\text{k} = 4.52\text{nF}$$

(Standard capacitor value chosen for  $C1$  is **4.7nF**)  $R1 = R1(\text{normalized}) \times Z = 1\Omega \times 8.4\text{k} = 8.4\text{k}\Omega$   $R2 = R2(\text{normalized}) \times Z = 1\Omega \times 8.4\text{k} = 8.4\text{k}\Omega$

(Standard value chosen for  $R1$  and  $R2$  is **8.45kΩ**)

### 1.2.2 High Pass Active Filter

The previous low-pass filter circuit of Figure 5 converts to a high-pass active filter per Figure 6.



**FIGURE 6. 2 Pole, 300Hz, Sallen and Key, High-Pass Filter**

# 1.0 Application Notes (Continued)

## 1.2.2.1 High-Pass Frequency Scaling Procedure

Choose a standard capacitor value and scale the impedances in the circuit according to the desired cutoff frequency (300Hz) as follows:  $C = C1 = C2$   $Z = 1 \text{ Farad}/C_{(\text{chosen})} \times 2\pi \times (\text{desired cutoff freq.}) = 1 \text{ Farad}/6.8\text{nF} \times 2\pi \times 300 \text{ Hz} = 78.05\text{k}$

$R1 = Z \times R1_{(\text{normalized})} = 78.05\text{k} \times (1/0.707) = 110.4\text{k}\Omega$   
(Standard value chosen for R1 is **110kΩ**)

$R2 = Z \times R2_{(\text{normalized})} = 78.05\text{k} \times (1/1.414) = 55.2\text{k}\Omega$   
(Standard value chosen for R1 is **54.9kΩ**)

## 1.2.3 Dual Amplifier Bandpass Filter

The dual amplifier bandpass (DABP) filter features the ability to independently adjust  $f_c$  and Q. In most other bandpass topologies, the  $f_c$  and Q adjustments interact with each other. The DABP filter also offers both low sensitivity to component values and high Qs. The following application of Figure 7, provides a 1kHz center frequency and a Q of 100.




FIGURE 7. 2 Pole, 1kHz Active, Bandpass Filter

### 1.2.3.1 DABP Component Selection Procedure

Component selection for the DABP filter is performed as follows:

1. First choose a center frequency ( $f_c$ ). Figure 7 represents component values that were obtained from the following computation for a center frequency of 1kHz.  $R2 = R3 = 1/(2\pi f_c C)$  Given:  $f_c = 1\text{kHz}$  and  $C_{(\text{chosen})} = 6.8\text{nF}$   
 $R2 = R3 = 1/(2\pi \times 1\text{kHz} \times 6.8\text{nF}) = 23.4\text{k}\Omega$   
(Chosen standard value is **23.7kΩ**)
2. Then compute R1 for a desired Q ( $f_c/BW$ ) as follows:  
 $R1 = Q \times R2$ . Choosing a Q of 100,  $R1 = 100 \times 23.7\text{k}\Omega = 2.37\text{M}\Omega$ .

## 1.3 PRINTED-CIRCUIT-BOARD LAYOUT FOR HIGH-IMPEDANCE WORK

It is generally recognized that any circuit which must operate with < 1000pA of leakage current requires special layout of the PC board. If one wishes to take advantage of the ultra-low bias current of the LMC6035/6, typically < 0.04pA, it is essential to have an excellent layout. Fortunately, the techniques for obtaining low leakages are quite simple. First, the user must not ignore the surface leakage of the PC board, even though it may at times appear acceptably low. Under conditions of high humidity, dust or contamination, the surface leakage will be appreciable.

To minimize the effect of any surface leakage, lay out a ring of foil completely surrounding the LMC6035 or LMC6036 inputs and the terminals of capacitors, diodes, conductors, resistors, relay terminals, etc. connected to the op amp's inputs. See Figure 8. To have a significant effect, guard rings should be placed on both the top and bottom of the PC board. This PC foil must then be connected to a voltage which is at the same voltage as the amplifier inputs, since no leakage current can flow between two points at the same potential. For example, a PC board trace-to-pad resistance of  $10^{12}\Omega$ , which is normally considered a very large resistance, could leak 5pA if the trace were a 5V bus adjacent to the pad of an input. This would cause a 100 times degradation from the amplifiers actual performance. However, if a guard ring is held within 5mV of the inputs, then even a resistance of  $10^{11}\Omega$  would cause only 0.05pA of leakage current, or perhaps a minor (2:1) degradation of the amplifier's performance. See Figure 9a, b, c for typical connections of guard rings for standard op amp configurations. If both inputs are active and at high impedance, the guard can be tied to ground and still provide some protection; see Figure 9 d.




FIGURE 8. Example, using the LMC6036 of Guard Ring in P.C. Board Layout

## 1.0 Application Notes (Continued)




FIGURE 9. Guard Ring Connections

### 1.3.1 CAPACITIVE LOAD TOLERANCE

Like many other op amps, the LMC6035/6 may oscillate when its applied load appears capacitive. The threshold of oscillation varies both with load and circuit gain. The configuration most sensitive to oscillation is a unity-gain follower. See the Typical Performance Characteristics.

The load capacitance interacts with the op amp's output resistance to create an additional pole. If this pole frequency is sufficiently low, it will degrade the op amp's phase margin so that the amplifier is no longer stable at low gains. As shown in *Figure 10*, the addition of a small resistor ( $50\Omega$ – $100\Omega$ ) in series with the op amp's output, and a capacitor ( $5\text{pF}$ – $10\text{pF}$ ) from inverting input to output pins, returns the phase margin to a safe value without interfering with lower-frequency circuit operation. Thus, larger values of capacitance can be tolerated without oscillation. Note that in all cases, the output will ring heavily when the load capacitance is near the threshold for oscillation.

### 1.4 Micro SMD Considerations

Contrary to what might be guessed, the micro SMD package does not follow the trend of smaller packages having higher thermal resistance. LMC6035 in micro SMD has thermal resistance of  $220^\circ\text{C/W}$  compared to  $230^\circ\text{C/W}$  in MSOP. Even when driving a  $600\Omega$  load and operating from  $\pm 7.5\text{V}$  sup-

plies, the maximum temperature rise will be under  $4.5^\circ\text{C}$ . For application information specific to micro SMD, see Application note AN-1112.




FIGURE 10.  $R_x$ ,  $C_x$  Improve Capacitive Load Tolerance

Capacitive load driving capability is enhanced by using a pull up resistor to  $V^+$  (*Figure 11*). Typically a pull up resistor conducting  $500\mu\text{A}$  or more will significantly improve capacitive load responses. The value of the pull up resistor must be determined based on the current sinking capability of the amplifier with respect to the desired output swing. Open loop gain of the amplifier can also be affected by the pull up resistor (see Electrical Characteristics).



# 1.0 Application Notes (Continued)






FIGURE 11. Compensating for Large Capacitive Loads with a Pull Up Resistor

## Connection Diagrams






## Ordering Information





| Package                                  | Temperature Range            | Transport Media          | NSC Drawing |
|--|------------------------------|--------------------------|-------------|
|  | Industrial<br>-40°C to +85°C |                          |             |
| 8-pin Small Outline (SO)                 | LMC6035IM                    | Rails                    | M08A        |
|  | LMC6035IMX                   | 2.5k Units Tape and Reel |             |
| 8-pin Mini Small Outline (MSOP)          | LMC6035IMM                   | 1k Units Tape and Reel   | MUA08A      |
|  | LMC6035IMMX                  | 3.5k Units Tape and Reel |             |
| 14-pin Small Outline (SO)                | LMC6036IM                    | Rails                    | M14A        |
|  | LMC6036IMX                   | 2.5k Units Tape and Reel |             |
| 14-pin Thin Shrink Small Outline (TSSOP) | LMC6036IMT                   | Rails                    | MTC14       |
|  | LMC6036IMTX                  | 2.5k Units Tape and Reel |             |
| 8-Bump micro SMD (Small Bump)            | LMC6035IBP                   | 250 Units Tape and Reel  | BPA08FFB    |
|  | LMC6035IBPX                  | 3k Units Tape and Reel   |             |
| 8-Bump Thin micro SMD (Large Bump)       | LMC6035ITL                   | 250 Units Tape and Reel  | TLA08JQA    |
|  | LMC6035ITLX                  | 3k Units Tape and Reel   |             |

**Physical Dimensions** inches (millimeters)

unless otherwise noted






**8-Lead (0.150" Wide) Molded Small Outline Package, JEDEC NS Package Number M08A**








**8-Lead (0.150" Wide) Molded Mini Small Outline Package, JEDEC NS Package Number MUA08A**

**Physical Dimensions** inches (millimeters) unless otherwise noted (Continued)




**14-Lead (0.150" Wide) Molded Small Outline Package, JEDEC NS Package Number M14A**



DIMENSIONS ARE IN MILLIMETERS




**14-Pin TSSOP NS Package Number MTC14**

**Physical Dimensions** inches (millimeters) unless otherwise noted (Continued)



DIMENSIONS ARE IN MILLIMETERS

**LAND PATTERN RECOMMENDATION**




BPA08XXX (Rev C)

NOTE: UNLESS OTHERWISE SPECIFIED.


1. EPOXY COATING.
2. 63Sn/37Pb EUTECTIC BUMP.
3. RECOMMEND NON-SOLDER MASK DEFINED LANDING PAD.
4. PIN A1 IS ESTABLISHED BY LOWER LEFT CORNER WITH RESPECT TO TEXT ORIENTATION PINS ARE NUMBERED COUNTERCLOCKWISE.
5. XXX IN DRAWING NUMBER REPRESENTS PACKAGE SIZE VARIATION WHERE X1 IS PACKAGE WIDTH, X2 IS PACKAGE LENGTH AND X3 IS PACKAGE HEIGHT.
6. REFERENCE JEDEC REGISTRATION MO-211, VARIATION BC.

**8-Bump micro SMD (6 mil bumps)**  
**NS Package Number BPA08FFB**  
**X<sub>1</sub> = 1.412mm X<sub>2</sub> = 1.412mm X<sub>3</sub> = 0.850mm**



**Physical Dimensions** inches (millimeters) unless otherwise noted (Continued)



**LAND PATTERN RECOMMENDATION**



**DIMENSIONS ARE IN MILLIMETERS**



TLA08XXX (Rev A)

NOTE: UNLESS OTHERWISE SPECIFIED.

1. EPOXY COATING.
2. 63Sn/37Pb EUTECTIC BUMP.
3. RECOMMEND NON-SOLDER MASK DEFINED LANDING PAD.
4. PIN A1 IS ESTABLISHED BY LOWER LEFT CORNER WITH RESPECT TO TEXT ORIENTATION PINS ARE NUMBERED COUNTERCLOCKWISE.
5. XXX IN DRAWING NUMBER REPRESENTS PACKAGE SIZE VARIATION WHERE X1 IS PACKAGE WIDTH, X2 IS PACKAGE LENGTH AND X3 IS PACKAGE HEIGHT.
6. REFERENCE JEDEC REGISTRATION MO-211, VARIATION BC.

**8-Bump Thin micro SMD (12 mil bumps)  
NS Package Number TLA08JQA  
X<sub>1</sub> = 1.717mm X<sub>2</sub> = 1.869mm X<sub>3</sub> = 0.600mm**

**LIFE SUPPORT POLICY**

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

**National Semiconductor Corporation**  
Americas  
Email: support@nsc.com

www.national.com

**National Semiconductor Europe**  
Fax: +49 (0) 180-530 85 86  
Email: europe.support@nsc.com  
Deutsch Tel: +49 (0) 69 9508 6208  
English Tel: +44 (0) 870 24 0 2171  
Français Tel: +33 (0) 1 41 91 8790

**National Semiconductor Asia Pacific Customer Response Group**  
Tel: 65-2544466  
Fax: 65-2504466  
Email: ap.support@nsc.com

**National Semiconductor Japan Ltd.**  
Tel: 81-3-5639-7560  
Fax: 81-3-5639-7507

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

### Products

|                        |  |
|------------------------|--|
| Audio                  | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers             | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters        | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products          | <a href="http://www.dlp.com">www.dlp.com</a>   |
| DSP                    | <a href="http://dsp.ti.com">dsp.ti.com</a>   |
| Clocks and Timers      | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface              | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                  | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt             | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers       | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                   | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Mobile Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity  | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |  |
|-------------------------------|--|
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Transportation and Automotive | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

TI E2E Community Home Page

[e2e.ti.com](http://e2e.ti.com)

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2011, Texas Instruments Incorporated