

Product Brief

Intel® Pentium® M Processor (90nm) with Intel® 3100 Chipset Development Kit

Embedded Computing



Intel® Pentium® M Processor (90nm) with Intel® 3100 Chipset Development Kit

Product Overview

The Intel® Pentium® M Processor (90nm) with Intel® 3100 Chipset Development Kit is an excellent platform for a variety of embedded and communications infrastructure applications. The platform enables outstanding instruction execution/watt while providing scalability with Intel® Celeron® M and Intel® Pentium® M processors on 90-nanometer (nm) process. The Intel® 3100 chipset combines server-class memory and I/O controller functions into a single component, creating the first integrated Intel® chipset specifically optimized for embedded, communications and storage applications. When combined with Intel® processors, the chipset addresses developers' needs for high-performance, high-reliability, low-power designs within small form factors such as PrAMC, CompactPCI*, and COMExpress*.

The Intel 3100 chipset integrates PCI Express* serial I/O technology and DDR2 memory technology to increase I/O bandwidth and reduce system latency for data-intensive applications. The 400 MHz front-side bus provides support for Intel Pentium M and Celeron M processors, as well as an upgrade path¹ to future use with next-generation Intel® dual-core processors. The chipset includes a four-channel Enhanced Direct Memory Access (EDMA) controller, providing low-latency, high-throughput data transfer capability with no CPU intervention for higher overall system performance. It also integrates I/O controller features such as Serial ATA, PCI and USB, saving board real estate and power by removing the need for a separate, legacy I/O bridge chip.

This and other development kits from Intel provide a fully working system with a range of performance options that can be modified or used immediately for product development. They also provide a validated board platform for software vendors to test BIOS and operating system software.



Product Highlights

Development Board

- Support for the following processors:
 - Intel Pentium M processor 745^A (1.8 GHz) 2 MB L2 Cache
 - Intel Pentium M processor Low Voltage 738^A (1.4 GHz) 2 MB L2 Cache
 - Intel Celeron M processor Ultra Low Voltage 373^A (1.0 GHz) 512 KB L2 Cache
 - Intel Celeron M processor 370^A (1.5 GHz) 1 MB L2 Cache
- 400 MHz front-side bus
- Support for integrated Intel 3100 chipset
- DDR2-400 MHz registered ECC for up to 4 GB of system memory
- One on-board PCI ATI RAGE Mobility* video chip (if on-board chip is not present, will include a video card kit)
- LPC bus Super I/O controller
- Support for USB 2.0 devices
- Four USB ports; UHCI or EHCI configurations

Product Highlights (continued)

- Two serial ports
- One parallel port
- Total of six SATA interfaces (six utilized in AHCI mode; four utilized in enhanced IDE mode)
- One floppy drive interface
- PS/2 keyboard and mouse ports
- Intel® BIOS support for Advanced Configuration and Power Interface (ACPI), plug and play, SMBIOS and Intel® Active Management Technology (Intel® AMT)
- Three PCI Express x4 bus add-in card connectors
- One PCI 32/33 bus add-in card connector, Specification 2.3
- Graphics card (Sapphire PCI using ATI Radeon® 7000 device with 64 MB memory)
- Dual-port PCI Express Gigabit network interface card
- Drivers CD
- One ATX 12V 450W power supply
- Pre-installed jumpers
- Cable set
- Firmware hub, socketed and flashed with the BIOS

Included in the Kit

- Intel 3100 chipset-based development board
- Intel Pentium M processor 745 (1.8 GHz) 2 MB L2 Cache
- CPU heat sink
- Two DDR2-400 MHz DIMM 1 GB registered ECC memory sticks

Software Overview

In order to provide customers with a complete development environment in the development kit, Intel works to help enable the platform to support customer applications and operating systems. Any software/firmware provided in the kit is subject to change without notice. For the most recent updates, please refer to the Web site for embedded Intel® architecture development kits at developer.intel.com/design/intarch/devkits/index.htm.

Ordering Information

IPDPM3100DEVKIT

¹ Not a scalable transition

⁴ Intel processor numbers are not a measure of performance. Processor numbers differentiate features within each processor family, not across different processor families. See http://www.intel.com/products/processor_number for details.

Intel Access

Embedded Intel® Architecture Home Page:	intel.com/design/intarch
Developer's Site:	developer.intel.com
Intel in Communications:	intel.com/communications
General Information Hotline:	(800) 628-8686 or (916) 356-3104 5 a.m. to 5 p.m. PST
Intel® Literature Center:	(800) 548-4725 7 a.m. to 7 p.m. CST (U.S. and Canada) <i>International locations please contact your local sales office.</i>

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH INTEL® PRODUCTS. EXCEPT AS PROVIDED IN INTEL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, INTEL ASSUMES NO LIABILITY WHATSOEVER, AND INTEL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY RELATING TO SALE AND/OR USE OF INTEL PRODUCTS, INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT, OR OTHER INTELLECTUAL PROPERTY RIGHT. INTEL MAY MAKE CHANGES TO SPECIFICATIONS, PRODUCT DESCRIPTIONS, AND PLANS AT ANY TIME, WITHOUT NOTICE.

Intel Corporation may have patents or pending patent applications, trademarks, copyrights, or other intellectual property rights that relate to the presented subject matter. The furnishing of documents and other materials and information does not provide any license, express or implied, by estoppel or otherwise, to any such patents, trademarks, copyrights, or other intellectual property rights. Intel products are not intended for use in medical, life saving, life sustaining, critical control or safety systems, or in nuclear facility applications. The Intel® Pentium® M Processor (90nm) with Intel® 3100 Chipset Development Kit may contain design defects or errors known as errata, which may cause the product to deviate from published specifications. Current characterized errata are available upon request.

*Other names and brands may be claimed as the property of others.

Intel, the Intel logo, Intel. Leap ahead, Intel. Leap ahead. logo, Pentium, and Celeron are trademarks or registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

Copyright © 2006 Intel Corporation. All rights reserved.

Printed in USA

0506/KSC/OCG/PP/300

 Please Recycle

313145-001US

