



Data Sheet

VI-200, VE-200

DC-DC Converters

50 to 200 Watts



Features

- RoHS compliant (VE-200)
- Up to 50 W/in³
- cULus, cTUVus
- Up to 90% efficiency
- Size: 4.6" x 2.4" x 0.5" (116,8 x 61,0 x 12,7mm)
- Remote sense and current limit
- OVP, thermal shutdown
- Logic disable
- Wide range output adjust
- Compatible power booster modules
- ZCS power architecture
- Low noise FM control
- CE Marked

Product Highlights

The VI-200 family, with over 12 million units shipped, is Vicor's broad series of "zero-current-switching" component-level DC-DC converters.

Operating at frequencies up to 2 MHz, VI-200 family converters offer exceptional power density, efficiency, noise performance, reliability and ease of use. Booster modules (VI-Bxx) provide a simple, cost-effective, off-the-shelf solution for higher power output requirements. One or more boosters may be used to create synchronous arrays capable of supplying several kilowatts of output power.

The flexibility of Vicor's power components is also available in half-size, half-power VI-J00 MiniMods.

Packaging Options

SlimMods™, high power density, flangeless devices and FinMods™, featuring integral finned heatsinks.

SlimMod: Option suffix: - S

Example: VI - 2XX - XX - S

FinMod: Option suffix: - F1, - F2, -F3 or -F4

Examples:

VI - 2XX - XX -F1, 0.25" fins, longitudinal

VI - 2XX - XX -F2, 0.50" fins, longitudinal

VI - 2XX - XX -F3, 0.25" fins, transverse

VI - 2XX - XX -F4, 0.50" fins, transverse

BusMod: Option suffix: -B1

MegaMod: VI - LXX - XX

Converter Selection Chart



[a] E for RoHS compliant

Input Voltage

| Nominal | Input Range Full Power | Max Power [b] | Low Line 75% Max Power | Transient [c] |
|---------------|------------------------|---------------|------------------------|---------------|
| 0 = 12 V | 10 – 20 V | (1) | n/a | 22 V |
| V = 24 V | 10 – 36 V | (7) | n/a | n/a |
| 1 = 24 V | 21 – 32 V | (4) | 18 | 36 V |
| W = 24 V | 18 – 36 V | (2) | n/a | n/a |
| 2 = 36 V | 21 – 56 V | (3) | 18 | 60 V |
| 3 = 48 V | 42 – 60 V | (4) | 36 | 72 V |
| N = 48 V | 36 – 76 V | (4) | n/a | n/a |
| 4 = 72 V | 55 – 100 V | (4) | 45 | 110 V |
| T = 110 V | 66 – 160 V | (2) | n/a | n/a |
| 5 = 150 V | 100 – 200 V | (5) | 85 | 215 V |
| 6 = 300 V | 200 – 400 V | (4) | 170 | 425 V |
| 7 = 150/300 V | 100 – 375 V | (6) | 90 | n/a |

| [b] Maximum Power | 5 V Outputs | >5 V Outputs | <5 V Outputs |
|-------------------|-------------|--------------|--------------|
| (1) | 75 W | 75 W | 15 A |
| (2) | 150 W | 150 W | 30 A |
| (3) | 100 W | 100 W | 20 A |
| (4) | 200 W | 200 W | 40 A |
| (5) | 150 W | 200 W | 40 A |
| (6) | 75 W | 100 W | 20 A |
| (7) | 50 W | 75 W [d] | 15 A |

[c] Transient voltage for 1 second.

[d] X, V, and T outputs are 50 W max.

Output Voltage

| | |
|------------|------------|
| Z = 2.0 V | 2 = 15 V |
| Y = 3.3 V | N = 18.5 V |
| 0 = 5.0 V | 3 = 24 V |
| X = 5.2 V | L = 28 V |
| W = 5.5 V | J = 36 V |
| V = 5.8 V | K = 40 V |
| T = 6.5 V | 4 = 48 V |
| R = 7.5 V | H = 52 V |
| M = 10 V | F = 72 V |
| 1 = 12 V | D = 85 V |
| P = 13.8 V | B = 95 V |

Product Grade Temperatures (°C)

| Operating | Storage |
|----------------|-----------------|
| E = -10 to +85 | E = -20 to +100 |
| C = -25 to +85 | C = -40 to +100 |
| I = -40 to +85 | I = -55 to +100 |
| M = -55 to +85 | M = -65 to +100 |

Overtemperature shutdown 95°C typical (recycle power to restart)

Output Power/Current Vout

| ≥ 5 V | < 5 V |
|-----------|----------|
| Y = 50 W | Y = 10 A |
| X = 75 W | X = 15 A |
| W = 100 W | W = 20 A |
| V = 150 W | V = 30 A |
| U = 200 W | U = 40 A |

For additional output power use "Boosters".
Change (VI-2xx-xx) to (VI-Bxx-xx)

CONVERTER SPECIFICATIONS

(typical at $T_{BP} = 25^{\circ}\text{C}$, nominal line and 75% load, unless otherwise specified)

INPUT SPECIFICATIONS

| Parameter | VI-200 E-Grade | | | VI-200 C-, I-, M-Grade | | | Units | Test Conditions |
|-------------------------------------|----------------|---|-----|---|----------------------|-----|----------|-------------------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Inrush charge | | 120×10^{-6} | | 120×10^{-6} | 200×10^{-6} | | Coulombs | Nominal line |
| Input reflected ripple current – pp | | 10% | | 10% | | | I_{IN} | Nominal line, full load |
| Input ripple rejection | | $25 + 20 \text{Log}\left(\frac{V_{in}}{V_{out}}\right)$ | | $30 + 20 \text{Log}\left(\frac{V_{in}}{V_{out}}\right)$ | | | dB | 120 Hz, nominal line |
| | | | | $20 + 20 \text{Log}\left(\frac{V_{in}}{V_{out}}\right)$ | | | | 2400 Hz, nominal line |
| No load power dissipation | | 1.35 | 2 | 1.35 | 2 | | Watts | |

OUTPUT CHARACTERISTICS

| Parameter | VI-200 E-Grade | | | VI-200 C-, I-, M-Grade | | | Units | Test Conditions |
|--------------------------------------|----------------|---------------------|------------|------------------------|---------------------|------|------------------------|----------------------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Setpoint accuracy | | 1% | 2% | 0.5% | 1% | | V_{NOM} | |
| Load/line regulation | | | 0.5% | 0.05% | 0.2% | | V_{NOM} | LL to HL, 10% to Full Load |
| Load/line regulation | | | 1% | 0.2% | 0.5% | | V_{NOM} | LL to HL, No Load to 10% |
| Output temperature drift | | 0.02 | | 0.01 | 0.02 | | % / $^{\circ}\text{C}$ | Over rated temp. |
| Long term drift | | 0.02 | | 0.02 | | | %/1K hours | |
| Output ripple – pp: | | | 150 | 60 | 100 | | mV | 20 MHz bandwidth |
| | | | 2 V, 3.3 V | | | | V_{NOM} | 20 MHz bandwidth |
| | | | 5 V | | | | V_{NOM} | 20 MHz bandwidth |
| | | | 3% | 0.75% | 1.5% | | V_{NOM} | 20 MHz bandwidth |
| Trim range ^[a] | 50% | | 110% | 50% | 110% | | V_{NOM} | |
| Total remote sense compensation | 0.5 | | | 0.5 | | | Volts | 0.25 V max. neg. leg |
| OVP set point | | 125% ^[b] | | 115% | 125% ^[b] | 135% | V_{NOM} | Recycle power |
| Current limit | 105% | | 135% | 105% | | 125% | I_{NOM} | Automatic restart |
| Short circuit current ^[c] | 20% | | 140% | 20% | | 130% | I_{NOM} | |

^[a] 10 V, 12 V, 15 V outputs, and V input range (10 – 36 V) standard trim range $\pm 10\%$. Consult factory for wider trim range.
3.3 V output trim range 2.20 to 3.63 V, 95 V output $-50 + 0\%$ trim range.

^[b] 131% nominal for booster modules.

^[c] Output voltages of 3.3 V or 5 V incorporate foldback current limiting; all other outputs provide constant current limiting.

CONTROL PIN SPECIFICATIONS

| Parameter | VI-200 E-Grade | | | VI-200 C-, I-, M-Grade | | | Units | Test Conditions |
|------------------------------|----------------|------|------|------------------------|-----|------|-------|--------------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Gate out impedance | | 50 | | 50 | | | Ohms | |
| Gate in impedance | | 1000 | | 1000 | | | Ohms | |
| Gate in open circuit voltage | | 6 | | 6 | | | Volts | Use open collector |
| Gate in low threshold | 0.65 | | | 0.65 | | | Volts | |
| Gate in low current | | | 6 | | | 6 | mA | |
| Power sharing accuracy | 0.95 | | 1.05 | 0.95 | | 1.05 | | |

CONVERTER SPECIFICATIONS (cont.)

■ DIELECTRIC WITHSTAND CHARACTERISTICS

| Parameter | VI-200 E-Grade | | | VI-200 C-, I-, M-Grade | | | Units | Test Conditions |
|---------------------|----------------|-----|-----|------------------------|-----|-----|------------------|-------------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Input to output | 3,000 | | | 3,000 | | | V _{RMS} | Baseplate earthed |
| Output to baseplate | 500 | | | 500 | | | V _{RMS} | |
| Input to baseplate | 1,500 | | | 1,500 | | | V _{RMS} | |

■ THERMAL CHARACTERISTICS

| Parameter | VI-200 E-Grade | | | VI-200 C-, I-, M-Grade | | | Units | Test Conditions |
|---|----------------|----------|-----|------------------------|----------|-----|---------|-----------------------------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Efficiency | | 78 – 88% | | | 80 – 90% | | | |
| Baseplate to sink thermal impedance | | 0.07 | | | 0.07 | | °C/Watt | With Vicor P/N 20266 |
| Thermal shutdown ^[d] (Drivers only) | 90 | 95 | 105 | 90 | 95 | 105 | °C | Cool and recycle power to restart |

^[d] No overtemp protection in booster modules.

■ MECHANICAL SPECIFICATIONS

| Parameter | VI-200 E-, C-Grade | | | VI-200 I-, M-Grade | | | Units | Test Conditions |
|-----------|--------------------|--------------|--------------|--------------------|--------------|--------------|-------------------|-----------------|
| | Min | Typ | Max | Min | Typ | Max | | |
| Weight | 6.2 (176) | 6.3 (178) | 6.4 (181) | 7.2 (205) | 7.3 (208) | 7.4 (210) | Ounces (Grams) | |

MECHANICAL DRAWING



Warranty

Vicor products are guaranteed for two years from date of shipment against defects in material or workmanship when in normal use and service. This warranty does not extend to products subjected to misuse, accident, or improper application or maintenance. Vicor shall not be liable for collateral or consequential damage. This warranty is extended to the original purchaser only.

EXCEPT FOR THE FOREGOING EXPRESS WARRANTY, VICOR MAKES NO WARRANTY, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

Vicor will repair or replace defective products in accordance with its own best judgement. For service under this warranty, the buyer must contact Vicor to obtain a Return Material Authorization (RMA) number and shipping instructions. Products returned without prior authorization will be returned to the buyer. The buyer will pay all charges incurred in returning the product to the factory. Vicor will pay all reshipment charges if the product was defective within the terms of this warranty.

Information published by Vicor has been carefully checked and is believed to be accurate; however, no responsibility is assumed for inaccuracies. Vicor reserves the right to make changes to any products without further notice to improve reliability, function, or design. Vicor does not assume any liability arising out of the application or use of any product or circuit; neither does it convey any license under its patent rights nor the rights of others. Vicor general policy does not recommend the use of its components in life support applications wherein a failure or malfunction may directly threaten life or injury. Per Vicor Terms and Conditions of Sale, the user of Vicor components in life support applications assumes all risks of such use and indemnifies Vicor against all damages.

Vicor's comprehensive line of power solutions includes high density AC-DC and DC-DC modules and accessory components, fully configurable AC-DC and DC-DC power supplies, and complete custom power systems.

Information furnished by Vicor is believed to be accurate and reliable. However, no responsibility is assumed by Vicor for its use. Vicor components are not designed to be used in applications, such as life support systems, wherein a failure or malfunction could result in injury or death. All sales are subject to Vicor's Terms and Conditions of Sale, which are available upon request.

Specifications are subject to change without notice.

Intellectual Property Notice

Vicor and its subsidiaries own Intellectual Property (including issued U.S. and Foreign Patents and pending patent applications) relating to the products described in this data sheet. Interested parties should contact Vicor's Intellectual Property Department.

Vicor Corporation
25 Frontage Road
Andover, MA, USA 01810
Tel: 800-735-6200
Fax: 978-475-6715

email

Customer Service: custserv@vicorpower.com
Technical Support: apps@vicorpower.com