

SERIAL DIGITAL AUDIO PASSIVE SIGNAL SPLITTER

AS400M

The AS400M Serial Digital Audio Passive Signal Splitter answers a demand from systems engineers for an economical way of dividing a single serial digital audio signal between two destinations. The modules are designed for in line use and, having no powered components, are as simple to use as a T-piece. A modest signal loss is incurred from the use of these modules, but they can be used freely on all medium and short cable runs.

<i>Input & Output Signal Format</i>	AES/EBU digital audio
<i>Number of Inputs</i>	1
<i>Number of Outputs</i>	2
<i>Insertion Loss at 1 MHz</i>	< 3.2 dB
<i>Impedance</i>	110 ohms*
<i>Temperature Range</i>	0°C to 70°C
<i>Aqueous Washable</i>	No
<i>Package</i>	DR00221B

*Note that for best impedance matching the impedance of the input and both outputs must be equal. If, for any reason, only one of the outputs is used the unused output must be properly terminated.

PACKAGE DETAIL

