

**FUJITSU****VOLTAGE  
REGULATOR****MB3752**February 1988  
Edition 1.0**VOLTAGE REGULATOR**

The Fujitsu MB3752 is a monolithic voltage regulator IC. It contains a temperature compensated reference voltage circuit, a surge protected error amplifier and high current protected circuit.



High current regulator, negative power supply regulator, floating regulator and switching regulator are made up by selection of external components.

Constant current limiting or foldback current limiting is selected by selection of external components.

It is suitable both industrial and consumer voltage regulator system.

The high performance makes a lot of application and enables operation with various functions.

- High Load Regulation: 0.03 % ( $1 \text{ mA} \leq I_L \leq 50 \text{ mA}$ )
- Wide Input Voltage Range: 40 V max.
- Wide Output Voltage Range: 2 V to 37 V
- Compatible with Fairchild  $\mu\text{A723}$
- Packages
  - 14-pin plastic DIP package (Suffix: -P)
  - 14-pin ceramic DIP package (Suffix: -Z)
  - 14-pin plastic Flat package (Suffix: -PF)

**4****PIN ASSIGNMENT****ABSOLUTE MAXIMUM RATINGS (see NOTE) ( $T_A = 25^\circ\text{C}$ )**

Rating	Symbol	Value			Unit
		Ceramic	Plastic	Flat	
Storage Temperature	$T_{STG}$	-65 ~ +150	-55 ~ +125	-55 ~ +125	°C
Operating Temperature	$T_A$	-55 ~ +125	-20 ~ +75	-20 ~ +75	°C
Power Dissipation	$P_D$	1000	800	620 *	mW
Output Current	$I_L$	150	150	150	mA
Zener Current	$I_Z$	25	25	25	mA
Current from $V_{REF}$	$I_R$	15	15	15	mA
Input Voltage	$V_{IN}$	40	40	40	V

NOTE: FLAT package is mounted on the epoxy board. (4cm x 4cm x 1.5mm)

Permanent device damage may occur if the above Absolute Maximum Ratings are exceeded. Functional operation should be restricted to the conditions as detailed in the operational sections of this data sheet. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.


This device contains circuitry to protect the inputs against damage due to high static voltages or electric fields. However, it is advised that normal precautions be taken to avoid application of any voltage higher than maximum rated voltages to this high impedance circuit.

**FUJITSU**

**MB3752**

**4**

**Fig. 1 — MB3752 EQUIVALENT CIRCUIT**



**4-4**

## RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	Value	Unit
Input Voltage	V <sub>IN</sub>	9.5 to 40	V
Load Current	I <sub>L</sub>	1 to 50	mA
Operating Temperature	T <sub>A</sub>	-20 to 75	°C

## 4

### ELECTRICAL CHARACTERISTICS

(V<sub>IN</sub> = 12 V, I<sub>L</sub> = 1 mA, R<sub>SC</sub> = 0, V<sub>O</sub> = 5 V, T<sub>A</sub> = 25°C)


Parameter	Symbol	Condition	Value			Unit
			Min	Typ	Max	
Input Voltage	V <sub>IN</sub>		9.5		40	V
Output Voltage	V <sub>O</sub>		2.0		37	V
Input-to-output Voltage Differential	V <sub>IN</sub> -V <sub>O</sub>		3.0		38	V
Bias Current	I <sub>B</sub>	I <sub>L</sub> = 0, V <sub>IN</sub> = 30 V			4.0	mA
Reference Voltage	V <sub>R</sub>		6.80	7.15	7.50	V
Input Regulation 1	R <sub>IN1</sub>	12 V ≤ V <sub>IN</sub> ≤ 15 V		0.01	0.1	%
Input Regulation 2	R <sub>IN2</sub>	12 V ≤ V <sub>IN</sub> ≤ 40 V		0.1	0.5	%
Input Regulation 3	R <sub>IN3</sub>	12 V ≤ V <sub>IN</sub> ≤ 15 V, 0°C ≤ T <sub>A</sub> ≤ 70°C			0.3	%
Load Regulation 1	R <sub>LD1</sub>	1 mA ≤ I <sub>L</sub> ≤ 50 mA		0.03	0.2	%
Load Regulation 2	R <sub>LD2</sub>	1 mA ≤ I <sub>L</sub> ≤ 50 mA, 0°C ≤ T <sub>A</sub> ≤ 70°C			0.6	%
Temperature Regulation	R <sub>T</sub>	0°C ≤ T <sub>A</sub> ≤ 70°C		0.2	1.0	%
Ripple Rejection Ratio	R.R.	f = 50 Hz to 10 kHz, CR = 0		74		dB
		f = 50 Hz to 10 kHz, CR = 5 μF		86		dB
Short Circuit Output Current	I <sub>SC</sub>	V <sub>O</sub> = 0, R <sub>SC</sub> = 10 Ω	60	70	80	mA

FUJITSU

MB3752

4

Fig. 2 — MEASUREMENT CIRCUIT



I)  $2 \text{ V} \leq V_o \leq V_R \quad V_o = V_R \frac{R_4}{R_3 + R_4}, \quad R_1 = \frac{R_3 \cdot R_4}{R_3 + R_4}, \quad R_2 = \infty, \quad R_3 + R_4 \leq 7 \text{ k}\Omega$

II)  $V_R \leq V_o \leq 37 \text{ V} \quad V_o = V_R \left( 1 + \frac{R_1}{R_2} \right), \quad R_3 = \frac{R_1 \cdot R_2}{R_1 + R_2}, \quad R_4 = \infty, \quad R_2 \leq 7 \text{ k}\Omega$

### III) Equations for measurement items

a)  $I_B = I_{IN} \left( \begin{array}{l} R_1 = 1.5 \text{ k}, \quad R_3 = 0, \quad I_L = 0, \\ R_2 = \infty, \quad R_4 = \infty, \quad R_L = \infty \end{array} \right)$

b)  $R_{IN1} = \frac{V_o (15 \text{ V}) - V_o (12 \text{ V})}{V_o (12 \text{ V})} \times 100$

c)  $R_{IN2} = \frac{V_o (40 \text{ V}) - V_o (12 \text{ V})}{V_o (12 \text{ V})} \times 100$

d)  $R_{LD} = \frac{V_o (1 \text{ mA}) - V_o (50 \text{ mA})}{V_o (1 \text{ mA})} \times 100$

e)  $I_{SC} = I_L \quad (R_L = 0)$

f)  $R_T = \frac{V_o (\text{MAX}) - V_o (\text{MIN})}{V_o (25^\circ\text{C})} \times 100$

Note: (b) to (f)  
( $V_o = 5 \text{ V}$  setting,  $R_1 = 1.5 \text{ k}\Omega$ ,  $R_2 = \infty$ ,  $R_3 = 2.15 \text{ k}\Omega$ ,  $R_4 = 5 \text{ k}\Omega$ ,  $R_L = 5 \text{ k}\Omega$ )

MB3752



## TYPICAL CHARACTERISTICS CURVES

Fig. 3 - INPUT-TO-OUTPUT VOLTAGE DIFFERENTIAL vs. MAXIMUM LOAD CURRENT





Fig. 4 - INPUT VOLTAGE vs. BIAS CURRENT



4

Fig. 5 - LOAD CURRENT vs. LOAD REGULATION









Fig. 6 - CURRENT LIMIT



4-7


## TYPICAL CHARACTERISTICS CURVES (Continued)

4



## APPLICATION EXAMPLES


Fig. 11 - BASIC HIGH VOLTAGE REGULATOR

 $V_R \leq V_O \leq 37 \text{ V}$ 

$$V_O = V_R \cdot \frac{R_1 + R_2}{R_2}$$

$$R_3 = \frac{R_1 + R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$

Fig. 12 - BASIC LOW VOLTAGE REGULATOR


 $2 \text{ V} \leq V_O \leq V_R$ 

$$V_O = V_R \cdot \frac{R_2}{R_1 + R_2}$$

$$R_3 = \frac{R_1 + R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$


4

Fig. 13 - FOLDBACK CURRENT LIMITING REGULATOR



$$I_L \leq I_K \quad V_O = V_R \cdot \frac{R_2}{R_1 + R_2}$$

$$R_3 = \frac{R_1 + R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$



$$V_O = \frac{R_B \cdot R_{SC}}{R_A} \cdot I_L - V_{SC} \left( 1 + \frac{R_B}{R_A} \right)$$

$$I_{SC} = \frac{V_{SC}}{R_{SC}} \cdot \left( 1 + \frac{R_A}{R_B} \right), \quad V_{SC} \approx 0.7 \text{ V}$$

$$I_K = I_{SC} + \frac{V_O}{R_{SC}} \cdot \frac{R_A}{R_B}$$


FUJITSU

MB3752

## APPLICATION EXAMPLES (Continued)

4


Fig. 14 - POSITIVE VOLTAGE REGULATOR NPN TRANSISTOR



$$V_o = V_R \cdot \frac{R_1 + R_2}{R_2}$$

$$R_3 = \frac{R_1 \cdot R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$

Fig. 15 - POSITIVE VOLTAGE REGULATOR PNP TRANSISTOR




$$V_o = V_R \cdot \frac{R_2}{R_1 + R_2}$$

$$R_3 = \frac{R_1 \cdot R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$

Fig. 16 - NEGATIVE VOLTAGE REGULATOR

$$|V_o| \geq 9.5 \text{ V}$$




$$V_o = V_R \cdot \left( 1 + \frac{R_2}{R_1} \right)$$

$$R_3 = \frac{R_1 \cdot R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$

Fig. 17 - NEGATIVE VOLTAGE REGULATOR

$$0 \leq |V_o| \leq V_R$$




$$V_o = \frac{V_R}{\left( 1 + R_2/R_1 \right)}, V_{IN2} + V_o \geq 9.5 \text{ V}$$


$$R_3 = \frac{R_1 \cdot R_2}{R_1 + R_2} \text{ for minimum temperature drift}$$

## APPLICATION EXAMPLES (Continued)

**Fig. 18 - NEGATIVE VOLTAGE REGULATOR (CURRENT LIMITING)**



**Fig. 19 - SWITCHING REGULATOR**



4

**Fig. 20 DUAL TRACKING REGULATOR (CURRENT LIMITING)**

$$V_{O1} = V_R \left( 1 + \frac{R_1}{R_2} \right) \quad V_{O1} \geq V_R$$


$$V_{O2} = \frac{R_4}{R_3} V_{O1} \quad V_{O1} + V_{O2} \geq 40$$

$$I_{L1\text{MAX}} = \frac{0.7}{R_5}$$

$$I_{L2\text{MAX}} = \frac{0.6}{R_5}$$

Example for  $\pm 15$  V,  $\pm 1$  A

$R_1 = 8.2\text{k}\Omega$
$R_2 = 7.5\text{k}\Omega$
$R_3 = 15\text{k}\Omega$
$R_4 = 15\text{k}\Omega$
$R_5 = R_6 = 0.39\Omega$
$R_7 = 2\text{k}\Omega$




FUJITSU

MB3752

## APPLICATION EXAMPLES (Continued)


Fig. 21 - POSITIVE FLOATING VOLTAGE REGULATOR



$$R_3 = R_4 = 3.3k \Omega$$

$$V_O = V_R + \frac{R_2 - R_1}{2R_1}$$


Fig. 22 - NEGATIVE FLOATING VOLTAGE REGULATOR



$$R_3 = R_4 = 3.3k \Omega$$

$$V_O = V_R + \frac{R_1 + R_2}{2R_1}$$

Fig. 23 - 5 V HIGH CURRENT VOLTAGE REGULATOR



$$R_4 = 100 \Omega \text{ to } 1k \Omega$$

$$R_5 = 10 \Omega \text{ to } 100 \Omega$$

$$I_{LMAX} = \frac{V_{CS}}{R_{SC}} \left( \frac{V_{CS} - 0.7}{\Delta V_{CS}/\Delta T} = -2 \text{ mV/}^{\circ}\text{C} \right)$$


$$V_{IN2} > V_{OMAX} + V_{CESATOUT} + R_{SC} \cdot I_{LMAX} + \frac{1}{n} - R_6 \cdot I_{LMAX} + \frac{V_{IN2P}}{2}$$

V<sub>CESATOUT</sub> : Maximum value between Q<sub>1</sub> to Q<sub>n</sub>R<sub>6</sub> : R<sub>6-1</sub> = R<sub>6-2</sub> ..... = R<sub>6-n</sub> = R<sub>6</sub>V<sub>IN2P</sub> : Maximum ripple amplitude of V<sub>IN2</sub>

MB3752

FUJITSU

## PACKAGE DIMENSIONS




4

4-13

**FUJITSU**

**MB3752**

## PACKAGE DIMENSIONS (Continued)




MB3752



## PACKAGE DIMENSIONS (Continued)

14-LEAD PLASTIC FLAT PACKAGE  
(CASE No.: FPT-14P-M01)



Dimensions in  
inches (millimeters)

F14003S-2C

4

4-15