

MM5450/5451

LED Display Driver

General Description

The MM5450 and MM5451 LED display drivers are monolithic MOS IC's fabricated in an N-Channel, metal-gate process. The technology produces low-threshold, enhancement-mode, and ion-implanted depletion-mode devices.

A single pin controls the LED display brightness by setting a reference current through a variable resistor connected to the supply.

Applications

- Industrial control indicator
- Relay driver
- Digital clock, thermometer, counter, voltmeter
- Instrumentation readouts

Features

- Continuous brightness control
- Serial data input
- No load signal requirement
- Enable (on MM5450)
- Wide power supply operation
- TTL compatibility
- 34 or 35 outputs, 15mA capability
- Alphanumeric capability

Ordering Information

Part Number	Junction Temp. Range	Package		
MM5450BN	–40°C to +85°C	40-pin Plastic DIP		
MM5451BN	–40°C to +85°C	40-pin Plastic DIP		
MM5450BV	–40°C to +85°C	44-pin PLCC		
MM5451BV	–40°C to +85°C	44-pin PLCC		

Block Diagram





Connection Diagram: Dual-in-line Package



Figure 3a, 3b.

Connection Diagram: Plastic Leaded Chip Carrier



Absolute Maximum Ratings

V_{SS} to V_{SS} +12V
1W
560mW
+150°C
–65°C to +150°C
+300°C

Operating Ratings

Supply Voltage (V _{DD} – V _{SS})	+4.75V to +11V
Ambient Temperature Range (T _A)	–40°C to +85°C

Electrical Characteristics

 $4.5V \le V_{DD} \le 11V$, $V_{SS} = 0V$; $T_A = 25^{\circ}C$, **bold** values indicate $-40^{\circ}C \le T_A \le +85^{\circ}C$; unless noted

Symbol	Parameter	Condition	Min	Тур	Max	Units
	Power Supply Current	-25°C to +85°C, excluding output loads -40°C to +85°C, excluding output loads			8.5 10	mA mA
	Data Input Voltage					
V _L V _H		logic-0 level, ±10µA input bias logic-1 level, 4.75V \leq V_{DD} \leq 5.25V V_{DD} $>$ 5.25V	-0.3 2.2 V _{DD} -2		0.8 V _{DD} V _{DD}	V V V
	Brightness Control Input Current	Note 2	0		0.75	mA
	Output Sink Current	segment off, V _{OUT} = 3.0V			10	μA
		segment on, $V_{OUT} = 1.0V$, Note 3 brightness input = $0\mu A$ brightness input = $100\mu A$ brightness input = $750\mu A$	0 2.0 15	2.7	10 4 25	μA mA mA
	Brightness Control Input Voltage	input current = 750μA	3.0		4.3	V
	Output Matching	Note 1			±20	%
f _C	Clock Input Frequency	Notes 5, 6			500	kHz
t _H	Clock Input High Time	Notes 5, 6	950			ns
tL	Clock Input Low Time	Notes 5, 6	950			ns
t _{DS}	Data Input Setup Time		300			ns
t _{DH}	Data Input Hold Time		300			ns
t _{DES}	Data Enable Input Setup Time		100			ns
	Reset Pad Current	die	8			μA

Note 1: Output matching is calculated as the percent variation $(I_{MAX} + I_{MIN}) \div 2$.

Note 2: With a fixed resistor on the brightness input pin, some variation in brightness will occur among devices.

Maximum brightness control input current can be 2mA providing it complies with Note 3 and the junction temperature equation.

Note 3: See Figures 7, 8 and 9 for recommended operating conditions and limits. Absolute maximum for each output should be limited to 40mA.

Note 4: V_{OUT} should be regulated by the user. See Figures 8 and 9 for allowable V_{OUT} vs. I_{OUT} operation.

Note 5: AC input waveform specification for test purpose: $t_R \le 20$ ns, $t_F \le 20$ ns, f = 500kHz, 50% ±10% duty cycle.

Note 6: Clock input rise and fall times must not exceed 300ns.

Functional Description

The MM5450 and MM5451 were designed to drive either 4- or 5-digit alphanumeric LED displays with the added benefit of requiring minimal interface with the display or data source.

Data is transferred serially via 2 signals; clock and serial data. Data transfer without the added inconvenience of an external load signal is accomplished by using a format of a leading "1" followed by the allowed 35 data bits. These 35 data bits are latched after the 36th has been transferred. This scheme provides non multiplexed, direct drive to the LED display. Characters currently displayed (thus, data output) changes only if the serial data bits differ from those previously transferred.

Control of the output current for LED displays provides for the display brightness. To prevent oscillations, a 1nF capacitor should be connected to pin 19, brightness control.

The block diagram is shown in Figure 1. For the MIC5450, the DATA ENABLE is a metal option and is used instead of the 35th output. The output current is typically 20-times greater that the current into pin 19, which is set by an external variable resistor.

There is an external reset connection shown which is available on unpackaged (die) only. Figure 2 illustrates the die pad locations for bonding in "chip on board" applications.

Figure 5 shows the input data format. A leading "1" is followed by 35 bits of data. After the 36th had been transferred, a LOAD signal is generated synchronously with the clock high state. This loads the 35 bits of data into the latches. The low side of the clock is used to generate a RESET signal which clears all shift registers for the next set of data. All shift registers are static master-slave, with no clear for the master portion of the first register, allowing continuous operation. There must be a complete set of 36 clocks or the shift registers will not clear.

When the chip first powers ON, an internal power ON reset signal is generated which resets all registers and all latches. The START bit and the first clock return the chip to its normal operation.

Figure 3 and 4 show the pin-out of the MIC5450 and MIC5451. Bit 1 is the first bit following the start bit and it will appear on pin 18. A logical "1" at the input will turn on the appropriate LED.

Figure 5 shows the timing relationships between data, clock and DATA ENABLE. A maximum clock frequency of 0.5MHz is assumed.

For applications where a lesser number of outputs are used, it is possible to either increase the current per output, or operate the part at higher than $1V V_{OUT}$. The following equation can be used for calculations.

 $T_{J} = (V_{OUT}) (I_{IED})$ (No. of segments) (124°C/W) + T_{A}

where:

 T_{J} = junction temperature + 150°C max

 V_{OUT} = the voltage at the LED driver outputs

 I_{LED} = the LED current

124°C/W = thermal resistance of the package

 T_{A} = ambient temperature

The above equation was used to plot Figures 7–9.



Typical Performance Characteristics







Figure 10. Typical Application of Constant Current Brightness Control





Typical Applications







Figure 13. Duplexing 8 Digits with One MM5450.

Package Information



44-Pin PLCC (V)

0.104

0.172

MICREL INC. 1849 FORTUNE DRIVE SAN JOSE, CA 95131 USA

TEL + 1 (408) 944-0800 FAX + 1 (408) 944-0970 WEB http://www.micrel.com

This information is believed to be accurate and reliable, however no responsibility is assumed by Micrel for its use nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent right of Micrel Inc.

© 2000 Micrel Incorporated