

2-PHASE HIGH VOLTAGE DC MOTOR DRIVE IC


GENERAL DESCRIPTION

The FS220, a 1-chip composed of hall sensor and output coil drivers, applied to a 2-phase DC motor. The high sensitivity of Hall effect sensor is suitable for motors from mini-type CPU coolers to blowers and DC fans. Typical operation current is 0.3A and operating voltage range is from 3.5V ~ 28V.


Using few external components, FS220, a high performance integrated IC, is designed for a single-phase DC motor circuit. The circuit diagram of the typical application example is as below.

FEATURES


- 1 chip hall sensor/drivers
- Wide operating voltage range: 3.5V~28V
- Output sink current up to 0.3A
- Low quiescent supply current under 5mA
- Package : TO-92SP-4




TYPICAL APPLICATION CIRCUIT



FUNCTIONAL BLOCK DIAGRAM



MARK VIEW




PIN DESCRIPTION

NAME	NO.	STATUS	DESCRIPTION
VCC	1	P	IC Power Supply
NO	2	O	Coil driver output It is low state during the N magnetic field.
SO	3	O	Coil driver output It is low state during the S magnetic field.
GND	4	P	IC Ground

ABSOLUTE MAXIMUM RATINGS

NO/SO Pin Voltage -----	45V
VCC Pin Voltage -----	30V
Peak Sink Current (I _o)	
Hold Current-----	600mA
Continuous Current -----	350mA
Peak Reverse Current (I _R) -----	100mA
Power Dissipation	
Ta=25 -----	850mW
Ta=85 -----	450mW
Thermal Resistance	
Θ_{ja} = -----	0.15 /mW
Operating Temperature Range -----	-20°C 85°C
Storage Temperature Range -----	-65°C 150°C
Junction Temperature -----	+150°C
Lead Temperature (Soldering, 10 sec) -----	+230°C



DC ELECTRICAL CHARACTERISTICS

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Minimum Operating Voltage	V_{CC}	No use pin is open (Fig1)		3.5		V
Maximum Operating Voltage	V_{CC}	$I_{CP} < 10\text{mA}$ No use pin is open (Fig1)		28.0		V
Quiescent Supply current	I_{CC}	No use pin is open $V_{CP} : 4.0\text{V} \sim 30\text{V}$ (Fig1)	2.0		6.0	mA
NO/SO Saturation Voltage	V_{SAT}	$I_o = 300\text{mA}$ (Fig1)			1.5	V
Note: Fig1 The IC output state is under N magnetic field.						


AC ELECTRICAL CHARACTERISTICS

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Rise time	(t_r)	$R_L=100 \quad (5\text{w}) \quad C_L=20\text{pF}$ (Fig1)			10	μs
Fall time	(t_f)	$R_L=100 \quad (5\text{w}) \quad C_L=20\text{pF}$ (Fig1)			300	nS

MAGNETIC CHARACTERISTICS

FS220-A	Ta=-20 85		
PARAMETER	MIN	MAX	UNIT
Bop	+5	+65	G
Brp	-65	-5	G
Bhys	10	130	

FS220-B	Ta=-20 85		
PARAMETER	MIN	MAX	UNIT
Bop		+95	G
Brp	-95		G
Bhys		190	



TEST CIRCUITS:




Fig 1

TYPICAL CHARACTERISTICS




Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6

FUNCTION DESCRIPTIONS

HALL SENSOR LOCATION

The Fig 2 is the hall sensor location, where marks the IC number. The best sensitivity, which can be intensified as much as possible, depends on the vertical distance and position between magnetic pole and the hall sensor (Fig 3). For the single-phase motor, this design is very important.




Fig 2 FS220 Hall Sensor Location




Fig 3 Magnetic Distribution and Z-axis position

DARLINGTON-PAIR TRANSISTOR OUTPUT

The figure 4 is the circuit diagram of Darlington-pair transistor. Under the heavy current loading, the power loss of the high saturation voltage can be calculated into the following formula:

$$P_C = (V_{BEQ1} + V_{CE(SAT)Q2}) * I_o$$

According to the IC package and the curve of the power loss, the P_c should be applied to and within the safety value.

45V is the voltage of Zener breakdown diode. However, if the voltage, excluding that of the power supply, is more than 45V under the long-time operation, the diode will be destroyed.




FIG. 4 Darlington-pair Transistor Circuits

APPLICATION NOTE

The Example of Typical Application Circuit

Fig 5 is the example of typical application circuit. The red, yellow, and black wires are the input points of the motor system: red, the input of power supply; yellow, the output of FG; black, the ground signal. R_C is an external pull-up resistance for the use of measuring FG signal. In view of the design, the value of R_C could be decided by the transistor saturation voltage (V_{ON}), sink current (I_C), and off-level voltage (V_C).

The formula is:
$$R_C = \frac{V_C - V_{ON}}{I_C}$$

For example:

$V_C = +5V$ for TTL level.

$I_C = 10mA$ at 0.2V saturation voltage

The safety value of $R_C = 470$

D1 is the reverse protection diode. As if the red and black wires reversely connect with the power source, the current will flow through the ground via IC and coils L1 and L2 to power supply. Under such kind of circumstances, the IC and coils are easy to be burned out. Therefore, D1, the reverse protection diode, is necessary for the design. However, D1 will also cause an extra voltage drop on the supply voltage.

C1 is a capacitor to reduce the ripple noise caused during the transient of the output stages.

The volume of the ripple noise depends on the coil impedance and characteristics.







Fig 5 Application Circuit

PACKAGE OUTLINE



PACKING SPECIFICATIONS

BAG & BOX DIMENSION




PACKING QUANTITY SPECIFICATIONS

1000 EA/1 BAG


25 BAGS/1 INSIDE BOX

4 INSIDE BOXES/1 CARTON

LABEL SPECIFICATIONS



BAG LABEL



INSIDE BOX & CARTON LABEL

ORDER INFORMATION

Part Number	Operating Temperature	Package	Description
FS220-A	-20 ~ +85	TO-92SP-4	±65G (B)
FS220-B	-20 ~ +85	TO-92SP-4	±95G (B)