

PNP TRANSISTOR**B1426****3.0A**

- AF OUTPUT AMPLIFIER
- FOR DC-DC CONVERTER
- FOR CAMERA MOTOR DRIVER

TO-92

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS} Ta=25ϕ

PARAMETERS	SYMBOL	MIN	TYP	MAX	UNIT	CONDITION
Collector-Emitter Breakdown Voltage	BVceo	-20			V	Ic=1mA
Collector-Base Breakdown Voltage	BVcbo	-20			V	Ic=5μA
Emitter-Base Breakdown Voltage	BVebo	-6			V	Ie=50μA
Collector-Base Leakage	Icbo			0.1	μA	Vcb=-10V
Emitter-Base Leakage	Iebo			0.1	μA	Veb=-5V
Collector-Emitter Saturation Voltage	Vce(sat)	^		-0.5	V	Ic=2A Ib=0.1A
DC Current Gain	Hfe1	80		390		Vce=-2V,Ic=0.5A
Collector Current	Ic			3	A	
Peak Collector Current	Icp			5	A(Pulse)	
Current Gain Bandwidth	f _T		240		MHz	Vcb=-2V, Ic=0.5A
Output Capacitance	Cob			50	pF	Vcb=-10V,Ie=0,f=1MHz
Power Dissipation	Pc			0.75	W	
Junction Temperature	Tj			150	ϕ	
Storage Temperature	Tstg	-55		150	ϕ	

**STANSON TECHNOLOGY**

120 Bentley Square, Mountain View, Ca 94040 USA

TEL: (650) 9389294 FAX: (650) 9389295