



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: SU7500RT3U

### SmartOnline Expandable Rack/Tower UPS System - On-line, double-conversion protection for mission-critical applications

#### Highlights

- 7500VA on-line 6U rack/tower UPS with expandable runtime (3U power module + 3U battery pack)
- Detachable PDU with manual bypass switch enables hot-swap UPS replacement without powering off connected loads
- 200/208/230/240V selectable input/output voltage
- 2% output voltage regulation over an input voltage range of 156V to 276V
- Enhanced serial communications ports, SNMP/Web Card Slot and EPO interfaces
- \$250,000 Ultimate Lifetime Insurance (USA & Canada only).

#### Description

7,500 VA (7.5kVA) on-line, double-conversion UPS system for critical server, network and telecommunications equipment. Installs in only 6 rack spaces (3U power module and 3U battery pack). Maximum installed rack depth of 32.5 in. Expandable battery runtime with optional BP240V10RT3U and BP240V32 external battery packs. Full-time sine wave 200, 208, 220, 230, or 240V +/-2% output. Actively converts raw incoming AC power to DC, then re-converts output back to completely regulated, filtered AC output. Operates continuously without using battery power during brownouts to 156V and overvoltages to 276V. Standard 3-wire 208V hardwire input connection; NEMA L6-30R and L6-20R output receptacles. Detachable input-output PDU module with manual bypass switch enables hot-swap UPS replacement without disrupting power to connected equipment. Network-grade AC surge and noise suppression. Zero transfer time between AC and battery operation. Network management interfaces support communications via RS-232, contact-closure port and optional SNMPWEBCARD slot. Supports detailed monitoring of equipment load levels, self-test data and utility power conditions via network interfaces. Includes PowerAlert monitoring software and complete cabling. Emergency Power Off (EPO) interface. Front panel LEDs offer at-a-glance confirmation of line power status, battery power status, AC-to-DC conversion, DC-to-AC conversion, bypass mode and output power status. LCD panel with scroll buttons offers detailed diagnostic test information at startup and during self tests, plus real-time data on input and output voltage, frequency (Hz), load percentage and battery charge level. LED/LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm. Self-test. Fault-tolerant auto-bypass mode. 4-post rackmount accessories and 2-9USTAND tower kit included; 2POSTRMKITWM 2-post rackmount hardware accessories available. Field replaceable, hot-swappable power module and external battery packs. Attractive all-black color scheme. 2-year warranty and \$250,000 [connected equipment insurance](#); extended warranty and service contracts available.

#### Applications

- Ideal for protection of sensitive electronics in any application calling for upright tower or 19 inch rackmount UPS protection. Common applications include any mix of servers, workstations, hubs, routers, concentrators, IP telephony and traditional PBX switching systems

#### Package Includes

- 3U power module with detachable hot-swap PDU input/output panel and bypass switch
- 3U external battery pack
- Two sets of 4 post rackmount rails (one for each of the 3U components)
- One set of tower stands for upright tower configuration
- PowerAlert software, complete data cabling, user manual with warranty information

#### Features

- 7,500 VA (7.5kVA) on-line, double-conversion UPS system (High voltage input/High voltage output)

- Detachable input-output PDU module with manual bypass switch enables hot-swap UPS replacement without powering off connected equipment
- Installs in only 6 rack spaces (3U power module/3U battery pack) with a maximum installed depth of 32.5 inches
- Offers 9 min. runtime at full load (7500VA/6000W) and 20 min. at half load (3750VA/3000W). Runtime is expandable with any number of optional BP240V10RT3U external battery packs
- Full-time sine wave 200, 208, 220, 230, or 240V +/-2% output (user selectable)
- Actively converts raw incoming AC power to DC, then re-converts output back to completely regulated, filtered AC output
- Operates continuously without using battery power during brownouts to 156V and overvoltages to 276V
- Standard 3-wire 208V hardwire input connection
- 2 x NEMA L6-30R and 4 x L6-20R output receptacles
- Detailed LCD panel with scroll buttons offers detailed diagnostic test information on startup and during self tests, plus real-time data on input and output voltage, frequency (Hz), load percentage, battery charge level and more
- Network-grade AC surge and noise suppression
- Zero transfer time between AC and battery operation
- Network management interfaces support communications via RS-232, contact-closure port and optional SNMPWEBCARD slot
- Supports detailed monitoring of equipment load levels, self-test data and mains power conditions via network interfaces. Includes PowerAlert monitoring software and complete cabling
- Emergency Power Off (EPO) interface
- Front panel LEDs offer at-a-glance confirmation of line power status, battery power status, AC-to-DC & DC-to-AC conversion, bypass mode and output power status.
- Fault-tolerant auto-bypass mode prevents loss of output during UPS fault conditions or excessive UPS loading
- 4-post rackmount and upright tower installation accessories included. 2POSTRMKITWM two post rackmount hardware accessories available
- Field replaceable, hot swappable power module and external battery packs
- Attractive all-black color scheme
- 2-year warranty; \$250,000 [connected equipment insurance](#)
- Extended warranty and service contracts available

## Specifications

OUTPUT	
Frequency compatibility	50 / 60 Hz
Output VA	7500
Output watts	6000
Output nominal voltage	208V AC (200/208/220/230/240V)
Output voltage regulation	Maintains pure sine wave output at all times, regulated within 2% of selected nominal output voltage, less than 3% total harmonic distortion when used with computer loads
Output frequency regulation	Regulates line frequency to 50/60Hz +/- 0.05Hz
Outlet quantity / type	4 x NEMA L6-20R, 2 x NEMA L6-30R
INPUT	
Maximum Input Amps (A)	200V - 35A / 208V- 33.7A / 220V -31.8A / 230V - 30.4A / 240vV- 29.2A
Input connection type	Hardwire
Voltage compatibility (VAC)	200; 208; 220; 230; 240
BATTERY	
Expandable battery runtime	Runtime is expandable with optional <a href="#">BP240V10RT3U</a> and <a href="#">BP240V32</a> external battery packs

<b>DC system voltage (VDC)</b>	240
<b>Battery Access</b>	User replaceable, hot swappable external battery pack
<b>Full load runtime</b>	9 min. (7500VA/6000W)
<b>Half load runtime</b>	20 min. (3750VA/3000W)
<b>Battery Pack Accessory (optional)</b>	<a href="#">BP240V10RT3U</a> , <a href="#">BP240V32</a>
<b>Connects to UPS via</b>	Included 3-wire DC cable
<b>Typical battery lifespan</b>	4-6 years
<b>Battery recharge rate</b>	Less than 8 hours to 90% (included battery set only)
<b>VOLTAGE REGULATION</b>	
<b>Voltage regulation description</b>	On-line, double-conversion process give this UPS the ability to maintain output voltage within +/-2% of selected nominal voltage at all times
<b>Overvoltage correction</b>	Maintains continuous operation without using battery power during overvoltages to 276V AC, regulating output within 2% of selected nominal
<b>Brownout correction</b>	Maintains continuous operation without using battery power during brownout / undervoltage conditions to 156V AC, regulating output within 2% of selected nominal
<b>LEDS ALARMS &amp; SWITCHES</b>	
<b>Alarms</b>	Multi-function audible alarm offers notification of UPS start, backup operation, low battery, overload, UPS fault, inverter fault, DC bus fault, overtemperature, remote shutdown, shutdown imminent and shutdown complete
<b>Switches</b>	Includes main power off/on switch, plus 2 switches to set and execute scrollable LCD functions
<b>Front panel LEDs</b>	6 LED DISPLAY: line power, bypass, inverter, charger, output AC and battery operation. LED/LCD display panel easily rotates for viewing in rackmount or tower configurations.
<b>SURGE / NOISE SUPPRESSION</b>	
<b>EMI / RFI AC noise suppression</b>	Yes
<b>AC suppression response time</b>	Instantaneous
<b>PHYSICAL</b>	
<b>Shipping weight (lbs)</b>	331
<b>Shipping weight (kg)</b>	150.3
<b>Cooling method</b>	Fan
<b>Unit Dimensions (HWD/in)</b>	Power Module 5.14 x 17.5 x 25, Battery Pack 5.16 x 17.5 x 25 (Installed depth of power module extends to 32.5 inches once detachable PDU backplate is installed)
<b>Unit Dimensions (HWD/cm)</b>	Power Module 13.3 x 44.4 x 63.5, Battery Pack 13.4 x 40.6 x 63.5 (Installed depth of power module extends to 82.6 cm once detachable PDU backplate is installed)
<b>Shipping Dimensions (HWD/in)</b>	39.75 x 31.5 x 23
<b>Shipping Dimensions (HWD/cm)</b>	101 x 80 x 58.4
<b>Unit weight (lbs)</b>	Power Module 55 lbs., Battery Pack: 136.5 lbs.

<b>Unit weight (kg)</b>	Power Module 25 kg., Battery Pack: 62 kg
<b>Material of construction</b>	Steel
<b>Form factors supported</b>	Rack (6U)
<b>ENVIRONMENTAL</b>	
<b>Relative Humidity</b>	0 to 95%, non-condensing
<b>Line mode BTU/hr. (Max.)</b>	2025 btu/hr. (91% efficiency line mode)
<b>COMMUNICATIONS</b>	
<b>WatchDog compatibility</b>	Yes, compatible with Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application / OS or hard power off/on reboot of connected equipment—ideal for unattended kiosk applications
<b>Network monitoring port</b>	Includes 2 built-in DB9 monitoring ports (1-RS232 / 1-contact closure)
<b>EPO port</b>	Includes dedicated EPO (emergency power off) interface and cabling
<b>SNMP compatibility</b>	Built-in accessory slot accommodates internal SNMP / Web card and other network accessories
<b>Software and cabling included</b>	Includes PowerAlert UPS monitoring software for all common network and standalone operating systems. Cabling included.
<b>LINE / BATTERY TRANSFER</b>	
<b>Transfer time from line power to battery mode</b>	Zero, online UPS continuously converts incoming AC to DC, then back to AC. When line power is interrupted, UPS maintains continuous output from battery reserves with absolutely no disruption in output AC power.
<b>Low voltage transfer to battery power</b>	Maintains continuous operation during undervoltages as low as 156VAC. Below this point, output is maintained utilizing battery reserves.
<b>High voltage transfer to battery power</b>	Maintains continuous operation during overvoltages to 276V AC. Above this point, output is maintained utilizing battery reserves.
<b>SPECIAL FEATURES</b>	
<b>Appearance</b>	Attractive all-black color scheme
<b>Cold Start</b>	Yes, inverter can be "cold started" to enable temporary AC output during a power failure
<b>CERTIFICATIONS</b>	
<b>Certifications</b>	Tested to UL1778 (USA), CSA C22.2 No. 107.3 (Canada), CE (European Union), NOM (Mexico), Class A (Emissions)
<b>WARRANTY</b>	
<b>Product Warranty Period (U.S., Canada &amp; Puerto Rico)</b>	2-year limited warranty
<b>Connected Equipment Insurance (U.S., Canada &amp; Puerto Rico)</b>	\$250,000 Ultimate Lifetime Insurance
<b>Optional Coverage</b>	3 year, 5 year, next day and on-site warranty coverage available for select opportunities - contact Tripp Lite

---

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=3207](http://www.tripplite.com/en/products/model.cfm?txtModelID=3207).

---

Copyright © 2011 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.