

# POWER TRANSFORMER PC MOUNT: WORLD SERIES

# **VPP10-1000**

## **Electrical Specifications (@25C)**

- 1. Maximum Power: 10.0VA
- 2. Input: Series: 230VAC, 50/60Hz; Parallel: 115VAC, 50/60Hz
- 3. Output: Series<sup>1</sup>: 10.0V CT@ 1.0A; Parallel<sup>2</sup>: 5.0V @ 2.0A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance:  $100M\Omega$
- 7. Hipot: 4000VAC between primary to secondary and windings to core.

#### **Construction:**

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safety:

Since the dual bobbin construction effectively reduces capacitance, electrostatic shielding is not required. World Series Transformers are designed and manufactured to meet the following agency approvals:



### Agency File:

UL: File E53148, UL 5085-1 and 3 (formerly UL 506), General Purpose. UL: File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3. CSA: File LR 37220. C22.2 NO. 66, General Purpose. TUV: File R 72072385, EN 60950, (IEC950) information Technology Equipment.

A. Dime	ensions:	nsions: Units: In ind							
А	В	С	D	Е	F	G	н		
1.25	1.375	0.187	0.200	0.400	1.562	1.875	1.140		

B. PIN DIM. : 0.036 SQ

C. WT Lbs. : 0.53

D. Mounting Holes: 0.112 dia. x 2.0

#### Connections<sup>3</sup>:

Input: Series – Pin 1 to Pin 6, Jumper Pin 4 to Pin 3 Parallel – Pin 1 to Pin 6, Jumper Pin 1 to Pin 4 and Pin 3 to Pin 6 Output: Series – Pin 7 to Pin 12, Jumper Pin 9 to Pin 10 Parallel – Pin 7 to Pin 12, Jumper Pin 7 to Pin 10 and Pin 9 to Pin 12

RoHS Compliance: Meets the requirements of 2002/95/EC, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


<sup>1</sup> Inherently limited. No fusing required. Class 2.

<sup>2</sup> Inherently limited. No fusing required. Class 2.


<sup>3</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.


Web: www.TriadMagnetics.com			
Phone 951-277-0757			
Fax 951-277-2757			


22520B Temescal Canyon Road Corona, California 92883













Publish Date: August 3, 2009