
# Non-Lighted and Lighted Rocker Switch

#### **Features**

- Unique leaf spring mechanism suppresses heat generation to improve safety during long power application
- Original forcible separation ensures positive contact separation, under severe conditions
- Neon lamp allows switch to be directly applied with supply voltage
- Double-break contacts with gap of 3mm incorporated in nonflammable housing
- Abundant variations of rockers and flanges allowing selection of the type best suited to the equipment where mounted
- UL, CSA, and VDE approved





vraering ini	ormatio	TB.							
Classification				Lighted (Neon lamps)					
	Nonlighted			, 100 to 125 VAC			200 to 240 VAC		
Flange color	White	Black	Gray	White	Black	Gray	White	Black	Gray
White	A8A-201	A8A-201-1	A8A-201-2	_	_	_			
Red	A8A-202	A8A-202-1	A8A-202-2	A8A-212	A8A-212-1	A8A-212-2	A8A-222	A8A-222-1	A8A-222-2
Green	A8A-203	A8A-203-1	A8A-203-2	A8A-213	A8A-213-1	A8A-213-2	A8A-223	A8A-223-1	A8A-223-2
Blue	A8A-204	A8A-204-1	A8A-204-2						_
Yellow	A8A-205	A8A-205-1	A8A-205-2	<u>-</u>	_ <del></del>	_	_		
Orange			. —	A8A-216	A8A-216-1	A8A-216-2	A8A-226	A8A-226-1	A8A-226-2
Black	A8A-207	A8A-207-1	A8A-207-2		<del>-</del>	_			

### **Specifications**

Contact	ratings

Item	Noninductive load (A)		Inductive load (A)		Inrush	
Rated voltage	Resistive load	Lamp load	Inductive load	Motor load	current	
125 VAC	16	10	16	16	100 A max.	
250 VAC	16	10	8	16		

Note: 1. The values in this table indicate the steady-state currents.

2. Inductive load has a power factor of 0.4 min. (AC) and a time constant of 7msec max. (DC).

3. Lamp load has an inrush current of 10 times the steady-state current, while motor load has an inrush current of 6 times the steady-state current.

#### **Neon lamp ratings**


Туре	Rated voltage (VAC)	Set current (mA)
A8A-21□□	100	1.5
A8A-22□□	220	1.5

Note: 1. The service life is 15,000 hours min.


2. LED lamps are also available in red. Use part number A8A-252-1.

### **Contact Form**

### Lighted



# **Non-lighted**




### **Characteristics**

(Data shown are of initial	value)			
Operating speed	0.5 to 500 mm/sec			
Operating frequency	Mechanical: 30 operations/min. max. Electrical: 20 operations/min. max.			
Insulation resistance	100 MΩ min. (at 500 VDC)			
Contact resistance	20 mΩ max. 6V/1A			
Dielectric strength	2,000 VAC, 50/60 Hz for 1 minute between terminals of same polarity 2,000 VAC, 50/60 Hz for 1 minute between terminals of different polarity* and also between each terminal and ground			
Vibration	Malfunction durability: 10 to 55 Hz; 1.5 mm double amplitude			
Shock	Malfunction durability: 200 m/sec² (approx. 20G's) Mechanical durability: 500 m/sec² (approx. 50G's)			
Ambient temperature	Operating: -20° to +50°C			
Humidity	45 to 85% RH			
Service life	Mechanical: 40,000 operations min. Electrical: 20,000 operations min.			
Weight	Non-lighted type: Approx. 15 g Lighted type: Approx. 16 g			


Note: 1. \*The dielectric strength of the lighted type between terminals of different polarity is excluded.


# **Dimensions**

[Unit: mm]



32±0.5 - 25.2 -





Operating characteristics

F max.	200 g
Р	8±1 mm
P	5±1 mm
P	5±1 n

Note: 1. Recommended panel thickness is 1.0 to 3.0 mm.

# **Approved by Standards**



Note that the rated values approved by each of the safety standards (e.g., UL, CSA) may be different from the performance characteristics individually defined in this catalog.

UL (File:No: E41515)/CSA (File No: LR45258:32)/VDE (File:No: \$1979)

#### **Hints on Correct Use**

# Mounting

The A8A can be mounted on a panel by one-touch. Mount the switch on the panel with the specified cutout dimensions and thickness. Do not use a warped panel or one with a protruding seam.

A mark (1.8-dia. depression) is provided on the case flange to indicate the ON side of the switch. Use this mark for reference when mounting the switch.

#### Wiring

The terminal Nos. 1 and 3 of the lighted type are at the primary side. The neon lamp of the lighted type illuminates when the switch is turned ON and extinguishes when it is turned OFF.

1-8-dia. depression OFF side