Blackhawk [™] BH560v2 System Trace for TI Devices

TI Devices: C6000, C5000, C2000, OMAP, DAVINCI, SITARA, TMS470, TMS570, ARM 7/9, ARM Cortex A8/R4/M3
Compatible Operating Systems: Windows® 2K, XP, Vista & 7
Part Number: BH-XDS-560v2

The Blackhawk XDS560v2 System Trace Emulator (BH560v2) is based on the new Instruments XDS560v2 JTAG emulator reference design (XDS560v2). The XDS560v2 design is the next-generation of the high-performance XDS560class technology first made available by Blackhawk with the USB560/LAN560 and XDS560 The XDS560v2 design Trace. includes both high-speed USB 2.0 and 10/100Mbit Ethernet host interfaces, multi-color state and activity LEDs and a flexible



ribbon coax JTAG cable. The XDS560v2 adds support for IEEE1149.7 and the system trace module (STM), an interface on the TI heterogeneous multi-core (ARM + DSP) devices. If you are familiar with the Blackhawk LAN560 product, you will already be familiar with this new design.

The BH560v2 meets all of the TI Xds560v2 reference design features and requirements and <u>extends</u> (improves) capabilities by offering the following enhanced features.

- POWER: This is the first and most important feature enhancement. The BH560v2 has the option to be powered from either the USB or Power over Ethernet connectors. The unit can be powered solely from the USB a great feature for road warriors. And for LAN operation, the BH560v2 offers a 802.11af POE connector that can be powered from a POE enabled switch or the PoE injector supply.
- <u>INDICATORS</u>: We also added dedicated power and USB activity LEDs, which are found on the current Blackhawk USB560m and LAN560 models.
- CONFIGURATION & TEST: The BH560v2 includes a graphical user interface application that allows users to find, update, configure and test Bh560v2 devices on the local area network (LAN). You can even name the units, configure DHCP or fixed IP and more.

Blackhawk XDS560v2 Enhanced Feature Set

- Power Over Ethernet Option
- Power Over USB Only Option
- Additional Dedicated LEDs for Power and USB
- LAN and USB Graphical Configuration & Diagnostic Tool

Standard Features of TI XDS560v2 and Blackhawk XDS560v2

- Supports Code Composer Studio v4.2 or later and all Ctools enabled devices
- Flexible 12.5 inch JTAG cable with native 60-pin MIPI HSPT Target Cable
- Includes 20-pin compact TI (cTI), 14-pin standard TI and 20-pin ARM Adapters
- Supports JTAG 1149.1 and 1149.7
- Auto-Adaptive T-clock (TCLK) up to 50MHz
- Auto Sensing Target voltage range from 1.2v to 4.1v
- JTAG Debug Isolation, JTAG loop-back Modes and Boot Mode EMU0 & EMU1
- Supports 1-4 pin System Trace with 128 Mbytes of System Trace Buffer
- Up to 100MHz export clock compliant to MIPI STP
- Auto compensating calibration for edge jitter, channel skew and duty cycle
- Adaptive receiver for setup/hold times up to 1.5ns
- High-Speed USB 2.0 port @ 480Mbit/sec and 10/100 Ethernet port
- Supports Mobile Industry Processor Interface (MIPI)
- Supports System Trace Protocol (STP) and High-speed Parallel Trace (HSPT)
- Eight (8) tri-color status, state and activity LEDs







Items Included in the Box

- 1. XDS560v2 System Trace Emulator Pod
- 2. System Trace Coax JTAG Cable
- 3. MIPI60 buffer board
- 4. Pin Converters: TI14, TI20, and ARM20 targets
- 5. USB Cable
- 6. Ethernet Cable
- 7. Quick Start Guide
- 8. CDROM
- POE Injector (power supply) and wall cords
- 10. Product Registration Card

Ordering Information

BH-XDS560v2 is the PoE model and includes the external power supply injector and network cables. This model can also be used as USB.

BH-XDS560v2-BP is the bus-powered (USB) model and includes a USB cable with a special Y-adapter for extra USB power. This model does not include the external PoE injector power supply.

BH-PoE-KIT-1 includes the power supply, wall cords and network cables.

Available in Europe from: A.R. Bayer DSP Systeme GmbH - Düsseldorf/Germany - www.jtag-tools.de