

Device Information

ISL9519

[Print Page](#)

Narrow VDC Regulator/Charger with SMBus Interface

- [Features Description](#)
- [Technical Documentation](#)
- [Pricing / Samples](#)
- [iSim Design Simulation](#)
- [Tools And Support](#)
- [Related Devices](#)

Datasheet



ISL9519

The ISL9519 datasheet is restricted to a very limited number of customers. To request a datasheet please email Majid Kafi at mkafi@intersil.com

Input Voltage Range (V)	4.5 to 22
Input Current Limit Accuracy (%)	±3
Battery Charge Voltage (V)	2V to 16.3V in 16mV Steps
Charging Voltage Accuracy (max) (%)	±0.5
Battery Charge Voltage Adjust (%)	16mV Steps
Charge Current Limit Accuracy (%)	±3
Trickle Charge Current Limit Accuracy (%)	166A to 346mA
Automatic Trickle Charge (typ) (V)	Yes (Threshold Set by User)
Battery Leakage Current (max) (µA)	25 (DCIN=0V, No System Load)
Automatic Power Source Selection	Yes
DC Adapter Detection	No
Topology	Variable Frequency Synchronous Buck
Switching Frequency (typ) (kHz)	100 to 400
Max Duty Cycle (%)	99
Audible Noise	No
Operating Temp. Range (°C)	-10 to 100
Thermal Shutdown (°C)	150

Product Information

Key Features

- ±0.5% System Voltage Accuracy (-10°C to +100°C)
- ±3% Accurate Input Current Limit
- ±3% Accurate Battery Charge Current Limit
- Variable Switching Frequency at Light Load Conditions for Higher Efficiency
- Fixed Frequency Operation at Higher Loads
 - Fixed Frequency Mode can be Forced by an External Pin
- Trickle Charge System for Deeply Discharged Batteries
 - Automatic Trickle Charge Current (256mA)
 - Holds Minimum Voltage to System
- SMBus 2-Wire Serial Interface
- Default System Voltage Values for 1-Cell, 2-Cell or 3-Cell Operation Selected by an External Pin
- Adapter In-rush FET Control
- Adapter Isolation FET Control
- Battery Short Circuit Protection
- Fast System-Load Transient Response
- Monitor Outputs
 - Adapter Current (2.5% Accuracy)
 - AC-adapter Present Indicator
- 11-Bit Max System Voltage Setting
- 7-Bit Min System Voltage Setting
- 6-Bit Charge Current Setting
 - Over 8A Battery Charger Current
- 6-Bit Adapter Current Setting
 - Over 8A Adapter Current
- +4.5V to +22V Adapter Voltage Range
- Pb-Free (RoHS Compliant)

Description

The ISL9519 is a highly integrated Narrow VDC system voltage regulator and battery charger controller. Operating parameters are programmable over the System Management Bus (SMBus). The ISL9519 is designed for applications where the system power source is either the battery pack or the output of the regulator/charger. This makes the max voltage to the system equal to the max battery voltage instead of the max adapter voltage. The ISL9519 also includes a patented system to control trickle charging deeply discharged batteries while maintaining system voltage at a user defined minimum. High efficiency is achieved with a DC/ DC synchronous-rectifier buck converter, equipped with diode emulation and variable switching frequency for enhanced light load efficiency and AC-adapter boosting prevention. The ISL9519 can charge one, two or three series connected Lithium-ion cells, at up to 8A charge current. Default settings for 1-, 2- or 3-cell operation at power-up are selected by an external pin. Integrated MOSFET drivers and bootstrap diode result in fewer components and smaller implementation area. Low offset current-sense amplifiers provide high accuracy.

The ISL9519 provides an open drain digital output that indicates the presence of the AC-adapter. The ISL9519 also provides an analog output that indicates the adapter current.

Pricing / Packaging / Samples / Ordering



iBuy direct from Intersil



iBuy direct - out of stock



Request samples



Check distributor inventory



Available in RoHS/Pb-Free

Part No.	Design-In Status	Temp.	Package	MSL	Price US \$	RoHS	Lead	Sample
ISL9519EVAL1Z	Active		Eval Board	N/A	Contact Us	✓	ⓘ	📦
ISL9519HRTZ	Active	Hi-Temp Comm	28 Ld TQFN	1	4.00	✓		📦
ISL9519HRTZ-T	Active	Hi-Temp Comm	28 Ld TQFN T+R	1	4.00	✓		📦
ISL9519TQFNEVAL2Z	Active		Eval Board	N/A	Contact Us	✓		📦

The price listed is the manufacturer's suggested retail price for quantities of 1K units. However, prices in today's market are fluid and may change without notice.

MSL = Moisture Sensitivity Level - per IPC/JEDEC J-STD-020

SMD = Standard Microcircuit Drawing

Technical Documentation

Datasheet(s):

[EN](#) The ISL9519 datasheet is restricted to a very limited number of customers. To request a datasheet please email Majid Kafi at mkafi@intersil.com

Evaluation Board(s):

[ISL9519 CONTROL Software Installer](#)
[ISL9519EVAL1Z Evaluation Board Setup Procedure](#)
[ISL9519EVAL2Z Evaluation Board Setup Procedure](#)

Tools And Support

iSim Design Simulation

No Models Available

Applications

Notebook Computers
 Tablet PCs
 Portable Equipment with Rechargeable Batteries



Related Devices



Parametric Table

- [ISL6251](#) Low Cost Multi-Chemistry Battery Charger Controller
- [ISL6251A](#) Low Cost Multi-Chemistry Battery Charger Controller
- [ISL6252](#) Highly Integrated Battery Charger Controller for Notebook Computers

ISL6252A	Highly Integrated Battery Charger Controller for Notebook Computers
ISL6253	Highly Integrated Battery Charger for Notebook Computers
ISL6255	Highly Integrated Battery Charger with Automatic Power Source Selector for Notebook Computers
ISL6255A	Highly Integrated Battery Charger with Automatic Power Source Selector for Notebook Computers
ISL6256	Highly Integrated Battery Charger with Automatic Power Source Selector for Notebook Computers
ISL6256A	Highly Integrated Battery Charger with Automatic Power Source Selector for Notebook Computers
ISL6257	Highly Integrated Narrow VDC Battery Charger for Notebook Computers
ISL6258	Narrow VDC Regulator/Charger with SMBus Interface
ISL6258A	Narrow VDC Regulator/Charger with SMBus Interface
ISL88731	SMBus Level 2 Battery Charger
ISL88731A	SMBus Level 2 Battery Charger
ISL88731C	SMBus Level 2 Battery Charger
ISL9220	Switching Charger for 1-Cell and 2-Cell Li-ion Batteries
ISL9220A	Switching Charger for 1-Cell and 2-Cell Li-ion Batteries
ISL9518	Narrow VDC Regulator/Charger with SMBus Interface
ISL9518A	Narrow VDC Regulator/Charger with SMBus Interface
ISL95871C	SMBus Interfaced Battery Charger with Internal FETs

[About Us](#) | [Careers](#) | [Contact Us](#) | [Investors](#) | [Legal](#) | [Privacy](#) | [Site Map](#) | [Subscribe](#) | [Intranet](#)



©2003-2010. Intersil Americas Inc. All rights reserved.