



## JB26 Jumper Bars

### Terminal Blocks Accessories



#### Features and Benefits



Screw jumper bars

#### Main Technical Data

	IEC	cULus - CSA	Ex e
Rated current	232 A	230 A	
Rated voltage	Standard use 1000 V	600 V	630 V
Alternated poles			Not authorized
Impulse withstand voltage	8000 V		
Protection	IP	NEMA	

#### Mounting Instructions

Screw

Tool		Allen Key Ø 4 mm Ø 0.157 in
Torque		2 Nm ± 0.4 17.7 lb.in ± 3.54

Material Specifications	Insulating material	Copper
	Flammability	NF F 16 101
Ambient temperature min/max	Service IEC 60068-2-1	-55 +110 °C -67 +230 F
	Storage	-55 +110 °C -67 +230 F
	Installing	

#### Ordering Details

##### JB26 Jumper Bars

Description	Type	Order Code	Pack <sup>(n°)</sup> pieces	Weight g (1 pce)
26 mm 1.02 in spacing	2 poles	JB26-2	1SNK 926 302 R0000	5 41.20
	3 poles	JB26-3	1SNK 926 303 R0000	5 65.70
	5 poles	JB26-5	1SNK 926 305 R0000	5 115.70
	10 poles	JB26-10	1SNK 926 310 R0000	5 241.50

#### JB26 Mounting Instructions



- With flat pliers, cut out the partitions on the terminal block insulating body. Be careful to not cut out the jumpered terminal blocks at both ends of the assembly,
- Mount the jumper bar with the recommended tool and torque.