Series 31



Choose one component from each of the colored sections to assemble a complete switch. For other options or further information please contact EAO Switch directly.

O: Indicator

Product Profile

The Series 31 is a high quality switch range that includes pushbuttons, indicators and buzzers. It is possible to choose up to 4NO/4NC snap-action switching elements per switch. Low level switching elements are also available.

Technical drawings see page 43

- IP40 Protection
- Switch Rating, 5A, 250VAC
- Raised Mounting into 16mm cut out
- Illumination using midget-grooved T-1³/₄ lamps or single chip LED's
- All standard lenses are transparent with translucent white diffuser and are available in different colors
- Buzzers voltage from 10 to 75VDC



Indicator bodies, raised in round, square and rectangular, black plastic, 16mm mounting, solder terminals



Illuminated pushbutton

Illuminated pushbutton actuator, snap-action, raised, rectangular, black plastic, 16mm mounting, solder terminals, gold over silver contacts

| nage | Part No. | Size | Part No. | Action | Contact Type | Size |
|--------|----------------------------|-----------|-----------------|----------------------|--------------|-----------|
| 1 | 31-040.005 | 18 x 24mm | 31-121.025 | Momentary | 1NO/1NC | 18 x 24mm |
| 2 | 31-050.005 | 18 x 18mm | 31-122.025 | Momentary | 2N0/2NC | 18 x 24mm |
| 3 | 31-030.005 | 18mm Ø | 31-261.025 | Maintained | 1N0/1NC | 18 x 24mm |
| | | | 31-262.025 | Maintained | 2N0/2NC | 18 x 24mm |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | QC terminal versions also | available | QC terminal ver | rsions also availabl | е | |
| r comp | lete switch also order 🏼 🍟 | Α | For complete s | witch also order | ÿ A | |

For complete switch also order

Buzzer





Illuminated pushbutton actuator, snap-action, raised, square, black plastic, 16mm mounting, solder terminals, gold over silver contacts



Illuminated pushbutton actuator, snap-action, raised, round, black plastic, 16mm mounting, solder terminals, gold over silver contacts



Buzzer, plastic bezel, raised, rectangular, 16mm mounting, continuous or intermittant tone, 88dB ± 8 at a distance of 0.1m

| 0. | Action | Contact type | Size | Part No. | Action | Contact type | Size | Image | Part No. | Voltage | Connection | |
|-----------|----------------------|--------------|-----------|----------------|--------------------|--------------|--------|-------|------------|-----------------------|--------------|---|
| 1.025 | Momentary | 1N0/1NC | 18 x 18mm | 31-131.025 | Momentary | 1N0/1NC | 18mm Ø | 1 | 31-810.005 | 10 - 55VAC/10 - 75VDC | PCB | |
| 2.025 | Momentary | 2N0/2NC | 18 x 18mm | 31-132.025 | Momentary | 2N0/2NC | 18mm Ø | 2 | 31-801.002 | 10 - 26VDC | QC terminals | |
| 1.025 | Maintained | 1N0/1NC | 18 x 18mm | 31-271.025 | Maintained | 1N0/1NC | 18mm Ø | | | | | |
| 2.025 | Maintained | 2N0/2NC | 18 x 18mm | 31-272.025 | Maintained | 2N0/2NC | 18mm Ø | | | | | |
| | | | | | | | | | | | | |
| | | | | | | | | | | | | |
| | | | | | | | | | | | | |
| | | | | | | | | | | | | |
| | | | | | | | | | | | | |
| rminal ve | ersions also availab | ole | | QC terminal ve | rsions also availa | ble | | | | | | |
| | | | | | | | | | | | | - |

For complete switch also order \ddot{Q}

For complete switch also order 🍟 🗛

Part No. 31-151 31-152 31-281 31-282

QC term

LED

Ô

Series 31



LED, T-1 $^{3}/_{4}$ MG, single chip, 12 Volt and 28 Volt. Also available in 6 Volt, 24 Volt and 48 Volt.

A Accessories



Choose one component from each of the colored sections to assemble a complete switch.

For other options or further information please contact EAO Switch directly.

Lens, opaque for rectangular pushbutton actuators, not for illumination



Lens, front transparent with white diffuser for rectangular indicator and pushbutton actuator

| Color | Part No. | Contact type | Color | Part No. | Size | Color | Part No. | Size |
|----------|--------------|------------------|-------|----------|-----------|----------|----------|-----------|
| Red | 10-2J09.1062 | 12VAC/DC, 7/14mA | Black | 31-901.0 | 18 x 24mm | Red | 31-903.2 | 18 x 24mm |
| O Yellow | 10-2J09.1064 | 12VAC/DC, 7/14mA | | | | O Yellow | 31-903.4 | 18 x 24mm |
| O Green | 10-2J09.1065 | 12VAC/DC, 4/7mA | | | | 🔵 Green | 31-903.5 | 18 x 24mm |
| O Blue | 10-2J09.1066 | 12VAC/DC, 7/14mA | | | | O Blue | 31-903.6 | 18 x 24mm |
| O White | 10-2J09.1069 | 12VAC/DC, 7/14mA | | | | O Clear | 31-903.7 | 18 x 24mm |
| Red | 10-2J13.1062 | 28VAC/DC, 7/14mA | | | | | | |
| O Yellow | 10-2J13.1064 | 28VAC/DC, 7/14mA | | | | | | |
| O Green | 10-2J13.1065 | 28VAC/DC, 4/7mA | | | | | | |
| O Blue | 10-2J13.1066 | 28VAC/DC, 7/14mA | | | | | | |
| O White | 10-2J13.1069 | 28VAC/DC, 7/14mA | | | | | | |

A Accessories



Lens, opaque for square pushbutton actuators, not for illumination



Lens, front transparent with white diffuser for square indicator and pushbutton actuator



Lens, opaque for round pushbutton actuators, not for illumination

| Color | Part No. | Size | Color | Part No. | Size | Color | Part No. | Size |
|-------|----------|-----------|----------|----------|-----------|-------|----------|--------|
| Black | 31-951.0 | 18 x 18mm | Red | 31-953.2 | 18 x 18mm | Black | 31-931.0 | 18mm Ø |
| | | | O Yellow | 31-953.4 | 18 x 18mm | | | |
| | | | 🔵 Green | 31-953.5 | 18 x 18mm | | | |
| | | | O Blue | 31-953.6 | 18 x 18mm | | | |
| | | | 🔿 Clear | 31-953.7 | 18 x 18mm | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |

IP40 5A 250VAC 16mm

Series 31





Choose one component from each of the colored sections to assemble a complete switch. For other options or further information please contact EAO Switch directly.

A Accessories



Lens, front transparent with white diffuser for round indicator and pushbutton actuator



Flap guard, raised, square, round and rectangular



Sprayproof cover, square and rectangular, IP65

| Color | Part No. | Size | Image | Part No. | Size | Image | Part No. | Comment | Size |
|----------|----------|--------|-------|--------------|------------------------|-------|----------|-------------------------|-----------|
| 🔴 Red | 31-933.2 | 18mm Ø | 1 | 31-925 | 18 x 24mm | 1 | 31-924.2 | PVC rear, silicon front | 18 x 24mm |
| O Yellow | 31-933.4 | 18mm Ø | 2* | 31-920 | 18 x 18mm | 2 | 31-923 | Both PVC | 18 x 18mm |
| Green | 31-933.5 | 18mm Ø | | | | | | | |
| O Blue | 31-933.6 | 18mm Ø | | | | | | | |
| O Clear | 31-933.7 | 18mm Ø | | | | | | | |
| | | | | | | | | | |
| | | | | | | | | | |
| | | | | | | | | | |
| | | | | | | | | | |
| | | | | *Can be used | with round pushbuttons | | | | |



A Accessories

Blanking plate




Mounting tool, lens and LED remover

| Image | Part No. | Size | Image | Part No. | Product description |
|-------|----------|-----------|-------|-----------|---------------------|
| 1 | 01-947.0 | 18 x 24mm | 1 | 01-907 | Mounting tool |
| 2 | 01-948.0 | 18 x 18mm | 2 | 02-905 | Lens remover |
| 3 | 01-949.0 | 18mm Ø | 3 | 61-9740.0 | LED remover |
| | | | 4 | 02-906 | Lamp remover |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |

Series 31


31 Indicator

Raised, Round, Square, Rectangular




31 Pushbutton

Illuminated, Raised, Round, Square, Rectangular



31 Buzzer


Raised





31 Indicator Cut-outs

Raised, Round, Square, Rectangular



31 Pushbutton Cut-outs

Raised, Round, Square, Rectangular

