

# Fuseholders 6 x 30 mm (1¼" x ¼")



16A 250Vac (max fuse rating\*) T-55 to T+70 (ambient)  
 Maximum dissipation wattage: 2.5W  
 UL 94V2 UL file E92075 CSA file LR44770

These products comply with safety category PC2

\*Users should be aware of the de-rating factors published by specialist manufacturers of fuses


Fuseholders with in-line termination have combination (4.8 / 6.3) terminals. It has not been possible to show both views here. Units with right angle terminals have user specified end terminals and combination mid-body terminals



**M873**  
Cover for C & T terminals



**A0035 00**  
In-line 6 x 30 1¼ x ¼ fuseholder  
Call factory for rating details



TERMINAL	BODY AND CAP	PANEL HOLE	DIMENSIONS (mm)
<p><b>C</b></p> <p>6.3 x 0.8</p>	<p><b>0345</b> (C terminal shown)</p> <p>© N F UL CE</p>	<p><b>RA</b></p> <p>16.0/16.1</p> <p>Panel thickness 0.8 - 2.0mm for snap-in 0.8 - 4.5mm for nut fixing</p>	<p><b>0345</b> (C terminal shown)</p>
<p><b>D</b></p> <p>6.3 x 0.8 Right angle</p>	<p><b>0345</b> (D terminal shown)</p> <p>© N F UL CE</p>	<p><b>RD</b></p> <p>16.0/16.1</p> <p>Panel thickness 0.8 - 2.0mm for snap-in 0.8 - 4.5mm for nut fixing</p>	<p><b>0345</b> (D terminal shown)</p>
<p><b>T</b></p> <p>4.8 x 0.8 Solder</p>	<p><b>0347</b> (T terminal shown)</p> <p>© N F UL CE</p>	<p><b>RD</b></p> <p>16.0/16.1</p> <p>Panel thickness 0.8 - 2.0mm for snap-in 0.8 - 4.5mm for nut fixing</p>	<p><b>0347</b> (C terminal shown)</p>
<p><b>U</b></p> <p>4.8 x 0.8 Right angle solder</p>	<p><b>0347</b> (U terminal shown)</p> <p>© N F UL CE</p>	<p><b>RD</b></p> <p>16.0/16.1</p> <p>Panel thickness 0.8 - 2.0mm for snap-in 0.8 - 4.5mm for nut fixing</p>	<p><b>0347</b> (D terminal shown)</p>