





General Purpose Fuses

French Ferrule

499-493

gI, gG

Ratings - gI-gG (Optional Blown-Fuse Indicator)

SIZE (mm x mm)	RATED IN CURRENT (A)	RATED VOLTAGE	CATALOG NUMBER		REFERENCE NUMBER		INTERRUPTING RATING (A)	STANDARD PACK/CTN.	
			w/o indicator	w/indicator	w/o indicator	w/indicator			
8 x 31  P217877	0.5	400V	15009	-	P218181	-	20kA - 400V	10	
	1		15011	-	C218709	-			
	2		15013	15213	Q219227	B222204			
	4		15019	15219	W222958	X222959			
	6		15023	15223	A211025	V201291			
	8		15027	15227	B213096	B211026			
	10		15031	15231	A214613	A212060			
	12		15033	15233	R218146	C213097			
	16		15035	15235	P216650	Y214105			
	20		15037	15237	F217877	J215127			
	25		15039	15239	D218710	S216147			
10 X 38  D211028	0.5	500V	16009	-	C211027	-	120kA - 500V	10	
	1		16011	-	B212061	-			
	2		16013	16213	D213098	S216853			
	4		16019	16219	X213598	E217170			
	6		16023	16223	K215128	T218185			
	8		16027	16227	D217169	V219231			
	10		16031	16231	S218194	E222207			
	12		16033	16233	W219761	H200751			
	16		16035	16235	G200750	H201809			
	20		16037	16237	D211028	X211551			
	25		16039	16239	E213099	W212585			
	32		400V	16243	A214107	Z213600			120kA - 400V
	14 X 51  C213803	1	690V	17011	-	K218716	-	80kA - 690V	10
2		17013		17213	Y219234	C201298			
4		17019		17219	A219765	H211032			
6		17023		17223	H222210	G212066			
8		17027		17227	D222965	K213104			
10		17031		17231	L200754	H214620			
12		17033		17233	L201812	R215640			
16		17035		17235	A211554	X216657			
20		17037		17237	Z212588	N217684			
25		17039		17239	C213603	M218718			
32		500V		17243	W216656	C219767	120kA - 500V		
40		500V		17247	X218198	F222967	120kA - 500V		
50		400V		17251	Z219235	D201299	120kA - 400V		
22 x 58  Q217180		4	690V	18013	-	F219241	-	80kA - 690V	10
	4	18019		18219	H219772	Q211039			
	6	18023		18223	P222216	P212073			
	8	18027		18227	L222972	R213110			
	10	18031		18231	T200761	N214119			
	12	18033		18233	J201304	Y215140			
	16	18035		18235	S201818	D216157			
	20	18037		18237	P211038	R217181			
	25	18039		18239	N212072	F218206			
	32	18043		18243	F212584	H219243			
	40	18047		18247	J213609	R222218			
	50	18051		18251	P214626	W200763			
	63	18055		18255	Y215646	V201820			
	80	18059		18259	Q217180	K211583			
	100	500V		18263	E218205	H212596	120kA - 500V		
	125	400V	18265	J219773	L213611	120kA - 400V			

400V-252
NO-16043


Blown-Fuse Indicator



BEFORE



AFTER



Dimensions

FUSE SIZE	A	B	C
8 x 31	8.5	31.5	6.3
10 x 38	10.3	38	10.5
14 x 51	14.3	51	13.8
22 x 58	22.2	58	16.2