

AC Voltage Detector

Model NC-1

(Cat. #2121.09)



WARNING: Use with caution. Improper use of this device can result in injury or death. DO NOT service this device if you are not qualified to do so.

SPECIFICATIONS:	
Voltage Sensitivity	100 to 240VAC
Frequency	50/60Hz
Detection Distance	<5mm
Over Voltage	600V Cat. III
Battery	2x1.5V AAA
Safety	For indoor use and in accordance with overvoltage 600V Cat. III, Pollution Degree 2

OPERATION:



WARNING: Risk of electrocution. Before testing for voltage, always test the voltage detector on a known live circuit to verify that the instrument is working properly and that the battery is still good.

Keep hands and fingers on the body of the probe and away from the probe tip.

To check AC electrical voltage in an outlet:

1. Touch the probe tip to a cord plugged into the outlet or insert it into the outlet hole.
2. If AC voltage is present, the detector light will flash and the audible warning will sound.

BATTERY INSTALLATION:

1. Access the battery compartment by gently prying up/out at the pocket clip using a small screwdriver.
2. Insert two AAA batteries (observe polarity)
3. Replace battery cover.



Chauvin Arnoux®, Inc. d.b.a. **AEMC®** Instruments
15 Faraday Drive • Dover, NH 03820 USA
(800) 343-1391 • (603) 749-6434
www.aemc.com