

Types HCT802, HCT802TX, HCT802TXV

Electrical Characteristics ($T_A = 25^\circ\text{C}$ unless specified otherwise)

Symbol	Parameters	Device B=Both	Min	Max	Units	Test Conditions
$B_{V_{DS}}$	Drain-Source Breakdown	B	90*		V	$I_D = 10\ \mu\text{A}^*$, $V_{GS} = 0$
V_{TH}	Gate Threshold Voltage	N	0.75	2.5	V	$V_{GS} = V_{DS}$, $I_D = 1\ \text{mA}$
		P	-2.0	-4.5	V	$I_D = -1\ \text{mA}$
I_{GSS}	Gate-Body Leakage	B		± 100	nA	$V_{GS} = \pm 20\ \text{V}$, $V_{DS} = 0$
I_{DSS}	Zero Gate Voltage Drain Current	B		10*	μA	$V_{DS} = 90\ \text{V}^*$, $V_{GS} = 0\ \text{V}$
		B		500*	μA	$T_j = 150^\circ\text{C}$
$I_{D(on)}$	On-State Drain Current	N	1.5		A	$V_{DS} = 25\ \text{V}$, $V_{GS} = 10\ \text{V}$
		P	-1.1		A	$V_{DS} = -15\ \text{V}$, $V_{GS} = -10\ \text{V}$
$R_{DS(on)}$	Drain-Source on Resistance	B		5	Ω	$V_{GS} = 10\ \text{V}^*$, $I_D = 1\ \text{A}^*$
G_{fs}	Forward Transconductance	N	170		mmho	$V_{DS} = 25\ \text{V}$, $I_D = 0.5\ \text{A}$
		P	200		mmho	$V_{DS} = -10\ \text{V}$, $I_D = -0.5\ \text{A}$
C_{iss}	Input Capacitance	N		70	pf	$V_{DS} = 25\ \text{V}$, $V_{GS} = 0\ \text{V}$, $f = 1\ \text{MHz}$
		P		150	pf	$V_{DS} = -25\ \text{V}$, $V_{GS} = 0\ \text{V}$, $f = 1\ \text{MHz}$
C_{oss}	Common Source Output Capacitance	N		40	pf	$V_{DS} = 25\ \text{V}$, $V_{GS} = 0\ \text{V}$, $f = 1\ \text{MHz}$
		P		60	pf	$V_{DS} = -25\ \text{V}$, $V_{GS} = 0\ \text{V}$, $f = 1\ \text{MHz}$
C_{rSS}	Reverse Transfer Capacitance	N		10	pf	$V_{DS} = 25\ \text{V}$, $V_{GS} = 0\ \text{A}$, $f = 1\ \text{MHz}$
		P		25	pf	$V_{DS} = -25\ \text{V}$, $V_{GS} = 0\ \text{A}$, $f = 1\ \text{MHz}$
$t_{(on)}$	Turn-on-time	N		15	ns	$V_{DD} = 25\ \text{V}$, $I_D = 1\ \text{A}$, $R_L = 50\ \Omega$
		P		50	ns	$V_{DD} = -25\ \text{V}$, $I_D = -0.5\ \text{A}$, $R_L = 50\ \Omega$
$t_{(off)}$	Turn-off-time	N		17	ns	$V_{DD} = 25\ \text{V}$, $I_D = 1\ \text{A}$, $R_L = 50\ \Omega$
		P		50	ns	$V_{DD} = -25\ \text{V}$, $I_D = -0.5\ \text{A}$, $R_L = 50\ \Omega$

* Reverse polarity for P-Channel device

HI-REL
SURFACE
MOUNT

Optek reserves the right to make changes at any time in order to improve design and to supply the best product possible.

Optek Technology, Inc. 1215 W. Crosby Road Carrollton, Texas 75006 (972)323-2200 Fax (972)323-2396