

# PW172KB

## Universal 15-19 Watt Series



**ITE / Switch Mode Power Supply**

**3 Year Warranty**

- 100-240 VAC Universal Input
- Desktop and Wall Plug Style with Interchangeable Blades\* (Kit Sold Separately)
- Single Output to 19W
- Eight Models Available; 5V to 48V
- Regulated Output with Low Ripple
- Impact Resistant Polycarbonate Enclosure
- Modified and Custom Designs
- No Load Power Consumption < 0.50W
- Designed to Meet EISA Requirements — see reverse side for details



\*Photo shows optional blades kit



**International Safety Standard Approvals**



## Specifications

### Output Specifications

Line and Load Regulation (Excluding cord)	Line Voltage +/-1% Load Voltage +/-5%
Ripple	1% Vp-p max.
Transient Response	0.5ms for 50% Load change Typical
Protection	Over-current Protection (Hiccup) Short Circuit Protection

### Input Specifications

Input Voltage Range	Universal input	100-240VAC -10%, +10%
Line Frequency		47-63Hz
Input Current	90VAC Input	0.5A max.
Protection		Internal Primary Current Fuse, Inrush Limiting

### Environmental Specifications

Thermal Performance	Operating temperature full load, no derating convectional cooling Non vented case	0° C to 40° C
Relative Humidity	Non-condensing	5% to 95%
Altitude		0-10,000 feet

### General Specifications

Topology	Switching-Fixed Frequency Flyback
Efficiency	Designed to Meet EISA Requirements — see reverse side
Hold-up Time @115VAC	18ms min.
Dielectric Withstand	3,000VAC or 4,250VDC Primary-Secondary 1,500VAC or 2,150VDC Primary-F.G.; 500VDC Secondary-F.G.
Storage Temp	-30° C to 85° C
Approvals and Safety Standards	UL60950-1, IEC/EN60950-1 EMC : EN55022/55024/61000
MTBF	100,000 Calculated Hours
Case and Dimension	Desktop Style 3.3L x 1.81W x 1.26H (in) 84.0L x 46.0W x 32.0H (mm)
Case Material	Black 94V0 Polycarbonate
Cord and Connectors	18AWG 1,800mm 2 Conductor. (5V Model: 1,500mm). Ault #3 Connector. Other connectors are also available.

# PW172KB

Universal 15-19 Watt Series

ITE / Switch Mode Power Supply

For the most current data and application support visit [www.slpower.com](http://www.slpower.com)

Ault Part Number	Output Voltage	Output Current Max	Max Watts	Ripple Vp-p max.
PW172KB05XX	5 V	3.00 A	15.0 W	50 mV
PW172KB06XX	6 V	2.50 A	15.0 W	60 mV
PW172KB09XX	9 V	2.00 A	18.0 W	90 mV
PW172KB12XX	12 V	1.50 A	18.0 W	120 mV
PW172KB15XX	15 V	1.20 A	18.0 W	150 mV
PW172KB18XX	18 V	1.00 A	18.0 W	180 mV
PW172KB24XX	24 V	0.75 A	18.0 W	240 mV
PW172KB48XX	48 V	0.40 A	19.2 W	480 mV

Ault Part Number Key				
PW172	K	B	05	XX
Product Family Name	Manufacturing Location	Design Revision Changes	Voltage DC	Connector Number

Input Configuration					
IEC320 w/ground C14 (F)	IEC320 w/o ground C18 (Q)	Shaver C8 (N)	N. America/ Japan (B)	Europe (M)	United Kingdom (G)
Specify the Input Configuration Code in your order.					

Optional AC Interchangeable Blade Kit - KT1027K		
Europe (M)	United Kingdom (G)	Australian (E)
Blade Kit Part Number - KT1027K		

Pin Connections	
Pinout Code	Center contact: positive
Description	Switchcraft 760 plug or equivalent
Suggested Mating	Switchcraft 712A jack or equivalent
Other Connectors are available by special order.	

2007 Energy Independence and Security Act – EISA									
<p>The Energy Independence and Security Act of 2007 was passed in December of 2007 and addresses minimum efficiency standards and standby levels for Class A external power supplies that are 250 watts and under. This law stipulates that external power supplies manufactured on July 1, 2008 and beyond meet certain minimum efficiency and standby criteria as defined below.</p>									
<p><b>Minimum Efficiency Criteria</b> Active mode is defined as when a power supply's input is connected to a line voltage AC and its output is connected to a DC or AC load drawing a portion of the product's power output. Depending on the power rating for the power supply, it must meet the minimum efficiency criteria outlined below.</p>									
<p><b>Energy-Efficiency Criteria for Active Mode:</b></p> <table border="0"> <tr> <td>output power on adapter label</td> <td>minimum average efficiency percentage</td> </tr> <tr> <td>0 to ≤ less than 1 watt</td> <td>≥ 0.50 * output power on adapter label</td> </tr> <tr> <td>&gt; 1 to ≤ 51 watts</td> <td>≥ [0.09 * Ln (output power on adapter label )] + 0.50</td> </tr> <tr> <td>&gt; 51 watts</td> <td>≥ 0.85</td> </tr> </table>		output power on adapter label	minimum average efficiency percentage	0 to ≤ less than 1 watt	≥ 0.50 * output power on adapter label	> 1 to ≤ 51 watts	≥ [0.09 * Ln (output power on adapter label )] + 0.50	> 51 watts	≥ 0.85
output power on adapter label	minimum average efficiency percentage								
0 to ≤ less than 1 watt	≥ 0.50 * output power on adapter label								
> 1 to ≤ 51 watts	≥ [0.09 * Ln (output power on adapter label )] + 0.50								
> 51 watts	≥ 0.85								
<p>The power supply must also meet a requirement for when its input is connected to a line voltage AC but its output is not connected to a load. Depending on the power output of the supply, it must keep its energy consumption below the following values.</p>									
<p><b>Energy Consumption Criteria for No Load Mode:</b></p> <table border="0"> <tr> <td>output power on adapter label</td> <td>maximum power consumption in no-load mode</td> </tr> <tr> <td>0 to &lt; 250 watts</td> <td>≤ 0.5 watts</td> </tr> </table>		output power on adapter label	maximum power consumption in no-load mode	0 to < 250 watts	≤ 0.5 watts				
output power on adapter label	maximum power consumption in no-load mode								
0 to < 250 watts	≤ 0.5 watts								

