

BVL WIDE RANGE LEAD ACID CHARGERS

- 100-250 VAC
- In Case IEC 320
- Automatic Fast/Float Function
- LED Indicators
- Charges Lead Acid Batteries
- Optimizes Battery Life
- Meets Safety Agency Requirements
- Complies with EMI-RFI Regulations
- Impact Resistant Polycarbonate Enclosure
- Private Label Marking Available
- 3 Year Warranty
- Modified and Custom Designs Also Available

BVL					
Ault Part No.	Voltage DC	Output Amps	Fast Charge Volts DC	Float Charge Volts DC	Max Watts
BVL061000003X	6V	1.0	7.35	6.90	7.35
BVL062000003X	6V	2.0			14.70
BVL120600003X	12V	0.6	14.70	13.80	8.82
BVL121200003X	12V	1.2			17.64
BVL240300003X	24V	0.3	29.40	27.60	8.82
BVL240600003X	24V	0.6			17.64

Ault Part No. Key					
BVL	06	100	00	03	Χ
Product Family Name	Voltage DC	Output Amps	Denotes standard or custom requirements	Connector	Manufacturing Location





Input	
Voltage	100-250 VAC -10%, +6%
Line Frequency	47 - 63 Hz
Current	0.5 (Lower current with higher voltage)
Protection	Internal primary current fuse Inrush limiting

Electrical	
Topology	Switching - DC battery charger
Dielectric Withstand	3000 VAC, 4242 VDC primary- secondary 1500 VAC, 2121 VDC primary-ground 500 DC secondary-ground
EMI	Complies with EMC Directives
CE	CE Compliant
MTBF	100,000 calculated hours
Protection	Foldback overcurrent. Short circuit protection

Safety Approvals		
Agency Listings	cULus 60950; TUV EN60950	

Environmental		
Operating Temperature	5° to 40° C with no derating	
Storage Temperature	-30° to +85° C	
Relative Humidity	5% to 95% non-condensing 0-10,000 feet	
Altitude	0-10,000 feet	
Cooling	Convectional - non vented case	

Mechanical	
Case and Dimensions	4.20L x 2.60W x 1.46H (in) 107L x 66W x 37H (mm)
Case Material	94V0 polycarbonate; black is standard color; other colors available - extra charges may apply
Weight	8 ounces, 210 grams (excluding cord)
Cords and Connectors	6 ft., 2 conductor, 18 AWG, Ault #3 connector. Other connectors are also available.

Input Configuration




W/ground C14 (F)

Configuration: In Case IEC320 with ground

LED Indicators		
Indicator #1 (Green)	On (unit energized) Off (unit de-energized)	
Indicator #2 (Amber)	On (battery discharged) Off (battery charged)	

Connector



Pinout Code	Center contact: positive
Description	Switchcraft 760 plug or equivalent
Suggested Mating	Switchcraft 712A jack or equivalent

Other Connectors are available by special order

