

XTIEC

Table 16-77. Auxiliary Contacts

	Conventional Thermal Current, Open at 60°C $I_{th} = I_e$, AC-1 in Amps	Poles	Contact Configuration	Circuit Symbol	Pkg. Qty.	Screw Terminals	Spring Cage Terminals
						Catalog Number	Catalog Number
Frame B – C — Front (Top) Mount							
	16	2	2NO		5	XTCEXFAC20	XTCEXFACC20
	16	2	1NO-1NC		5	XTCEXFAC11	XTCEXFACC11
	16	2	2NC		5	XTCEXFAC02	XTCEXFACC02
	16	2	1NO _E -1NC _L		5	XTCEXFALC11 ①	XTCEXFALCC11 ①
	16	2	1NO-1NC		5	XTCEXFDC11 ②	XTCEXFDC11 ②
	16	2	2NC		5	XTCEXFCC02 ②	XTCEXFCC02 ②
	16	4	4NO		5	XTCEXFAC40	XTCEXFACC40
	16	4	3NO-1NC		5	XTCEXFAC31	XTCEXFACC31
	16	4	2NO-2NC		5	XTCEXFAC22	XTCEXFACC22
	16	4	1NO-3NC		5	XTCEXFAC13	XTCEXFACC13
	16	4	4NC		5	XTCEXFAC04	XTCEXFACC04
	16	4	1NO _E -1NC _L		5	XTCEXFCLC22 ①	XTCEXFCLCC22 ①
	16	4	2NO-2NC		5	XTCEXFCC22 ②	XTCEXFCC22 ②

① 1 early-make contact (1NO_E), 1 late-break contact (1NC_L).

② To avoid duplicate terminal numbers in contact sequence, these auxiliary contacts should only be used with contactors having a built-in 1NO contact (XTCE...B10_, XTCE...C10_).