

## High Current Linear Power Supply, 0-32VDC- 20A, LED Model 1790



The model 1790 is a cost effective, high power, regulated DC power supply with 640 Watt output (0 to 32V, 0 to 20A). It is a linear high current DC power supply suitable for bench operation or standard 19" rack operation. This linear power supply is a high power workhorse that will easily deliver clean power to your high current circuits.

- Constant Voltage/Constant Current Operation
- Remote Programming Facility
- Facility for Presetting the Output Voltage and Max.
- Load Current Limits
- Separate DC Output ON/OFF Switch
- Remote Sensing Facility
- High Stability and Close Regulation  $\pm 0.01\%$
- Meet CE Specifications

# High Current DC Power Supplies

## Model 1790, 1791 High Current DC Power Supply

Models 1790/1791 are cost effective, high power, regulated DC power supplies with 640 Watt output. They are linear high current DC power supplies suitable for bench operation or standard 19" rack operation. These linear power supplies are high power workhorses that will easily deliver clean power to your high-current circuits.

### Ideal for telecom application

Since noise elimination is critical for telecom application, the 1790 & 1791 DC power supplies offer low noise output, so that power supply noise does not interfere with testing of telecom devices. The 1790 & 1791 are ideal for manufacturers who build equipment for telecom industry that operates from 48V or higher DC rail such as: base stations, switches, public and private telecom network equipment, PBX system and DC to DC power supplies that provide power to this equipment.

These well-regulated constant voltage/constant current supplies deliver 0-32V at 0-20A (Model 1790) or 0-64V at 0-10A (Model 1791). They can be adjusted continuously throughout the output range by front panel controls. The units will automatically cross over from constant voltage to constant current mode and vice-versa if the output exceeds preset limits. Front panel LED meters are provided for monitoring voltage and current. The load terminals and remote sense terminals are located on the front panel. Either the positive or negative output terminal may be grounded or floated up to a maximum of  $\pm 300\text{VDC}$  above ground.

Special features include the ability to set constant current with no load and remote sense to compensate for any wire loss. The 1790 and 1791 are designed to meet CE specifications and have superior performance to comparable models costing 20 to 30% more.

- Constant Voltage/Constant Current Operation
- Remote Programming Facility
- Facility for Presetting the Output Voltage and Max. Load Current Limits
- Separate DC Output ON/OFF Switch
- Remote Sensing Facility
- High Stability and Close Regulation  $\pm 0.01\%$
- Meet CE Specifications



1790



1791

## Specifications

	models	
	1790	1791
Output (DC)	0-32V	0-64V
Output Current (DC)	0-20A	0-10A
Constant Voltage Mode		
Line Regulation (120V $\pm$ 10%)	$\pm 0.01\% \pm 2\text{mV}$	
Load Regulation	$\pm 0.01\% \pm 2\text{mV}$	
Ripple and Noise	$\leq 1\text{mV rms max}$	
Constant Current Mode		
Line Regulation (120V $\pm$ 10%)	$\pm 0.05\% \pm 10\text{mA}$	
Load Regulation	$\pm 0.05\% \pm 10\text{mA}$	
Ripple and Noise	6mA rms Max	
Overload Protection	Constant current type	
Stability	$\pm 0.2\% \pm 10\text{mV}$ in CV mode $\pm 0.5\% \pm 10\text{mA}$ in CC mode	
Operating Temperature	32° to 104°F (0° to 40°C)	
Power Requirement	120/230V, 60 Hz $\pm 10\%$	
Dimension (W x H x D)	19 x 5.25 x 15.75" (483 x 133 x 400mm)	
Weight	62 lbs. (28.1 kg)	

## Accessories

SUPPLIED: User Manual  
OPTIONAL: TL-30 Hook up leads

**Two Year Warranty**