# **Compact Proximity Sensor**

# As Easy To Install as a Microswitch

■ A compact Proximity Sensor with the feel of a microswitch.





Be sure to read Safety Precautions on page 4.

### **Ordering Information**

		Output specifications	Model		
Appearance	Sensing distance		Operation mode		
			NO	NC	
Microswitch type	0.000	DC 3-wire, NPN voltage output	TL-M2ME1	TL-M2ME2	
	2 mm	AC 2 wire	TL-M2MY1		
	F	DC 3-wire, NPN voltage output	TL-M5ME1	TL-M5ME2	
	5 mm	AC 2 wire	TL-M5MY1		

Note: Models with different frequencies are also available. The model numbers are TL-M\(\sum M\sum \subseteq 5\) (e.g., TL-M2ME15).

### **Ratings and Specifications**


Item Model		TL-M2ME1, TL-M2ME2, TL-M2MY1	TL-M5ME1, TL-M5ME2, TL-M5MY1		
Sensing distance		2 mm ±10%	5 mm ±10%		
Set distance		0 to 1.6 mm	0 to 4 mm		
Differential tra	ivel	10% max. of sensing distance			
Detectable ob	ject	Ferrous metal (The sensing distance decreases with non-ferrous metal. Refer to Engineering Data on page 2.)			
Standard sens	sing object	Iron, 15 × 15 × 1 mm			
Response free	quency	E Models: 500 Hz, Y Models: 20 Hz	E Models: 250 Hz, Y Models: 20 Hz		
Power supply (operating vol		E Models: 12 to 24 VDC (10 to 30 VDC), ripple (p-p): 20% max. Y Models: 100 to 220 VAC (90 to 250 VAC), 50/60 Hz			
Current consu	ımption	E Models: 15 mA max. at 24 VDC (no-load)			
Leakage curre	ent	Y Models: 2.5 mA max. at 200 VAC			
Control	Load current	E Models: 100 mA max. at 12 VDC, 200 mA max. at 24 VDC Y Models: 10 to 200 mA			
output	Residual voltage	E Models: 1 V max. Y Models: Refer to <i>Residual Output Voltage</i> under <i>Engineering Data</i> on page <i>3</i> .			
Indicators		E Models: Detection indicator (red) Y Models: Operation indicator (red)			
Operation mode (with sensing object approaching)		E1/Y1 Models: NO E2 Models: NC  Refer to the timing charts under I/O Circuit Diagrams on page 3 for details.			
Protection circuits		E Models: Reverse polarity protection, Surge suppressor Y Models: Surge suppressor			
Ambient temp	erature range	Operating/Storage: -25 to 70°C (with no icing or condensation)			
Ambient humi	dity range	Operating/Storage: 35% to 95% (with no condensation)			

Item Model		TL-M2ME1, TL-M2ME2, TL-M2MY1	TL-M5ME1, TL-M5ME2, TL-M5MY1		
Temperatu	ire influence	±10% max. of sensing distance at 23°C in the temperature range of –25 to 70°C			
Voltage inf	fluence	E Models: ±2.5% max. of sensing distance at rated voltage in the rated voltage ±15% range Y Models: ±1% max. of sensing distance at rated voltage in the rated voltage ±10% range			
Insulation	resistance	50 MΩ min. (at 500 VDC) between current-carrying parts and case			
Dielectric strength		E Models: 500 VAC, 50/60 Hz for 1 min between current-carrying parts and case Y Models: 2,000 VAC, 50/60 Hz for 1 min between current-carrying parts and case			
Vibration resistance		Destruction: 10 to 55 Hz, 1.5-mm double amplitude for 2 hours each in X, Y, and Z directions			
Shock resistance		Destruction: 500 m/s² 10 times each in X, Y, and Z directions			
Degree of	protection	IEC 60529 IP67, in-house standards: oil-resistant			
Connectio	n method	Pre-wired Models (Standard cable length: 2 m)			
Weight (pa	cked state)	Approx. 75 g			
Materials	Case	Heat-resistant ABS			
waterials	Sensing surface	meat-resistant AdS			
Accessories		Instruction manual			

## **Engineering Data (Typical)**


### **Sensing Area**

### TL-M2□/M5□




### **Leakage Current**

### TL-M□MY1




### Influence of Sensing Object Size and Material


#### TL-M2ME




### TL-M2MY1




#### TL-M5M



### **Residual Output Voltage**





## I/O Circuit Diagrams

#### **DC 3-Wire Models**

Operation mode	Output specifi- cations	Model	Timing chart	Output circuit
NO	NPN	TL-M2ME1 TL-M5ME1	Sensing object  Load (between brown and black leads)  Output voltage (between black and blue leads)  Detection indicator (red)  Present None  Deprate Reset  High Low  ON  OFF	$\begin{array}{c c} & & & & & \\ \hline & 100 \ \Omega & & & \\ \hline & 100 \ \Omega & & \\ \hline & & & & \\ \hline & & & & \\ \hline & & & &$
NC		TL-M2ME2 TL-M5ME2	Sensing object Present None  Load (between brown and black leads) Reset Output voltage (between black and blue leads) Low Detection indicator ON (Red) OFF	*1. 200 mA max. (load current). *2. When a transistor is connected.

#### **AC 2-Wire Models**

Operation mode	Model	Timing chart	Output circuit
NO	TL-M2MY1 TL-M5MY1	Sensing object  Present None  Load  Operate Reset  Operation indicator ON (Red)  OFF	Prox Inity Sensor main circuit

### **Safety Precautions**

#### Refer to Warranty and Limitations of Liability.

#### **MARNING**

This product is not designed or rated for ensuring safety of persons either directly or indirectly. Do not use it for such purposes.




### **Precautions for Correct Use**


Do not use this product under ambient conditions that exceed the ratings.

#### Design

#### **Influence of Surrounding Metal**

When installing Sensors on metal surfaces or near metal, ensure that the minimum distances given in the following table are maintained.





Note: For direct mounting, the distance "C" will equal 0 only in the shaded section of the above left-side section.


#### Influence of Surrounding Metal

(Unit: mm)

Model Distance	Α	В	С
TL-M2M	12	10	15
TL-M5M	18	25	30

#### **Mutual Interference**

When installing Sensors face-to-face or side-by-side, ensure that the minimum distances given in the following table are maintained.



#### **Mutual Interference**

(Unit: mm)

Model	Distance	Α	В	С	D
TL-M2M		60 (30)	40 (0)	30 (0)	10 (0)
TL-M5M		120 (60)	80 (40)	70 (30)	50 (10)


Note: Values in parentheses apply to Sensors operating at different frequencies.

#### Mounting

The maximum tightening torque that should be applied to the mounting screws is 0.98 N·m.

**Dimensions** (Unit: mm)

#### TL-M2M



#### TL-M5M

