

# Power Transformer Chassis Mount: Quick Pack

# F3-12

## **Description:**

The F3-12 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

## Electrical Specifications (@25C);

Maximum Power: 2.4VA

Input Voltage: 115VAC@50/60Hz Output Voltage: 12.6VCT@0.2A

#### Construction:

Split bobbing non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering.

#### Safety:

UL Class B E53148



### **Dimensions:**


А	В	С	D	Е	F	G
1.187	1.75±.03	2.062	1.187	1.625	.187 Dia	.562

Notes: 1. Units: inches.

2. Terminal size: .187" X 0.021".

3. Weight: .25 lbs


### Schematic:





Input: 1 to 3
Output: 4 to 6

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.







Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

22520B Temescal Canyon Road Corona, California 92883

Publish Date: February 4, 2010