

## POWER TRANSFORMER Chassis Mount: International Series

# VPL16-300

#### Electrical Specifications (@25C)

- 1. Maximum Power: 5.0VA
- Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
  Output Voltage Series<sup>1</sup>: 16.0V CT@ 0.310A, Parallel<sup>2</sup>: 8.0V @ 0.620A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.



#### Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

#### Agency Files:

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV Certificate No.: R72072385, EN60950, Information Technology





	Dimensions:				Units: In inche		
ĺ	Α	В	С	D	Е	F	
Ī	1.437	2.375	1.437	2.00	8.00	0.187	

Weight: 0.4 lbs.

### Connections<sup>3</sup>:

Input: Series - BLK to BLU, Jumper WHT to BRN

Parallel - BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series – RED to GRY, Jumper YEL to VIO


Parallel - RED to GRY, Jumper RED to VIO and YEL to GRY


RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

22520B Temescal Canyon Road Corona, California 92883







**SCHEMATIC** 

Publish Date: October 26, 2009

<sup>&</sup>lt;sup>1</sup> Inherently limited. No fusing required. Class 2 not wet, Class 3 wet.

<sup>&</sup>lt;sup>2</sup> Inherently limited. No fusing required. Class 2.

<sup>&</sup>lt;sup>3</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.