

POWER TRANSFORMER Chassis Mount: International Series

VPL25-1900

Electrical Specifications (@25C)

- 1. Maximum Power: 25.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
- 3. Output Voltage1: 25.2V CT@ 1.984A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.
- 6. Recommended Fuse²:

Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-2 ½, 2.5A 250V, ¼ x 1 ¼

Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

Agency Files:

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV Certificate No.: R72072385, EN60950, Information Technology





| Dimensions: | | | Units: In inches | | | |
|-------------|------|-------|------------------|------|-------|--|
| Α | В | С | D | Е | F | |
| 2.562 | 4.00 | 2.250 | 3.562 | 8.00 | 0.187 | |

Weight: 2.3 lbs.

Connections³:

Input: Series - BLK to BLU, Jumper WHT to BRN

Parallel - BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: RED to YEL


RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.


* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

22520B Temescal Canyon Road Corona, California 92883









SCHEMATIC

Publish Date: October 26, 2009

¹ Non-Inherently limited. Class 2 not wet, Class 3 wet.

² Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.

³ Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.