

# Power Transformer Chassis Mount: Quick Pack

## F8-36

## **Description:**

The F8-36 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

## Electrical Specifications (@25C):

Maximum Power: 100.0VA Input Voltage: 115VAC@50/60Hz Output Voltage: 36.0VCT@2.8A

### Construction:

Split bobbing non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering.

#### Safety:

UL Class B E53148



### **Dimensions:**


Α	В	С	D	Е	F	G
2.562	3.562	4.031	2.250	3.062	.187 Dia	1.312

Notes: 1. Units: inches.

2. Terminal size: .187" X 0.021".

3. Weight: 2.75 lbs

#### Schematic:





Input: 2 to 4
Output: 6 to 10

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.







Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

22520B Temescal Canyon Road Corona, California 92883

Publish Date: February 5, 2010