

3-MODE 150mA LDO REGULATOR with the Reverse Current Protection

NO.EA-118-071227

OUTLINE

The R1163x Series consist of CMOS-based voltage regulator ICs with high output voltage accuracy and low supply current. These ICs perform with the chip enable function and realize a standby mode with ultra low supply current. To prevent the destruction by over current, the current limit circuit is included. The R1163x Series have 3-mode. One is standby mode with CE or standby control pin. Other two modes are realized with ECO pin™. Fast Transient Mode (FT mode) and Low Power Mode (LP mode) are alternative with ECO pin™. Consumption current is reduced at Low Power Mode compared with Fast Transient Mode. The output voltage is maintained between FT mode and LP mode.

Further, the reverse current protection circuit is built-in. Therefore, if a higher voltage than V_{DD} pin is forced to the output pin, the reverse current to V_{DD} pin is very small (Max. 0.1μA), so it is suitable for backup circuit.




Since the packages for these ICs are SOT-23-5, SON-6, and DFN(PLP)1616-6 packages, high density mounting of the ICs on boards is possible.

FEATURES

- Supply Current Typ. 6.0μA (Low Power Mode),
Typ. 70μA (Fast Transient Mode)
- Standby Mode Typ. 0.6μA
- Reverse Current Max. 0.1μA
- Dropout Voltage Typ. 0.25V ($I_{OUT}=150mA$, Output Voltage=3.0V Type)
- Ripple Rejection Typ. 70dB (f=1kHz, FT Mode)
- Temperature-Drift Coefficient of Output Voltage Typ. ±100ppm/°C
- Line Regulation Typ. 0.02%/V (FT Mode)
- Output Voltage Accuracy ±1.5% (±2.5% at LP Mode)
- Package SOT-23-5, SON-6, DFN(PLP)1616-6
- Output Voltage Stepwise setting with a step of 0.1V
in the range of 1.5V to 4.0V is possible
- Input Voltage Range 2.0V to 6.0V
- Built-in fold-back protection circuit Typ. 40mA (Current at short mode)
- Performs with Ceramic Capacitors $C_{IN}=1.0\mu F$, $C_{OUT}=\text{Ceramic } 0.47\mu F$

APPLICATIONS

- Precision Voltage References.
- Power source for electrical appliances such as cameras, VCRs and hand-held communication equipment.
- Power source for battery-powered equipment.

BLOCK DIAGRAM**R1163xxx1B****R1163xxx1D****R1163xxx1E**

SELECTION GUIDE


The output voltage, the auto-discharge function*, the package and the taping type for the ICs can be selected at the user's request. The selection can be available by designating the part number as shown below;

R1163xxx1x-xx-X ←Part Number
↑↑ ↑ ↑ ↑
a b c d e

Code	Contents
a	Designation of Package Type : N: SOT-23-5 D: SON-6 K: DFN(PLP)1616-6
b	Setting Output Voltage (V_{OUT}) : Stepwise setting with a step of 0.1V in the range of 1.5V to 4.0V is possible. Exceptions: 1.85V=R1163x181x5-xx-x, 2.75V=R1163x271x5-xx-x, 2.85V=R1163x281x5-xx-x
c	Designation of Chip Enable Option : B: "H" active type and without the auto-discharge function*. D: "H" active and with the auto-discharge function*. E: "H" active type and without auto-discharge function*. ECO logic reverse type (Low Power mode at ECO="H")
d	Designation of Taping Type : Refer to Taping Specifications;TR type is the standard direction.
e	Designation of composition of pin plating: -F : Lead free plating (SOT-23-5, SON-6) None: Au plating (DFN(PLP)1616-6)

*) When the mode is into standby with CE signal, auto discharge transistor turns on, and it makes the turn-off speed faster than normal type.

PIN CONFIGURATIONS



PIN DESCRIPTIONS

• SOT-23-5

Pin No	Symbol	Pin Description
1	V _{DD}	Input Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin
4	ECO	MODE alternative pin
5	V _{OUT}	Output pin

• SON-6

Pin No	Symbol	Pin Description
1	V _{DD}	Input Pin
2	NC	No Connection
3	V _{OUT}	Output pin
4	ECO	MODE alternative pin
5	GND	Ground Pin
6	CE	Chip Enable Pin

*) Tab in the parts have GND level.
(They are connected to the back side of this IC.)
Do not connect to other wires or land patterns.

• DFN(PLP)1616-6

Pin No	Symbol	Pin Description
1	V _{OUT}	Output pin
2	GND	Ground Pin
3	ECO	MODE alternative pin
4	CE	Chip Enable pin
5	NC	No Connection
6	V _{DD}	Input Pin

*) Tab in the parts have GND level.
(They are connected to the back side of this IC.)
Do not connect to other wires or land patterns.

ABSOLUTE MAXIMUM RATINGS

Symbol	Item	Rating	Unit
V_{IN}	Input Voltage	6.5	V
V_{ECO}	Input Voltage (ECO Pin)	-0.3 ~ 6.5	V
V_{CE}	Input Voltage (CE Pin)	-0.3 ~ 6.5	V
V_{OUT}	Output Voltage	-0.3 ~ 6.5	V
I_{OUT}	Output Current	180	mA
P_D	Power Dissipation (SOT-23-5) *	420	mW
	Power Dissipation (SON-6) *	500	
	Power Dissipation (DFN(PLP)1616-6)*	560	
T_{opt}	Operating Temperature Range	-40 ~ 85	°C
T_{stg}	Storage Temperature Range	-55 ~ 125	°C

*) For Power Dissipation, please refer to PACKAGE INFORMATION to be described.

ABSOLUTE MAXIMUM RATINGS

Absolute Maximum ratings are threshold limit values that must not be exceeded ever for an instant under any conditions. Moreover, such values for any two items must not be reached simultaneously. Operation above these absolute maximum ratings may cause degradation or permanent damage to the device. These are stress ratings only and do not necessarily imply functional operation below these limits.

ELECTRICAL CHARACTERISTICS

R1163xxx1B/D

Topt=25°C

Symbol	Item		Conditions		Min.	Typ.	Max.	Unit
V _{OUT}	Output Voltage	(FT Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =V _{IN} 1mA ≤ I _{OUT} ≤ 30mA		×0.985		×1.015	V
		(LP Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =GND 1mA ≤ I _{OUT} ≤ 30mA		×0.975		×1.025	
ΔV _{OUT}	Output Voltage Deviation between FT Mode and LP Mode		V _{IN} =Set V _{OUT} +1V, I _{OUT} =30mA	V _{OUT} > 2.0V	-1.2	0	1.2	%
			V _{OUT} ≤ 2.0V	-24	0	24	mV	
I _{OUT}	Output Current		V _{IN} -V _{OUT} =1.0V		150			mA
ΔV _{OUT} / ΔI _{OUT}	Load Regulation	(FT Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =V _{IN} 1mA ≤ I _{OUT} ≤ 150mA			20	40	mV
		(LP Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =GND 1mA ≤ I _{OUT} ≤ 150mA			20	45	
V _{DIF}	Dropout Voltage		Refer to the following table					
I _{SS1}	Supply Current (FT Mode)		V _{IN} =Set V _{OUT} +1V V _{ECO} =V _{IN}			70	100	μA
I _{SS2}	Supply Current (LP Mode)		V _{IN} =Set V _{OUT} +1V V _{ECO} =GND			6.0	10.0	μA
I _{standby}	Supply Current (Standby)		V _{IN} =Set V _{OUT} +1V, V _{CE} =GND V _{ECO} =GND or V _{IN}			0.6	1.0	μA
ΔV _{OUT} / ΔV _{IN}	Line Regulation	(FT Mode)	Set V _{OUT} +0.5V ≤ V _{IN} ≤ 6.0V I _{OUT} =30mA, V _{ECO} =V _{IN} If V _{OUT} ≤ 1.6V, then 2.2V ≤ V _{IN} ≤ 6.0V			0.02	0.10	%/V
		(LP Mode)	Set V _{OUT} +0.5V ≤ V _{IN} ≤ 6.0V I _{OUT} =30mA, V _{ECO} =GND If V _{OUT} ≤ 1.6V, then 2.2V ≤ V _{IN} ≤ 6.0V			0.05	0.20	
RR	Ripple Rejection (FT Mode)		Ripple 0.2Vp-p, V _{IN} =Set V _{OUT} +1V, I _{OUT} =30mA, V _{ECO} =V _{IN} If V _{OUT} ≤ 1.7V, then V _{IN} =Set V _{OUT} +1.2V	f=1kHz		70		dB
			f=10kHz		60			
V _{IN}	Input Voltage				2.0		6.0	V
ΔV _{OUT} / ΔT _{opt}	Output Voltage Temperature Coefficient		I _{OUT} =30mA -40°C ≤ T _{opt} ≤ 85°C			±100		ppm /°C
I _{lim}	Short Current Limit		V _{OUT} =0V			40		mA
I _{PD}	CE Pull-down Current					0.3	0.6	μA
R _{PDE}	ECO Pull-down Resistance				2	5	30	MΩ
V _{CEH}	CE, ECO Input Voltage "H"				1.0		6.0	V
V _{CEL}	CE, ECO Input Voltage "L"				0		0.35	V
en	Output Noise "H" (FT Mode)		BW=10Hz to 100kHz			30		μVRms
	Output Noise "L" (LP Mode)		BW=10Hz to 100kHz			40		
R _{LOW}	Low Output Nch Tr. ON Resistance (of D version)		V _{CE} =0V			60		Ω
I _{REV}	Reverse Current		V _{OUT} >0.5V, 0V ≤ V _{IN} ≤ 6V			0	0.1	μA

R1163xxx1E

Top_t=25°C


Symbol	Item		Conditions		Min.	Typ.	Max.	Unit
V _{OUT}	Output Voltage	(FT Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =GND 1mA ≤ I _{OUT} ≤ 30mA		×0.985		×1.015	V
		(LP Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =V _{IN} 1mA ≤ I _{OUT} ≤ 30mA		×0.975		×1.025	
ΔV _{OUT}	Output Voltage Deviation between FT Mode and LP Mode		V _{IN} =Set V _{OUT} +1V, I _{OUT} =30mA	V _{OUT} > 2.0V	-1.2	0	1.2	%
				V _{OUT} ≤ 2.0V	-24	0	24	mV
I _{OUT}	Output Current		V _{IN} -V _{OUT} =1.0V		150			mA
ΔV _{OUT} / ΔI _{OUT}	Load Regulation	(FT Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =GND 1mA ≤ I _{OUT} ≤ 150mA			20	40	mV
		(LP Mode)	V _{IN} =Set V _{OUT} +1V, V _{ECO} =V _{IN} 1mA ≤ I _{OUT} ≤ 150mA			20	45	
V _{DIF}	Dropout Voltage		Refer to the following table					
I _{SS1}	Supply Current (FT Mode)		V _{IN} =Set V _{OUT} +1V V _{ECO} =GND			70	100	μA
I _{SS2}	Supply Current (LP Mode)		V _{IN} =Set V _{OUT} +1V V _{ECO} =V _{IN}			6.0	10.0	μA
I _{standby}	Supply Current (Standby)		V _{IN} =Set V _{OUT} +1V, V _{CE} =GND V _{ECO} =GND or V _{IN}			0.6	1.0	μA
ΔV _{OUT} / ΔV _{IN}	Line Regulation	(FT Mode)	Set V _{OUT} +0.5V ≤ V _{IN} ≤ 6.0V I _{OUT} =30mA, V _{ECO} =GND If V _{OUT} ≤ 1.6V, then 2.2V ≤ V _{IN} ≤ 6.0V			0.02	0.10	%/V
		(LP Mode)	Set V _{OUT} +0.5V ≤ V _{IN} ≤ 6.0V I _{OUT} =30mA, V _{ECO} =V _{IN} If V _{OUT} ≤ 1.6V, then 2.2V ≤ V _{IN} ≤ 6.0V			0.05	0.20	
RR	Ripple Rejection (FT Mode)		Ripple 0.2Vp-p V _{IN} =Set V _{OUT} +1V, I _{OUT} =30mA, V _{ECO} =GND If V _{OUT} ≤ 1.7V, then V _{IN} =Set V _{OUT} +1.2V	f = 1kHz		70		dB
				f = 10kHz		60		
V _{IN}	Input Voltage				2.0		6.0	V
ΔV _{OUT} / ΔT _{opt}	Output Voltage Temperature Coefficient		I _{OUT} = 30mA -40°C ≤ T _{opt} ≤ 85°C			±100		ppm /°C
I _{lim}	Short Current Limit		V _{OUT} = 0V			40		mA
I _{PD}	CE Pull-down Current					0.3	0.6	μA
V _{CEH}	CE, ECO Input Voltage "H"				1.0		6.0	V
V _{CEL}	CE, ECO Input Voltage "L"				0		0.4	V
en	Output Noise "H" (FT Mode)		BW = 10Hz to 100kHz			30		μVrms
	Output Noise "L" (LP Mode)		BW = 10Hz to 100kHz			40		
I _{REV}	Reverse Current		V _{OUT} >0.5V, 0V ≤ V _{IN} ≤ 6V			0	0.1	μA

ELECTRICAL CHARACTERISTICS by OUTPUT VOLTAGE

$T_{opt} = 25^\circ\text{C}$

Output Voltage V _{OUT} (V)	Dropout Voltage (mV)				
	Condition	V _{DIF} (ECO=H)		V _{DIF} (ECO=L)	
		Typ.	Max.	Typ.	Max.
1.5 ≤ V _{OUT} < 1.6	I _{OUT} =150mA	400	680	420	680
1.6 ≤ V _{OUT} < 1.7		380	550	390	550
1.7 ≤ V _{OUT} < 1.8		350	520	370	520
1.8 ≤ V _{OUT} < 2.0		340	490	350	490
2.0 ≤ V _{OUT} < 2.8		290	425	300	430
2.8 ≤ V _{OUT} ≤ 4.0		250	350	250	350

TYPICAL APPLICATION



(External Components)

TECHNICAL NOTES

When using these ICs, consider the following points:

Phase Compensation

In these ICs, phase compensation is made for securing stable operation even if the load current is varied. For this purpose, be sure to use a $0.47\mu\text{F}$ or more ceramic capacitor C2.

(Test these ICs with same external components as ones to be used on the PCB.)

When a tantalum capacitor is used with this IC, if the equivalent series resistor (ESR) of the capacitor is large, output voltage may be unstable.

PCB Layout

Make V_{DD} and GND lines sufficient. If their impedance is high, noise pickup or unstable operation may result. Connect a capacitor C1 with as much as 1.0μF capacitor between V_{DD} and GND pin as close as possible.


Set external components such as an output capacitor C2, as close as possible to the ICs and make wiring as short as possible.

TYPICAL CHARACTERISTICS


Unless otherwise provided, capacitors are ceramic type.

1) Output Voltage vs. Output Current


R1163x151x ECO=H




R1163x151x ECO=L




R1163x281x ECO=H




R1163x281x ECO=L



R1163x40x ECO=H




R1163x40x ECO=L




R1163x

2) Output Voltage vs. Input Voltage


R1163x151x ECO=H




R1163x15x ECO=L




R1163x28x ECO=H




R1163x28x ECO=L









R1163x40x ECO=H



R1163x40x ECO=L




3) Supply Current vs. Input Voltage**R1163x151x ECO=H****R1163x151x ECO=L****R1163x281x ECO=H****R1163x281x ECO=L****R1163x401x ECO=H****R1163x401x ECO=L**


R1163x

4) Output Voltage vs. Temperature


R1163x151x ECO=H




R1163x151x ECO=L




R1163x281x ECO=H




R1163x281x ECO=L












R1163x401x ECO=H




R1163x401x ECO=L




5) Supply Current vs. Temperature**R1163x151x ECO=H****R1163x151x ECO=L****R1163x281x ECO=H****R1163x281x ECO=L****R1163x401x ECO=H****R1163x401x ECO=L**







6) Standby Current vs. Input Voltage**7) Reverse Current vs. Output Voltage****8) Dropout Voltage vs. Output Current**

R1163x151x ECO=H




R1163x151x ECO=L




R1163x161x ECO=H**R1163x161x ECO=L****R1163x171x ECO=H****R1163x171x ECO=L****R1163x181x ECO=H****R1163x181x ECO=L**

R1163x


R1163x211x ECO=H




R1163x211x ECO=L




R1163x281x ECO=H




R1163x281x ECO=L



R1163x401x ECO=H




R1163x401x ECO=L




9) Dropout Voltage vs. Set Output Voltage

R1163x ECO=H




R1163x ECO=L




10) Ripple Rejection vs. Input Bias Voltage


R1163x281x ECO=H




R1163x281x ECO=H



R1162x281x ECO=H




R1162x281x ECO=H




R1163x

R1163x281x ECO=H




R1163x281x ECO=H




11) Ripple Rejection vs. Frequency


R1163x151x ECO=H




R1163x151x ECO=L




R1163x281x ECO=H




R1163x281x ECO=L



R1163x401x ECO=H




R1163x401x ECO=L




12) Input Transient Response


R1163x151x ECO=H




R1163x151x ECO=L



R1163x151x ECO=L




R1163x281x ECO=H




R1163x

R1163x281x ECO=H




13) Load Transient Response


R1163x151x ECO=H




R1163x151x ECO=H









R1163x151x ECO=H




R1163x151x ECO=H






R1163x

R1163x281x ECO=L




R1163x281x ECO=L




14) Turn on speed with CE pin


R1163x151x ECO=H




R1163x151x ECO=L




R1163x151x ECO=H




R1163x151x ECO=L




R1163x151x ECO=H




R1163x151x ECO=L




R1163x281x ECO=H




R1163x281x ECO=L



R1163x281x ECO=H




R1163x281x ECO=L




R1163x


R1163x281x ECO=H




R1163x281x ECO=L




R1163x401x ECO=H




R1163x401x ECO=L




R1163x401x ECO=H




R1163x401x ECO=L



R1163x401x ECO=H




R1163x401x ECO=L




15) Turn off speed with CE pin


R1163x151xD



R1163x281xD



R1163x401xD




R1163x

16) Output Voltage at Mode alternative point




R1163x151B/D

$V_{IN}=2.5V$, $C_{IN}=\text{Ceramic } 1.0\mu F$,
 $C_{OUT}=\text{Ceramic } 0.47\mu F$



R1163x281B/D

$V_{IN}=3.8V$, $C_{IN}=\text{Ceramic } 1.0\mu F$,
 $C_{OUT}=\text{Ceramic } 0.47\mu F$



TECHNICAL NOTES





When using these ICs, consider the following points:

In these ICs, phase compensation is made for securing stable operation even if the load current is varied. For this purpose, be sure to use a capacitor C_{OUT} with good frequency characteristics and ESR (Equivalent Series Resistance) in the range described as follows:

The relations between I_{OUT} (Output Current) and ESR of Output Capacitor are shown below. The conditions when the white noise level is under $40\mu V$ (Avg.) are marked as the hatched area in the graph.

<Test conditions>


(1) Frequency band: 10Hz to 2MHz




- SOT-23-5 (SC-74A)

Unit: mm

PACKAGE DIMENSIONS




TAPING SPECIFICATION



TAPING REEL DIMENSIONS REUSE REEL (EIAJ-RRM-08Bc)

(1reel=3000pcs)

**RICOH**

POWER DISSIPATION (SOT-23-5)

This specification is at mounted on board. Power Dissipation (P_D) depends on conditions of mounting on board.

This specification is based on the measurement at the condition below:

(Power Dissipation (SOT-23-5) is substitution of SOT-23-6.)



Measurement Conditions

	Standard Land Pattern
Environment	Mounting on Board (Wind velocity=0m/s)
Board Material	Glass cloth epoxy plastic (Double sided)
Board Dimensions	40mm × 40mm × 1.6mm
Copper Ratio	Top side : Approx. 50%, Back side : Approx. 50%
Through-hole	φ0.5mm × 44pcs

Measurement Result

($T_{opt}=25^{\circ}\text{C}$, $T_{jmax}=125^{\circ}\text{C}$)


	Standard Land Pattern	Free Air
Power Dissipation	420mW	250mW
Thermal Resistance	$\theta_{ja}=(125-25)^{\circ}\text{C}/0.42\text{W}=238^{\circ}\text{C/W}$	400°C/W



Measurement Board Pattern

○ IC Mount Area Unit : mm

RECOMMENDED LAND PATTERN




(Unit: mm)

RICOH


• SON-6

Unit: mm

PACKAGE DIMENSIONS




TAPING SPECIFICATION



TAPING REEL DIMENSIONS REUSE REEL (EIAJ-RRM-08Bc)

(1reel=3000pcs)



POWER DISSIPATION (SON-6)

This specification is at mounted on board. Power Dissipation (P_D) depends on conditions of mounting on board. This specification is based on the measurement at the condition below:



Measurement Conditions

	Standard Land Pattern
Environment	Mounting on Board (Wind velocity=0m/s)
Board Material	Glass cloth epoxy plastic (Double sided)
Board Dimensions	40mm × 40mm × 1.6mm
Copper Ratio	Top side : Approx. 50% , Back side : Approx. 50%
Through-hole	φ0.5mm × 44pcs

Measurement Result

($T_{opt}=25^{\circ}\text{C}$, $T_{jmax}=125^{\circ}\text{C}$)

	Standard Land Pattern	Free Air
Power Dissipation	500mW	250mW
Thermal Resistance	$\theta_{ja}=(125-25^{\circ}\text{C})/0.5\text{W}=200^{\circ}\text{C/W}$	-




Power Dissipation

Measurement Board Pattern

○ IC Mount Area (Unit : mm)

RECOMMENDED LAND PATTERN



RICOH


PACKAGE INFORMATION

PE-DFN(PLP)1616-6-071010


- DFN(PLP)1616-6

Unit: mm

PACKAGE DIMENSIONS




TAPING SPECIFICATION



TAPING REEL DIMENSIONS

(1reel=5000pcs)



RICOH

POWER DISSIPATION (PLP(DFN)1616-6)

This specification is at mounted on board. Power Dissipation (P_D) depends on conditions of mounting on board.

This specification is based on the measurement at the condition below:

(DFN(PLP)1616-6 is a reference value calculated from the DFN(PLP)1820-6 package.)



Measurement Conditions

Standard Land Pattern	
Environment	Mounting on Board (Wind velocity=0m/s)
Board Material	Glass cloth epoxy plastic (Double sided)
Board Dimensions	40mm × 40mm × 1.6mm
Copper Ratio	Top side : Approx. 50% , Back side : Approx. 50%
Through-hole	φ0.54mm × 30pcs

Measurement Result

($T_{opt}=25^{\circ}\text{C}$, $T_{jmax}=125^{\circ}\text{C}$)


Standard Land Pattern	
Power Dissipation	560mW
Thermal Resistance	$\theta_{ja}=(125-25^{\circ}\text{C})/0.56\text{W}=179^{\circ}\text{C/W}$



Measurement Board Pattern

○ IC Mount Area Unit : mm


RECOMMENDED LAND PATTERN



RICOH

R1163N SERIES MARK SPECIFICATION

- SOT-23-5 (SC-74A)



①, ②, ③ : Product Code (refer to Part Number vs. Product Code)

④, ⑤ : Lot Number

- Part Number vs. Product Code


Part Number	Product Code		
	①	②	③
R1163N151B	V	1	5
R1163N161B	V	1	6
R1163N171B	V	1	7
R1163N181B	V	1	8
R1163N191B	V	1	9
R1163N201B	V	2	0
R1163N211B	V	2	1
R1163N221B	V	2	2
R1163N231B	V	2	3
R1163N241B	V	2	4
R1163N251B	V	2	5
R1163N261B	V	2	6
R1163N271B	V	2	7
R1163N281B	V	2	8
R1163N291B	V	2	9
R1163N301B	V	3	0
R1163N311B	V	3	1
R1163N321B	V	3	2
R1163N331B	V	3	3
R1163N341B	V	3	4
R1163N351B	V	3	5
R1163N361B	V	3	6
R1163N371B	V	3	7
R1163N381B	V	3	8
R1163N391B	V	3	9
R1163N401B	V	4	0
R1163N181B5	V	4	1
R1163N281B5	V	4	2
R1163N271B5	V	4	3

Part Number	Product Code		
	①	②	③
R1163N151D	W	1	5
R1163N161D	W	1	6
R1163N171D	W	1	7
R1163N181D	W	1	8
R1163N191D	W	1	9
R1163N201D	W	2	0
R1163N211D	W	2	1
R1163N221D	W	2	2
R1163N231D	W	2	3
R1163N241D	W	2	4
R1163N251D	W	2	5
R1163N261D	W	2	6
R1163N271D	W	2	7
R1163N281D	W	2	8
R1163N291D	W	2	9
R1163N301D	W	3	0
R1163N311D	W	3	1
R1163N321D	W	3	2
R1163N331D	W	3	3
R1163N341D	W	3	4
R1163N351D	W	3	5
R1163N361D	W	3	6
R1163N371D	W	3	7
R1163N381D	W	3	8
R1163N391D	W	3	9
R1163N401D	W	4	0
R1163N181D5	W	4	1
R1163N281D5	W	4	2

Part Number	Product Code		
	①	②	③
R1163N151E	3	1	F
R1163N161E	3	1	G
R1163N171E	3	1	H
R1163N181E	3	1	J
R1163N191E	3	1	K
R1163N201E	3	2	A
R1163N211E	3	2	B
R1163N221E	3	2	C
R1163N231E	3	2	D
R1163N241E	3	2	E
R1163N251E	3	2	F
R1163N261E	3	2	G
R1163N271E	3	2	H
R1163N281E	3	2	J
R1163N291E	3	2	K
R1163N301E	3	3	A
R1163N311E	3	3	B
R1163N321E	3	3	C
R1163N331E	3	3	D
R1163N341E	3	3	E
R1163N351E	3	3	F
R1163N361E	3	3	G
R1163N371E	3	3	H
R1163N381E	3	3	J
R1163N391E	3	3	K
R1163N401E	3	4	A
R1163N181E	3	4	B
R1163N281E	3	4	C
R1163N271E	3	4	D

R1163D SERIES MARK SPECIFICATION

• SON-6



①, ② : Product Code (refer to Part Number vs. Product Code)

③, ④ : Lot Number

• Part Number vs. Product Code


Part Number	Product Code	
	①	②
R1163D151B	S	5
R1163D161B	S	6
R1163D171B	S	7
R1163D181B	S	8
R1163D191B	S	9
R1163D201B	T	0
R1163D211B	T	1
R1163D221B	T	2
R1163D231B	T	3
R1163D241B	T	4
R1163D251B	T	5
R1163D261B	T	6
R1163D271B	T	7
R1163D281B	T	8
R1163D291B	T	9
R1163D301B	U	0
R1163D311B	U	1
R1163D321B	U	2
R1163D331B	U	3
R1163D341B	U	4
R1163D351B	U	5
R1163D361B	U	6
R1163D371B	U	7
R1163D381B	U	8
R1163D391B	U	9
R1163D401B	V	0
R1163D181B5	V	1
R1163D281B5	V	2
R1163D271B5	V	3

Part Number	Product Code	
	①	②
R1163D151D	W	5
R1163D161D	W	6
R1163D171D	W	7
R1163D181D	W	8
R1163D191D	W	9
R1163D201D	X	0
R1163D211D	X	1
R1163D221D	X	2
R1163D231D	X	3
R1163D241D	X	4
R1163D251D	X	5
R1163D261D	X	6
R1163D271D	X	7
R1163D281D	X	8
R1163D291D	X	9
R1163D301D	Y	0
R1163D311D	Y	1
R1163D321D	Y	2
R1163D331D	Y	3
R1163D341D	Y	4
R1163D351D	Y	5
R1163D361D	Y	6
R1163D371D	Y	7
R1163D381D	Y	8
R1163D391D	Y	9
R1163D401D	Z	0
R1163D181D5	Z	1
R1163D281D5	Z	2

Part Number	Product Code	
	①	②
R1163D151E	0	5
R1163D161E	0	6
R1163D171E	0	7
R1163D181E	0	8
R1163D191E	0	9
R1163D201E	1	0
R1163D211E	1	1
R1163D221E	1	2
R1163D231E	1	3
R1163D241E	1	4
R1163D251E	1	5
R1163D261E	1	6
R1163D271E	1	7
R1163D281E	1	8
R1163D291E	1	9
R1163D301E	2	0
R1163D311E	2	1
R1163D321E	2	2
R1163D331E	2	3
R1163D341E	2	4
R1163D351E	2	5
R1163D361E	2	6
R1163D371E	2	7
R1163D381E	2	8
R1163D391E	2	9
R1163D401E	3	0
R1163D181E5	3	1
R1163D281E5	3	2
R1163D271E5	3	3

R1163K SERIES MARK SPECIFICATION

- DFN(PLP)1616-6



①~④ : Product Code (refer to Part Number vs. Product Code)

⑤, ⑥ : Lot Number

- Part Number vs. Product Code

Part Number	Product Code			
	①	②	③	④
R1163K151B	M	1	5	B
R1163K161B	M	1	6	B
R1163K171B	M	1	7	B
R1163K181B	M	1	8	B
R1163K191B	M	1	9	B
R1163K201B	M	2	0	B
R1163K211B	M	2	1	B
R1163K221B	M	2	2	B
R1163K231B	M	2	3	B
R1163K241B	M	2	4	B
R1163K251B	M	2	5	B
R1163K261B	M	2	6	B
R1163K271B	M	2	7	B
R1163K281B	M	2	8	B
R1163K291B	M	2	9	B
R1163K301B	M	3	0	B
R1163K311B	M	3	1	B
R1163K321B	M	3	2	B
R1163K331B	M	3	3	B
R1163K341B	M	3	4	B
R1163K351B	M	3	5	B
R1163K361B	M	3	6	B
R1163K371B	M	3	7	B
R1163K381B	M	3	8	B
R1163K391B	M	3	9	B
R1163K401B	M	4	0	B
R1163K181B5	M	1	8	5
R1163K281B5	M	2	8	5
R1163K271B5	M	2	7	5

Part Number	Product Code			
	①	②	③	④
R1163K151D	N	1	5	D
R1163K161D	N	1	6	D
R1163K171D	N	1	7	D
R1163K181D	N	1	8	D
R1163K191D	N	1	9	D
R1163K201D	N	2	0	D
R1163K211D	N	2	1	D
R1163K221D	N	2	2	D
R1163K231D	N	2	3	D
R1163K241D	N	2	4	D
R1163K251D	N	2	5	D
R1163K261D	N	2	6	D
R1163K271D	N	2	7	D
R1163K281D	N	2	8	D
R1163K291D	N	2	9	D
R1163K301D	N	3	0	D
R1163K311D	N	3	1	D
R1163K321D	N	3	2	D
R1163K331D	N	3	3	D
R1163K341D	N	3	4	D
R1163K351D	N	3	5	D
R1163K361D	N	3	6	D
R1163K371D	N	3	7	D
R1163K381D	N	3	8	D
R1163K391D	N	3	9	D
R1163K401D	N	4	0	D
R1163K181D5	N	1	8	5
R1163K281D5	N	2	8	5
R1163K271D5	N	2	7	5

RICOH