

Data Sheet Supplement Version 3.0 (valid for 8" product)

Dynamic Differential Hall Effect Sensor

TLE4928C

For all parameters not specified in this document the TLE4925/25C data sheet is valid.



Туре	Marking	Ordering Code	Package
TLE4928C	28C	SP000269349	PG-SSO-3-9



1 TLE4928C

1.1 Operating Range

No.	Parameter	Symbol	min	typ	max	Unit	Remarks
1.1.1	Power on time	t _{on}			1	ms	Time to achieve
							specified accuracy
							After power on the
							output of the IC is
							always in high-state.
							After internal resets
							output is locked ¹ .

1.2 AC/DC Characteristics

Note: Not part of production testing, verified by design and characterization.

No.	Parameter	Symbol	min	typ	max	Unit	Remarks
1.2.1	Frequency range	f	0.006		8	kHz	Operation below 6Hz ²
1.2.2	Offset recalibration time after last output change	t _{reset}	165	195	225	ms	Valid for calibrated mode
							Output locked to state
							before recalibration

 $^{^1}$ Output of the IC is locked in present state (high-state or low-state) after an internal reset is launched. This reset happens typically every 195ms when there is no output switching in either case. See also 1.2.2. A voltage reset causes a release of the output and output is in high state after power on again. 2 output will switch if magnetic signal is changing more that $2x \left| \Delta B_{min} \right|$ within offset recalibration time even below 6Hz once per magnetic edge, increased phase error is possible



Revision	History:	April 2007	Version 3.0		
Previous Ve	ersion: 2.0				
Page	Subjects (major changes since last revision)				
1	Data sheet is valid for 8" products				
1	Ordering code added				

Infineon Technologies AG © Infineon Technologies AIM SC All Rights Reserved.

http://www.infineon.com/products/sensors

We Listen to Your Comments

Any information within this document that you feel is wrong, unclear or missing at all? Your feedback will help us to continuously improve the quality of this document. Please send your proposal (including a reference to this document) to:

Sensors@infineon.com

$\overline{}$
\sim
\leq