

Linear Systems replaces discontinued Siliconix 2N4118

The LS4118 is an Ultra-High Input Impedance N-Channel JFET

<p>The LS4118 provides ultra-high input impedance. The device is specified with a 10-pA limit and is ideal for use as a high-impedance sensitive front-end amplifier.</p> <p>LS4118 Benefits:</p> <ul style="list-style-type: none"> Insignificant Signal Loss/Error Voltage with High-Impedance Source Low Power Consumption (Battery) Maximum Signal Output, Low Noise High Sensitivity to Low-Level Signals <p>LS4118 Applications:</p> <ul style="list-style-type: none"> High-Impedance Transducer Smoke Detector Input Infrared Detector Amplifier Precision Test Equipment 	<p>FEATURES</p> <p>DIRECT REPLACEMENT FOR SILICONIX 2N4118</p> <table border="1"> <tr> <td>LOW POWER</td> <td>$I_{DSS} < 90 \mu A$</td> </tr> <tr> <td>MINIMUM CIRCUIT LOADING</td> <td>$I_{GSS} < 10 pA$</td> </tr> </table> <p>ABSOLUTE MAXIMUM RATINGS @ 25°C (unless otherwise noted)</p> <p>Maximum Temperatures</p> <table border="1"> <tr> <td>Storage Temperature</td> <td>-65°C to +175°C</td> </tr> <tr> <td>Operating Junction Temperature</td> <td>-55°C to +150°C</td> </tr> </table> <p>Maximum Power Dissipation</p> <table border="1"> <tr> <td>Continuous Power Dissipation</td> <td>300mW</td> </tr> </table> <p>MAXIMUM CURRENT</p> <table border="1"> <tr> <td>Gate Current (Note 1)</td> <td>50mA</td> </tr> </table> <p>MAXIMUM VOLTAGES</p> <table border="1"> <tr> <td>Gate to Drain or Gate to Source (Note 2)</td> <td>-40V</td> </tr> </table>	LOW POWER	$I_{DSS} < 90 \mu A$	MINIMUM CIRCUIT LOADING	$I_{GSS} < 10 pA$	Storage Temperature	-65°C to +175°C	Operating Junction Temperature	-55°C to +150°C	Continuous Power Dissipation	300mW	Gate Current (Note 1)	50mA	Gate to Drain or Gate to Source (Note 2)	-40V
LOW POWER	$I_{DSS} < 90 \mu A$														
MINIMUM CIRCUIT LOADING	$I_{GSS} < 10 pA$														
Storage Temperature	-65°C to +175°C														
Operating Junction Temperature	-55°C to +150°C														
Continuous Power Dissipation	300mW														
Gate Current (Note 1)	50mA														
Gate to Drain or Gate to Source (Note 2)	-40V														

LS4118 ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTIC	MIN	TYP.	MAX	UNITS	CONDITIONS
BV_{GSS}	Gate to Source Breakdown Voltage	-40	--	-	V	$I_G = -1 \mu A, V_{DS} = 0V$
$V_{GS(off)}$	Gate to Source Cutoff Voltage	-1	--	-3	V	$V_{DS} = 10V, I_D = 1nA$
I_{DSS}	Gate to Source Saturation Current	0.08	--	0.24	mA	$V_{DS} = 10V, V_{GS} = 0V$
I_{GSS}	Gate Leakage Current	--	--	-10	pA	$V_{GS} = -20V, V_{DS} = 0V$
g_{fs}	Forward Transconductance (Note 3)	80	--	250	μmho	$V_{GS} = -20V, V_{DS} = 0V, 150^\circ C$
g_{os}	Output Conductance	--	--	5		$V_{DS} = 10V, V_{GS} = 0V, f = 1kHz$
C_{iss}	Input Capacitance	--	--	3	pF	$V_{DS} = 10V, V_{GS} = 0V, f = 1MHz$
C_{rss}	Reverse Transfer Capacitance	--	--	1.5		

NOTES	1. Absolute maximum ratings are limiting values above which LS4118 serviceability may be impaired. 2. Due to symmetrical geometry, these units may be operated with source and drain leads interchanged 3. This parameter is measured during a 2ms interval 100ms after power is applied. (Not a JEDEC condition.)
--------------	--

Micross Components Europe



Tel: +44 1603 788967

Email: chipcomponents@micross.com

Web: <http://www.micross.com/distribution>

Available Packages:

LS4118 in SOT-23
 LS4118 in bare die.

Please contact Micross for full package and die dimensions

SOT-23 (Top View)

