


### DESCRIPTION

The AMC3100 is a high efficiency synchronous buck DC/DC converter using a constant frequency, current mode architecture. Adjustable version and fixed output voltages of 1.2V, 1.5V and 1.8V are available. 300uA low supply current at no load and <1uA supply current at shutdown. The 2.5V to 5.5V input voltage range makes the AMC3100 ideally suited for single Li-Ion battery-powered applications. 100% duty cycle provides low dropout operation, extending battery life in portable systems. PWM pulse skipping mode operation provides very low output ripple voltage for noise sensitive applications.

Switching frequency is internally set at 1.5MHz, allowing using small surface mount inductors and capacitors. The internal synchronous switch increases efficiency and eliminates the need for an external Schottky diode. Low output voltages are easily supported with the 0.6V feedback reference voltage.

The AMC3100 is available in a low profile (1mm) Thin SOT-23-5L package.

### TYPICAL APPLICATION



### SYMBOLIZATION

| Device Name     | Output Voltage | Marking |
|-----------------|----------------|---------|
| AMC3100DBFT     | Adjustable     | A64A    |
| AMC3100-1.2DBFT | 1.2V Fixed     | A642    |
| AMC3100-1.5DBFT | 1.5V Fixed     | A645    |
| AMC3100-1.8DBFT | 1.8V Fixed     | A648    |


### FEATURES

- **High Efficiency: Up to 96%**
- **600mA Output Current at  $V_{IN}=3V$**
- **2.5V to 5.5V Input Voltage Range**
- **1.5MHz Constant Switching Frequency**
- **No Schottky Diode Required**
- **100% Duty Cycle as Low Dropout Operation**
- **0.6V Reference Voltage Allows 0.6V Minimum Output Voltage**
- **<1uA Shutdown Mode Supply Current**
- **Current Mode Operation for Excellent Line and Load Transient Response**
- **Over-temperature Protected**
- **4KV HBM ESD Protection**
- **5-Pin Thin SOT-23 package**

### APPLICATIONS

- PDA, Personal Media Player
- Smart Phone
- Digital Still Camera, Video Camcorder
- Portable Instruments
- Bluetooth Headset

### PACKAGE PIN OUT



**TSOT-23-5L  
( Top View )**

\* Note:  $V_{FB}$  pin for adjustable version.  
 $V_{OUT}$  pin for fixed voltage version.

### ORDER INFORMATION


|  |                                       |
|--|---------------------------------------|
| <b>DB</b>  | SOT-23                                |
|  | 5-pin                                 |
|  | <b>AMC3100DBF</b> (Adjustable)        |
|  | <b>AMC3100-X.XDBF</b> (Fixed Voltage) |
| Note: 1. All surface-mount packages are available in Tape & Reel. Append the letter "T" to part number (i.e. AMC3100-1.8DBFT).<br>2. The letter "F" is marked for Lead Free process. |                                       |

**PIN DESCRIPTION**

| Pin Number | Pin Name                       | Pin Function   |
|------------|--------------------------------|--|
| 1          | RUN                            | Enable pin. Higher than 1.5V to turn on the device. Lower than 0.3V to turn it off. The shutdown mode supply current less than $<1\mu\text{A}$ supply current. This pin should not be floating.  |
| 2          | GND                            | Ground   |
| 3          | SW                             | Power Switch Output. Connects to the drains of the internal P-CH and N-CH MOSFET switches.   |
| 4          | $V_{\text{IN}}$                | Supply Input Pin.  |
| 5          | $V_{\text{FB}}/V_{\text{OUT}}$ | $V_{\text{FB}}$ (AMC3100): Feedback Input Pin. Connect $V_{\text{FB}}$ to the center point of the external resistor divider. The feedback threshold voltage is 0.6V.<br>$V_{\text{OUT}}$ (AMC3100-X.X): Output Voltage Feedback Pin. An internal resistive divider divides the output voltage down for comparison to the internal reference voltage. |

**PACKAGE THERMAL DATA**

|   |           |
|---|-----------|
| Thermal Resistance from Junction to Ambient, $\theta_{\text{JA}}$   | 250 °C /W |
| Note :<br>Junction Temperature Calculation: $T_j = T_A + (P_D \times \theta_{\text{JA}})$ .<br>$P_D$ : Power Dissipation, $T_A$ : Ambient temperature, $\theta_{\text{JA}}$ : Thermal Resistance-Junction to Ambient<br>The $\theta_{\text{JA}}$ numbers are guidelines for the thermal performance of the device/PC-board system.<br>All of the above assume no ambient airflow. |           |

**BLOCK DIAGRAM**

**ABSOLUTE MAXIMUM RATINGS** (Note 1)

|  |                       |
|--|-----------------------|
| Input Voltage, $V_{IN}$                  | -0.3V to 6V           |
| RUN, $V_{FB}$ Voltage                    | -0.3V to $V_{IN}$     |
| SW Voltage                               | -0.3 to $V_{IN}+0.3V$ |
| P-Channel Switch Source Current (DC)     | 800mA                 |
| N-Channel Switch Sink Current (DC)       | 800mA                 |
| Peak SW Sink and Source Current          | 1.3A                  |
| Operating Temperature Range (Note 2)     | -40°C to 85°C         |
| Junction Temperature, $T_J$ (Note 3)     | 125°C                 |
| Storage Temperature Range                | -60°C to 150°C        |
| Lead Temperature (soldering, 10 seconds) | 300°C                 |

Note 1: Absolute Maximum Ratings are those values beyond which the life of a device may be impaired.

Note 2: The AMC3100 is guaranteed to meet performance specifications from 0°C to 70°C. Specifications over the -40°C to 85°C operating temperature range are assured by design, characterization and correlation with statistical process controls.

Note 3:  $T_J$  is calculated from the ambient temperature  $T_A$  and power dissipation  $P_D$  according to the following formula:










$$T_J = T_A + (P_D \times \theta_{JA}).$$










**RECOMMENDED OPERATING CONDITIONS**




| Parameter                            | Symbol   | Min | Typ | Max | Unit |
|--------------------------------------|----------|-----|-----|-----|------|
| Supply Voltage                       | $V_{IN}$ | 2.5 |     | 5.5 | V    |
| Operating free-air temperature range | $T_A$    | -40 |     | 85  | °C   |

**ELECTRICAL CHARACTERISTICS**

| $V_{IN}=3.6V, T_A=25^{\circ}C$ . (Unless otherwise noted) |                  |  |        |            |          |          |
|---|------------------|--|--------|------------|----------|----------|
| Parameter   | Symbol           | Condition  | Min    | Typ        | Max      | Unit     |
| Input DC Supply Current<br>Active Mode                    | $I_S$            | $V_{FB}=0.5V$ or $V_{OUT}=90\%$ ,<br>$I_{LOAD}=0A$                   |        | 300        | 400      | $\mu A$  |
|   |                  | Shutdown<br>$V_{RUN}=0V, V_{IN}=4.2V$                                |        | 0.1        | 1        |          |
| Regulated Output Voltage                                  | $V_{OUT}$        | AMC3100-1.8, $I_{OUT}=100mA$   | 1.746  | 1.800      | 1.854    | V        |
|   |                  | AMC3100-1.5, $I_{OUT}=100mA$   | 1.455  | 1.500      | 1.545    |          |
|   |                  | AMC3100-1.2, $I_{OUT}=100mA$   | 1.164  | 1.200      | 1.236    |          |
| Output Voltage Line Regulation                            | $\Delta V_{OUT}$ | $V_{IN}=2.5V$ to $5.5V$  |        | 0.04       | 0.4      | %V       |
| Output Voltage Load Regulation                            | $V_{LDREG}$      |  |        | 0.5        |          | %        |
| Peak Inductor Current                                     | $I_{PK}$         | Duty Cycle < 35%, $V_{IN}=3V$ ,<br>$V_{FB}=0.5V$ or $V_{OUT}=90\%$ , | 0.75   | 1          | 1.25     | A        |
| Feedback Current  | $I_{VFB}$        |  |        |            | $\pm 30$ | nA       |
| Regulated Feedback Voltage                                | $V_{FB}$         | $T_A=25^{\circ}C$  | 0.5880 | 0.6        | 0.6120   | V        |
|   |                  | $T_A=0^{\circ}C \leq T_A \leq 85^{\circ}C$                           | 0.5865 | 0.6        | 0.6135   |          |
|   |                  | $T_A=-40^{\circ}C \leq T_A \leq 85^{\circ}C$                         | 0.5850 | 0.6        | 0.6150   |          |
| Reference Voltage Line Regulation                         | $\Delta V_{FB}$  | $V_{IN}=2.5V$ to $5.5V$  |        | 0.04       | 0.4      | %V       |
| Oscillator Frequency                                      | $f_{OSC}$        | $V_{FB}=0.6V$ or $V_{OUT}=100\%$                                     | 1.2    | 1.5        | 1.8      | MHz      |
| $R_{DS(ON)}$ of P-Channel FET                             | $R_{PFET}$       | $I_{SW}=100mA$   |        | 0.4        | 0.5      | $\Omega$ |
| $R_{DS(ON)}$ of N-Channel FET                             | $R_{NFET}$       | $I_{SW}=-100mA$  |        | 0.35       | 0.45     | $\Omega$ |
| SW Leakage  | $I_{LSW}$        | $V_{RUN}=0V, V_{SW}=0V$ or $5V$ ,<br>$V_{IN}=5V$                     |        | $\pm 0.01$ | $\pm 1$  | $\mu A$  |
| RUN Threshold   | $V_{RUN}$        |  | 0.3    | 1          | 1.5      | V        |
| RUN Leakage Current                                       | $I_{RUN}$        |  |        | $\pm 0.01$ | $\pm 1$  | $\mu A$  |

**CHARACTERIZATION CURVES**






**APPLICATION INFORMATION**

The basic AMC3100 application circuit is shown in Figure 1. External component selection is driven by load requirement:

**Adjustable Output Voltage:**

In adjustable version, the output voltage is set by the below formula (1):

$$V_{OUT} = 0.6V \left( 1 + \frac{R1}{R2} \right) \quad 0.6V \leq V_{OUT} \leq 5.5V \quad (1)$$

The external resistor divider sets the output voltage (see figure 1). Choose R1 around 1MΩ, R2 is then given by:

$$R2 = \frac{R1}{\left( \frac{V_{OUT}}{0.6V} - 1 \right)}$$




Figure 1

Table 1- Resistor Selection vs. Adjust Output Voltage.

| V <sub>OUT</sub> | R1      | R2        |
|------------------|---------|-----------|
| 1.2V             | 1MΩ, 1% | 1MΩ, 1%   |
| 1.5V             | 1MΩ, 1% | 667KΩ, 1% |
| 1.8V             | 1MΩ, 1% | 500KΩ, 1% |
| 2.5V             | 1MΩ, 1% | 316KΩ, 1% |
| 3.3V             | 1MΩ, 1% | 222KΩ, 1% |

**Inductor selection:**

For most applications, the value of the inductor will fall in the range of 1uH to 4.7uH. Its value is chosen based on the desired ripple current. Large value inductors lower ripple current, and small value inductors result in higher ripple currents.


Higher V<sub>IN</sub> or V<sub>OUT</sub> also increases the ripple current as shown in the formula (2):

$$\Delta I_L = \frac{V_{OUT}}{fL} \left( 1 - \frac{V_{OUT}}{V_{IN}} \right) \quad \text{Where, } f = \text{operating frequency, and } \Delta I_L = \text{ripple current in the inductor.} \quad (2)$$

**C<sub>OUT</sub> selection:**

The output capacitor keeps output voltage ripple small and ensures regulation loop stable. The output capacitor impedance shall be low in switching frequency. The output ripple ΔV<sub>OUT</sub> approximately:

$$\Delta V_{OUT} \cong \Delta I_L \left( ESR + \frac{1}{8fC_{OUT}} \right) \quad \text{Where, } C_{OUT} = \text{output capacitance.}$$

**PACKAGE**
**TSOT-23-5L**


**IMPORTANT NOTICE**

ADDtek reserves the right to make changes to its products or to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

A few applications using integrated circuit products may involve potential risks of death, personal injury, or severe property or environmental damage. ADDtek integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life-support applications, devices or systems or other critical applications. Use of ADDtek products in such applications is understood to be fully at the risk of the customer. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

ADDtek assumes no liability to customer product design or application support. ADDtek warrants the performance of its products to the specifications applicable at the time of sale.

---

**ADDtek Corp.**  
9F, No. 20, Sec. 3, Bade Rd., Taipei, Taiwan, 105  
TEL: 2-25700299  
FAX: 2-25700196

---