

<p>PIN 1 TYPE B</p> <p>PIN 1 TYPE A</p> <p>A B</p> <p>.100 [2.54]</p> <p>.098 [2.50]</p> <p>.025 [0.64] SQ</p>	<p>A = .100 [2.54] X No. of Positions. B = .100 [2.54] X No. of Spaces.</p> <p>.130 [3.30]</p> <p>.197 [5.00]</p> <p>C</p>	<p><b>PH1</b> SMT-SINGLE ROW</p> <p><b>PH1-15-UA-SMT-B</b></p> <p>Recommended PCB Layout</p> <p>SMT-A</p> <p>SMT-B</p>
<p>PIN 2</p> <p>PIN 1</p> <p>A B</p> <p>.100 [2.54]</p> <p>.197 [5.00]</p> <p>.025 [0.64] SQ</p>	<p>A = .100 [2.54] X No. of Positions per row. B = .100 [2.54] X No. of Spaces.</p> <p>.130 [3.30]</p> <p>.295 [7.50]</p> <p>C</p>	<p><b>PH2</b> SMT-DUAL ROW</p> <p><b>PH2-26-UA-SMT</b></p> <p>Recommended PCB Layout</p>
<p>PIN 1</p> <p>A B</p> <p>.100 [2.54]</p> <p>.180 [4.57]</p> <p>.098 [2.50]</p>	<p>A = .100 [2.54] X No. of Positions. B = .100 [2.54] X No. of Spaces.</p> <p>0.154 [3.90]</p> <p>C</p>	<p><b>PH1RB</b> SMT-SINGLE ROW</p> <p><b>PH1RB-10-UA-SMT</b></p> <p>Recommended PCB Layout</p>
<p>PIN 2</p> <p>PIN 1</p> <p>A B</p> <p>.100 [2.54]</p> <p>.197 [5.00]</p> <p>.180 [4.57]</p>	<p>A = .100 [2.54] X No. of Positions per row. B = .100 [2.54] X No. of Spaces.</p> <p>.100 [2.54]</p> <p>C</p>	<p><b>PH2RA</b> SMT-DUAL ROW</p> <p><b>PH2RA-20-UA-SMT</b></p> <p>Recommended PCB Layout</p>