

# MICRO

**ELECTRONICS**

**BC143**

GENERAL DESCRIPTION :

The BC143 is a PNP silicon planar epitaxial transistor. It features low saturation voltage, low collector cutoff current and high breakdown voltage. It is intended for use in driver stage of high power audio amplifiers. It can be supplied together with BC144 as a matched pair.

MECHANICAL OUTLINE



ABSOLUTE MAXIMUM RATINGS :

Continuous Power Dissipation @ $T_A=25^\circ\text{C}$ , $P_{\text{max}}$	0.8W
Continuous Power Dissipation @ $T_A=45^\circ\text{C}$ , $P_{\text{max}}$	0.708W
Continuous Power Dissipation @ $T_C=25^\circ\text{C}$ , $P_{\text{max}}$	4W
Continuous Power Dissipation @ $T_C=75^\circ\text{C}$ , $P_{\text{max}}$	2.86W
Maximum Collector Junction Temperature, $T_j$	200°C
Storage Temperature Range, $T_{\text{stg}}$	-55°C to +200°C
Soldering Temperature (10 sec. time limit)	260°C
Continuous Collector Current, $I_C^{\text{max}}$	-1A
Collector-Base Voltage, $V_{\text{CBO}}$	-60V
Collector-Emitter Voltage, $V_{\text{CEO}}$	-60V
Emitter-Base Voltage, $V_{\text{EBO}}$	-5V

ELECTRICAL CHARACTERISTICS @  $T_A=25^\circ\text{C}$  (unless otherwise stated) :

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
Collector-Base Breakdown Voltage	$BV_{\text{CBO}}$	-60			V	$I_C=-10\mu\text{A}$ $I_E=0$
Collector-Emitter Breakdown Voltage	$LV_{\text{CEO}}$	-60			V	$I_C=-10\text{mA}$ $I_B=0$
Emitter-Base Breakdown Voltage	$BV_{\text{EBO}}$	-5			V	$I_E=-10\mu\text{A}$ $I_C=0$
Collector Cutoff Current	$I_{\text{CBO}}$	-0.1	-50	nA		$V_{\text{CB}}=-30\text{V}$ $I_E=0$
Collector Cutoff Current	$I_{\text{CBO}}$	-0.002	-50	uA		$V_{\text{CB}}=-30\text{V}$ $I_E=0$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$	-0.3			V	$T_A=75^\circ\text{C}$ $I_C=-500\text{mA}$ $I_B=-25\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$	-0.25	-0.5		V	$I_C=-500\text{mA}$ $I_B=-50\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$	-1.2			V	$I_C=-1000\text{mA}$ $I_B=-50\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$	-0.7	-1		V	$I_C=-1000\text{mA}$ $I_B=-100\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$	-0.7			V	$V_{\text{CE}}=-10\text{V}$ $I_C=-10\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$	-0.75			V	$V_{\text{CE}}=-10\text{V}$ $I_C=-100\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$	-0.85			V	$V_{\text{CE}}=-1\text{V}$ $I_C=-300\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$	-0.93			V	$V_{\text{CE}}=-1\text{V}$ $I_C=-500\text{mA}$

**MICRO ELECTRONICS LTD. 美科有限公司**

38, Hung To Road, Microtron Building, Kwun Tong, Kowloon, Hong Kong.  
Kwun Tong P.O. Box 69477 Hong Kong. Fax No. 341 0321 Telex: 43510 Micro Hx. Tel: 343 0181-5

P.T.O.

----- CONTINUE -----

ELECTRICAL CHARACTERISTICS @  $T_A=25^\circ C$  (unless otherwise stated) :

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
D.C. Current Gain	$h_{FE}$		88			$V_{CE}=-10V$ $I_C=-10mA$
D.C. Current Gain	$h_{FE}$		85			$V_{CE}=-10V$ $I_C=-10mA$
D.C. Current Gain	$h_{FE}$	20	40			$V_{CE}=-1V$ $I_C=-300mA$
D.C. Current Gain	$h_{FE}$	15	30			$V_{CE}=-1V$ $I_C=-500mA$
High Frequency Current Gain	$h_{fe}$		1.5			$V_{CE}=-10V$ $I_C=-50mA$ $f=100MHz$
Collector-Base Capacitance BC143-BC144 match pair	$C_{CB}$ $h_{FE}$ ratio		13		pF	$V_{CB}=-10V$ $I_E=0$ $V_{CE}=-1V$ $I_C=-500mA$
		0.8		1.25		