




**SMSC**<sup>™</sup>  
SUCCESS BY DESIGN

**KBC1100L**

## Mobile KBC with SFI, ADC and DAC with SMSC SentinelAlert!<sup>™</sup>



### PRODUCT FEATURES

Data Brief

- 3.3V Operation with 5V Tolerant Buffers
- ACPI 1.0b/2.0 and PC99a/PC2001 Compliant
- LPC Interface with Clock Run Support
  - Serial IRQ Interface Compatible with Serialized IRQ Support for PCI Systems
  - 15 Direct IRQs
  - Three 8-Bit DMA Channels
  - ACPI SCI Interface
  - nSMI
  - Shadowed write only registers
- LPC/Firmware Hub Host Flash Interface
  - Single Byte FWH Memory Read and FWH Memory Write Support
  - FWH ID Support
  - 16MB FWH Flash and Register Addressing, 128K Legacy BIOS Addressing
  - Single Byte LPC Memory Read and LPC Memory Write Support
- Serial Peripheral Interface (SPI)
  - 2-pin interface with single Data In/Out Data pin
  - Single Ported Controller with Keeper Circuit
- 8 MByte Shared FlashROM Interface (SFI)
  - 8051/Host CPU Hardware Arbitrated Interface
  - 0.5 - 8MB - Host System BIOS & 8051 Keyboard
  - 8051 64KB Code Space Accessible as Separate 32KB Pages in Flash
  - Low-Power Flash Access Modes
  - 8051-Programmable Flash Access Protection
    - Read/Write/No-Access Protection
    - Variable Bank Sizes
- Host Flash Address Redirection for Recovery
- Serial Flash Programming Interface
- Two Power Planes
  - Low Standby Current in Sleep Mode
  - Intelligent Auto Power Management for Super I/O
  - Main powered blocks power supplied by standby power plane and controlled by power management signals
- 3-Port ACPI Embedded Controller Interface
- Configuration Register Set
  - Compatible with ISA Plug-and-Play Standard (Version 1.0a)
  - Four Pin Selectable Addressing Options
  - 8051-Programmable Base Address
- High-Performance Embedded 8051 Keyboard and System Controller
  - Provides System Power Management
  - System Watch Dog Timer (WDT)
  - 8042 Style Host Interface Relocatable to 480 Different Base I/O Addresses
  - Supports Interrupt and Polling Access
  - Interrupt Accelerator
  - 512 Bytes Data RAM
  - 2 Kilobytes Scratch ROM/RAM
  - On-Chip Memory-Mapped Control Registers
  - Up to 18x8 Keyboard Scan Matrix
  - Two 16 Bit Timer/Counters
  - Eleven 8051 Interrupt Sources
  - Thirty-Two 8-Bit, Host/8051 Mailbox Registers
  - Thirty-six Maskable Hardware Wake-Up Events
  - Fast GATEA20
  - Fast CPU\_RESET
  - Multiple Clock Sources and Operating Frequencies up to 32MHz
  - IDLE and SLEEP Modes
  - Low Power Fail-Safe Ring Oscillator  $\pm 10\%$  Accuracy
  - Hibernation Timer with programmable wake-up from 0.5ms to 128 minutes
  - 8051-Driven 16550A UART
    - 16-Byte Send/Receive FIFOs
    - External Baud Clock Option
  - Power-Fail Status Register
- Battery Backed Resources
  - 32KHz clock generator
  - 1 Week Wakeup timer
- One 8584-Style SMBus Controller
  - 8051 Host Interface Logic Allows Master or Slave Operation
  - Controllers are Fully Operational on Standby Power
  - 2 Ports per Controller

- Two independent Hardware Driven PS/2 Ports
  - Fully functional on Main and/or Suspend Power
  - PS/2 edge Wake Capable
  - Wake on specific mouse protocol
  - Wake on specific keyboard protocol
- 72 General Purpose I/O Pins
  - 62 8051 Addressable I/O Pins
  - 7 8051 Addressable Out-only Pins
  - 2 8051 Addressable In-only Pins
  - 16 I/Os Mapped into 8051 SFR Space
  - 1 LPC/8051-Addressable I/O
  - 14 Maskable Hardware Wake-Event Capable
  - 67 Programmable Open-Drain/Push-Pull Outputs
  - 2 SMSC SentinelAlert! Direct Battery Management GPIO's
- Four Programmable Pulse-Width Modulator Outputs
  - Multiple clock Sources and Independent Clock Rates
  - 8 Bit Duty Cycle Granularity
- Three Fan Tachometer Inputs
- Three Programmable 16-bit Counter/Timers
- Direct Battery Management with SMSC SentinelAlert!
  - Analog to Digital Converter with
    - 8 channels, 8b/10b conversion
    - 20ms conversion time for 8 channels
  - Digital to Analog Converter with SMSC SentinelAlert!
    - 3 channels, 8b conversion
    - 1.5ms conversion time for 3 channels
  - 2-GPIO's with SMSC SentinelAlert!
  - 2-Single pin remote temperature sensor inputs
  - HW\_PROTECT# output thermal event indication
- MCU Serial Debug Port
- Integrated Standby Power Reset Generator
- 144 Pin VTQFP Package; Green, Lead-Free Package also available



**ORDER NUMBER(S):**

**KBC1100L-PE FOR 144 PIN, VTQFP PACKAGE; KBC1100L-PU FOR 144 PIN VTQFP PACKAGE (GREEN, LEAD-FREE)**



80 Arkay Drive  
Hauppauge, NY 11788  
(631) 435-6000  
FAX (631) 273-3123

Copyright © SMSC 2005. All rights reserved.

Circuit diagrams and other information relating to SMSC products are included as a means of illustrating typical applications. Consequently, complete information sufficient for construction purposes is not necessarily given. Although the information has been checked and is believed to be accurate, no responsibility is assumed for inaccuracies. SMSC reserves the right to make changes to specifications and product descriptions at any time without notice. Contact your local SMSC sales office to obtain the latest specifications before placing your product order. The provision of this information does not convey to the purchaser of the described semiconductor devices any licenses under any patent rights or other intellectual property rights of SMSC or others. All sales are expressly conditional on your agreement to the terms and conditions of the most recently dated version of SMSC's standard Terms of Sale Agreement dated before the date of your order (the "Terms of Sale Agreement"). The product may contain design defects or errors known as anomalies which may cause the product's functions to deviate from published specifications. Anomaly sheets are available upon request. SMSC products are not designed, intended, authorized or warranted for use in any life support or other application where product failure could cause or contribute to personal injury or severe property damage. Any and all such uses without prior written approval of an Officer of SMSC and further testing and/or modification will be fully at the risk of the customer. Copies of this document or other SMSC literature, as well as the Terms of Sale Agreement, may be obtained by visiting SMSC's website at <http://www.smsc.com>. SMSC is a registered trademark of Standard Microsystems Corporation ("SMSC"). Product names and company names are the trademarks of their respective holders.

**SMSC DISCLAIMS AND EXCLUDES ANY AND ALL WARRANTIES, INCLUDING WITHOUT LIMITATION ANY AND ALL IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE, AND AGAINST INFRINGEMENT AND THE LIKE, AND ANY AND ALL WARRANTIES ARISING FROM ANY COURSE OF DEALING OR USAGE OF TRADE.**

**IN NO EVENT SHALL SMSC BE LIABLE FOR ANY DIRECT, INCIDENTAL, INDIRECT, SPECIAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES; OR FOR LOST DATA, PROFITS, SAVINGS OR REVENUES OF ANY KIND; REGARDLESS OF THE FORM OF ACTION, WHETHER BASED ON CONTRACT; TORT; NEGLIGENCE OF SMSC OR OTHERS; STRICT LIABILITY; BREACH OF WARRANTY; OR OTHERWISE; WHETHER OR NOT ANY REMEDY OF BUYER IS HELD TO HAVE FAILED OF ITS ESSENTIAL PURPOSE, AND WHETHER OR NOT SMSC HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.**

## General Description

---

The KBC1100L is an integrated Keyboard/System Management Controller which incorporates a high-performance 8051 Micro-Controller, an LPC Bus/Firmware Hub Host Interface and a Super I/O. The KBC1100L is powered by two separate supply planes (VCC1, VCC0) to provide “instant on” and sophisticated system power management functions. The KBC1100L power control circuitry supports multiple low power-down modes.


The KBC1100L incorporates a Direct Battery Management (DBM) with SMSC SentinelAlert! accessible by the 8051. Together with external remote temperature sensor(s) can provide complete Analog Monitoring & Control System. The KBC1100L DBM includes an 8 channel ADC, a 3 channel DAC with SMSC SentinelAlert! and up to 2 SMSC SentinelAlert! GPIO's, two channel one-pin Temperature Sensor Communication Links, and a hardware protect output that requires no programming or 8051 intervention to operate.

The KBC1100L incorporates a Standby Power Reset Generator (RESGEN) which monitors the VCC1 power input and generates the internal VCC1 power on reset for the KBC1100L. The KBC1100L also outputs VCC1RST# which can be used to reset the Flash memory on the Shared Flash Interface (SFI).

A block diagram of the KBC1100L including the distribution of the supply planes is shown in [Figure 1 on page 5](#).



# Package Outline



**Figure 2 144 Pin VTQFP Package Outline, 20 x 20 x 1.0 Body 2mm Footprint**

**Table 1 144 Pin VTQFP Package Parameters**

	MIN	NOMINAL	MAX	REMARK
A	~	~	1.20	Overall Package Height
A1	0.05	~	0.15	Standoff
A2	0.95	~	1.05	Body Thickness
D	21.80	~	22.20	X Span
D1	19.80	~	20.20	X Body Size
E	21.80	~	22.20	Y Span
E1	19.80	~	20.20	Y Body Size
H	0.09	~	0.20	Lead Frame Thickness
L	0.45	0.60	0.75	Lead Foot Length
L1	~	1.00	~	Lead Length
e		0.50 BSC.		Lead Pitch
q	0°	~	7°	Lead Foot Angle
W	0.13	0.18	0.23	Lead Width
R1	0.08	~	~	Lead Shoulder Radius
R2	0.08	~	0.20	Lead Foot Radius
ccc	~	~	0.08	Coplanarity

**Notes:**

- Controlling Unit: millimeter.
- Tolerance on the true position of the leads is  $\pm 0.04$  mm maximum.
- Package body dimensions D1 and E1 do not include the mold protrusion. Maximum mold protrusion is 0.25 mm.
- Dimension for foot length L measured at the gauge plane 0.25 mm above the seating plane.
- Details of pin 1 identifier are optional but must be located within the zone indicated.