

## Dual 4-Channel Driver with Oscillator & LVDS



The EL6833 is a high performance, dual output, laser driver for writeable 'super-combo' CD - DVD drives. The

ENA pin enables the chip, while the SEL1 pin selects the I<sub>OUT</sub> pin. Various waveforms can be generated where the amplitude is determined by the currents flowing into I<sub>INR</sub>, I<sub>IN2</sub>, I<sub>IN3</sub>, and I<sub>IN4</sub>. The timing is determined by the signals at WEN2-WEN2B, WEN3-WEN3B, and WEN4-WEN4B. The oscillator is enabled when OSEN-OSENB is high. The amplified I<sub>INR</sub> current of the selected channel is enabled when the ENA pin is high. The total output current is the sum of the read current, the enabled write currents, and the oscillator current when enabled.

Usually a voltage DAC will drive a resistor that is in series with the I<sub>INR</sub>, I<sub>IN2</sub>, I<sub>IN3</sub> and I<sub>IN4</sub> input. The resistor allows the user to optimize the current gain for each channel.

Output write current pulses are enabled when a high is applied to the WEN2-WEN2B, WEN3-WEN3B, or WEN4-WEN4B pin. The write current will flow to the selected output. When SEL1 is high I<sub>OUT1</sub> is selected. WENRB enables read and oscillator current when low.

The R<sub>F</sub> oscillators frequency is determined by R<sub>FREQ1</sub> or R<sub>FREQ2</sub>, and its amplitude by R<sub>AMP1</sub> or R<sub>AMP2</sub>.

### Ordering Information

PART NUMBER	PACKAGE	TAPE & REEL	PKG. DWG. #
EL6833CL	32-Pin QFN	-	MDP0046
EL6833CL-T7	32-Pin QFN	7"	MDP0046
EL6833CL-T13	32-Pin QFN	13"	MDP0046
EL6833CLZ (Note)	32-Pin QFN (Pb-Free)	-	MDP0046
EL6833CLZ-T7 (Note)	32-Pin QFN (Pb-Free)	7"	MDP0046
EL6833CLZ-T13 (Note)	32-Pin QFN (Pb-Free)	13"	MDP0046

NOTE: Intersil Lead-Free products employ special lead-free material sets; molding compounds/die attach materials and 100% matte tin plate termination finish, which is compatible with both SnPb and lead-free soldering operations. Intersil Lead-Free products are MSL classified at lead-free peak reflow temperatures that meet or exceed the lead-free requirements of IPC/JEDEC J Std-020B.

### Features

- Two channels for CD or DVD
- Voltage-controlled output current source requiring one external set resistor per channel
- Rise time = 0.8ns
- Fall time = 0.8ns
- DVD - Channel 2 to 240mA max
- DVD - Channel 3 to 170mA max
- DVD - Channel 4 to 100mA max
- CD - Channel 2 to 350mA max
- CD - Channel 3 to 250mA max
- On chip oscillator with frequency and amplitude control by use of external resistors to ground
- Oscillator frequency to 600MHz
- Oscillator amplitude to 100mA<sub>P-P</sub>
- Single +5V supply (±10%)
- Chip ENAs for power savings
- External LVDS termination
- Pb-free available

### Applications

- Super combo drives

**Get FULL DATASHEET**

All Intersil U.S. products are manufactured, assembled and tested utilizing ISO9000 quality systems.  
Intersil Corporation's quality certifications can be viewed at [www.intersil.com/design/quality](http://www.intersil.com/design/quality)

---

*Intersil products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design, software and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.*

---

For information regarding Intersil Corporation and its products, see [www.intersil.com](http://www.intersil.com)