

Main

| | |
|-------------------------------|--|
| Range of product | Hyde Park |
| Sensor type | Ultrasonic sensor |
| Series name | Superprox + |
| Device short name | SC650 |
| Sensor design | Flat form |
| [Sn] nominal sensing distance | 254 mm |
| Type of sensing window | Configurable |
| Material | Plastic |
| Enclosure material | ULTEM |
| Front material | Silicone rubber |
| Type of output signal | Discrete |
| Wiring technique | 4-wire |
| [Us] rated supply voltage | 12...24 V DC (overload and short-circuit protection) |
| Supply voltage limits | 10...28 V DC |
| Electrical connection | 1 male connector M12 4 pins |
| Product specific application | Discrete proximity |

Complementary

| | |
|---------------------------------|--|
| Maximum differential travel | 0.35 mm |
| Blind zone | 51 mm |
| Transmission frequency | 500 kHz |
| Repeat accuracy | 0.07 % |
| Beam angle | 7 ° |
| Minimum size of detected object | Cylinder diameter 1.59 mm - up to 76.2 mm sensing distance |
| Current consumption | 60 mA |
| Maximum switching current | 100 mA (reverse polarity protection) |
| Height | 16.25 mm |
| Width | 30 mm |
| Depth | 16.25 mm |
| Length | 84.32 mm |
| Product weight | 0.07 kg |

Environment

| | |
|---------------------------------------|--|
| Product certifications | UL |
| Marking | CE |
| NEMA degree of protection | NEMA 4X (indoor use only) |
| IP degree of protection | IP67 |
| Ambient air temperature for operation | 0...60 °C |
| Ambient air temperature for storage | -40...100 °C |
| Relative humidity | 100 % without condensation |
| Vibration resistance | +/-1 mm conforming to IEC 60068-2-6 10...55 Hz |
| Shock resistance | 30 gn in all 3 axes for 11 ms conforming to IEC 60068-2-27 |
| Resistance to electromagnetic fields | 10 V/m (level 3) conforming to IEC 61000-4-3 |
| Resistance to fast transients | 1 kV (level 3) conforming to IEC 61000-4-4 |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.