



The Littelfuse POWR-Switch provides a simple and economical solution for applications that require selective coordination and shunt trip capabilities. Common applications include elevator circuits, data processing rooms, and building emergency systems.

By utilizing Class J time delay fuses, the POWR-Switch is easily coordinated with other system overcurrent devices. The shunt trip capability allows the POWR-Switch to meet the ANSI/ASME standard that requires power to be automatically disconnected before water is turned on by the fire safety system. The POWR-Switch also features pre-wired control circuits that can help reduce installation costs.

STANDARD FEATURES

- 600V 3-pole fuse power switch
- 200,000 RMS interrupting rating
- Shunt trip 120V
- Control power terminal block
- Ground lug per NEC
- Class J fuse block
- NEMA 1 enclosures

OPTIONAL FEATURES

- Control power transformer with fuses and blocks
- Fire safety interface relay
- Key to test switch
- Pilot light "On"
- Isolated neutral lug
- Mechanical interlock auxiliary contact for hydraulic elevators with automatic recall (5 amp 120 VAC rated)
- Fire alarm voltage monitoring relay
- NEMA 3R, 4, and 12 enclosures

BENEFITS

- Optional features offer flexibility for a variety of applications
- UL Listed package
- Lower installation costs than systems with many separate components
- Pre-wired control circuits lower installation time
- Lockable Operating handle meets all code and safety requirements
- No confusion over which building trade is supplying the components
- POWR-Switch is a single unit...which makes procurement easier than systems with multiple components

NEW



ORDERING INFORMATION

Complete catalog numbers consist of switch catalog numbers and the desired options. See example below.

Example Catalog Number:

LPS T8 R1 K N1 U = Littelfuse Catalog Number LPS1T48R1KN1U

Littelfuse Switch Catalog Number		Control Power Transformer Std. 100VA with PRI & SEC Fuse (120V Sec.)		Fire Safety Interface Relay (3PDT, 10amp, 120V)		Key to Test Switch		Pilot Light "ON"		Isolated Neutral Lug		Mechanical Interlock Auxiliary Contact for Hydraulic Elevators w/ Automatic Recall (5 amp 120 VAC rated)		Fire Alarm Voltage Monitoring Relay (Tp Monitor Shunt Trip Voltage)		Optional Enclosures	
Catalog No	Rating	Rating	Option Code	Rating	Option Code	Rating	Option Code	Rating	Option Code	Rating	Option Code	Rating	Option Code	Rating	Option Code	Rating	Option Code
LPS3	30A	208V	T20	24 VDC Coil	R2	120V	K	Red	R	30-60A	N6	1 NO & 1 NC	A	Single Pole	F1	NEMA 3R	U
LPS6	60A	240V	T24	120 VAC Coil	R1			Green	G	100A	N1	2 NO & 2 NC	B	Three Pole	F3	NEMA 4	Y
LPS1	100A	480V	T48					White	W	200A	N2					NEMA 12	Z
LPS2	200A	600V	T60							400A	N4						
LPS4	400A																

Note: Desired options must appear in the order shown above. Typical options include Control Power Transformer, Fire Safety Interface Relay, Mechanical Interlock Auxiliary Contact and Fire Alarm Voltage Monitoring Relay.

SPECIFICATIONS

Approvals: UL Listed and CSA Certified

Rating: 30A, 60A, 100A, 200A, 400A

Shunt Trip Ratings:

Amp Rating	Voltage Rating	Max Inrush	Max Ontime	Momentary Inrush
30-400	120V, 60Hz	4A	1.5 cycles	140VA

ENCLOSURE DIMENSIONS

Catalog Series	Amp Rating	NEMA 1 Dimensions	NEMA 3R Dimensions	NEMA 4, 12 Dimensions	Lug Size
LPS3	30	24"H x 20"W x 9"D	24"H* x 20"W x 8"D	24"H x 20"W x 10"D	#14 - #8 AL or CU
LPS6	60	24"H x 20"W x 9"D	24"H* x 20"W x 8"D	24"H x 20"W x 10"D	#14 - #8 AL or CU
LPS1	100	24"H x 20"W x 9"D	24"H* x 20"W x 8"D	24"H x 20"W x 10"D	#8 - 1/0 AL or CU
LPS2	200	30"H x 20"W x 9"D	30"H* x 20"W x 8"D	24"H x 20"W x 10"D	#6 - 250kcmil AL or CU
LPS4	400	48"H x 36"W x 12"D	Contact Factory	Contact Factory	Contact Factory

Note: Over-size enclosures used to accommodate control power transformer, interface relay and terminal blocks.

*For NEMA 3R enclosures add 2 inches to height for mounting tabs.

