

### Main

|                             |                                   |
|-----------------------------|-----------------------------------|
| Product or component type   | Communication card                |
| Range compatibility         | Altivar 61<br>Altivar 61Q         |
| Communication port protocol | LonWorks                          |
| Connector type              | 1 removable 3-way screw connector |
| Transmission rate           | 78 kbps                           |

### Complementary

|                       |   |
|-----------------------|---|
| Topology              | TP/FT-10 (free topology)  |
| Communication service | LonMark 0000: Node Object<br>LonMark 6010: Variable Speed Motor Drive   |
| Display type          | 1 LED for fault<br>1 LED for service<br>1 LED for status<br>Graphic display terminal for control word received<br>Graphic display terminal for reference received |
| Product weight        | 0.3 kg  |

### Environment

|                          |           |
|--------------------------|-----------|
| RoHS EUR status          | Compliant |
| RoHS EUR conformity date | 1030      |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.