


Low-cost audio/video switch and 4-channel SD video filter

Data brief

Features

- I²C bus control
- Interrupt signal output
- Video section:
 - Three CVBS inputs; two CVBS outputs
 - Two RGB or YPrPb or chroma / one FB input; one RGB or YPrPb or chroma / one FB output
 - 7-MHz low-pass filters on four encoder inputs
 - Gain of 6 dB on all RGB and CVBS outputs
 - Integrated 150-Ω buffers
 - Capabilities of integrated output buffers:
 - CVBS_TV can drive two standard 150-Ω video loads
 - CVBS_VCR can drive one standard 150-Ω video load and one 600-Ω modulator load
 - RGB can drive a standard 150-Ω video load
 - AC- or DC-coupled video outputs
 - Two slow blanking inputs/outputs
 - Bottom clamp on all CVBS and bottom/average/synchronized clamp on RGB inputs
 - AC-coupled inputs for all video signal
 - Crosstalk: 50 dB minimum
- Audio section:
 - Three inputs; two outputs
 - Stereo sound capability
 - One mono sound output
 - Differential or single-ended audio encoder input



- Selectable gain on one stereo input
- Audio muting on the output
- Audio outputs drive 3.1 V RMS into 2 kΩ
- Full-range volume control with soft control
- Audio BSkyB compatible

Applications

- Set-top boxes (IP, cable, satellite, terrestrial)
- Integrated digital TV plug-in
- Blu-ray and DVD players

Description

The STV6419 is a highly integrated I²C bus-controlled audio and video switch matrix, optimized for use in digital set-top box or DVD recorder applications. It provides the audio and video routings (CVBS and RGB) required in a non-full two SCART set-top box design.

The STV6419 is a fully integrated solution for filtering and buffering SD signals.

Table 1. Device summary

Order code	Temperature range	Package	Packaging
STV6419AG	0 to 70 °C	LQFP48 (7 × 7 mm ²)	Tray
STV6419AGT	0 to 70 °C	LQFP48 (7 × 7 mm ²)	Tape and reel

1 Introduction

The STV6419 is an I²C-controlled integrated circuit for switching, filtering and buffering audio and video signals in any dual, non-full SCART application. It can be used in products such as SD and HD set-top boxes or DVD/BD players and recorders for European markets.

It can be connected to four video DAC outputs of an MPEG decoder, allowing simultaneous switching and driving of the composite and RGB signals, or the S-video signal only, to the TV SCART output, as well as the composite signal to the VCR SCART output. Further, the device provides the switching of the composite and RGB signals, or the S-video signals only, from the VCR SCART to the TV SCART.


The STV6419 manages the slow blanking and fast blanking signalling through the I²C bus.

The STV6419 provides the minimum required set of features to support the dual-SCART connector with significant cost reduction over existing solutions (such as STV6417 or competition) and in line with a price-sensitive, soon-to-be-phased-out legacy topology, for which set-top box manufacturers are no longer willing to pay a premium.

The STV6419 is one of the family of five, pin-compatible products (Figure 1) that complete the new generation of audio and video switches and buffers from STMicroelectronics. Together they cover, both technically and price-wise, the whole market spectrum from mid-range SD retail (zapper set-top boxes or basic recorders) up to DVR HD operators (set-top boxes or recorders with SD component output).

Features	Benefits
DC-coupled video inputs.	Reduces component count.
AC- and DC-coupled high-drive capability video outputs (for 70-Ω (minimum) loads).	Connects to any type of display and drives several composite and RF modulator outputs without external active components.
8-step selectable audio gain up to +28 dB, supporting output of 3.1 V RMS (minimum).	Easy fine-tune of THD and SNR depending on requirements, whilst matching any specific audio output level, including China Cable, and saving external op-amps.
Pin-compatibility with four other products.	Combines single-device space-saving (up to 50%) benefits with commodity price/flexibility benefits to allow a single PCB design covering the entire market spectrum.
Pin-compatibility with STV6417AH.	Provides dual-source solution at no cost premium in case of market shortage or sudden rise in demand.
Pin-compatibility with STV6418AH.	Provides dual-source solution at no cost premium in case of market shortage or sudden rise in demand.

Figure 1. Pin-compatible devices



2 Revision history

Table 2. Document revision history

Date	Revision	Changes
06-Oct-2011	1	Initial release.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY TWO AUTHORIZED ST REPRESENTATIVES, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2011 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com