#### TOSHIBA Schottky Barrier Diode

# CMS17

Switching Mode Power Supply Applications Portable Equipment Battery Applications


- Forward voltage:  $V_{FM} = 0.48 V (max)$
- Average forward current: IF(AV) = 2.0 A
- Repetitive peak reverse voltage: VRRM = 30 V
- Suitable for compact assembly due to a small surface-mount package: "M-FLAT<sup>TM</sup>" (Toshiba package name)"

#### Maximum Ratings (Ta = 25°C)

Characteristic	Symbol	Rating	Unit
Repetitive peak reverse voltage	V <sub>RRM</sub>	30	V
Average forward current	I <sub>F (AV)</sub>	2.0 (Note)	А
Nonrepetitive peak surge current	I <sub>FSM</sub>	30 (50 Hz)	А
Junction temperature	Тј	-40~150	°C
Storage temperature range	T <sub>stg</sub>	-40~150	°C

Note:  $Ta = 77^{\circ}C$ 

Device mounted on a ceramic board Board size:  $50 \text{ mm} \times 50 \text{ mm}$ Soldering size:  $2 \text{ mm} \times 2 \text{ mm}$ Board thickness: 0.64 tRectangular waveform ( $\alpha = 180^{\circ}$ ), VR = 15 V



Weight: 0.023 g (typ.)

#### Electrical Characteristics (Ta = 25°C)

Characteristic	Symbol	Test Condition	Min	Тур.	Мах	Unit	
Peak forward voltage	V <sub>FM (1)</sub>	I <sub>FM</sub> = 1.0 A (pulse test)	—	0.42	_	v	
	V <sub>FM (2)</sub>	I <sub>FM</sub> = 2.0 A (pulse test) —		0.45	0.48	v	
Peak repetitive reverse current	I <sub>RRM (1)</sub>	V <sub>RRM</sub> = 5 V (pulse test)	_	0.8		μA	
	I <sub>RRM (2)</sub>	(2) V <sub>RRM</sub> = 30 V (pulse test)		10	100	μΑ	
Junction capacitance	Cj	$V_{R} = 10 V, f = 1.0 MHz$	_	90	_	pF	
Thermal resistance (junction to ambient)		Device mounted on a ceramic board (board size: 50 mm × 50 mm) (soldering land: 2 mm × 2 mm) (board thickness: 0.64 t)			60		
	R <sub>th</sub> (j-a)	Device mounted on a glass-epoxy board (board size: 50 mm × 50 mm) (soldering land: 6 mm × 6 mm) (board thickness: 1.6 t)	_	_	135	°C/W	
		Device mounted on a glass-epoxy board (board size: 50 mm × 50 mm) (soldering land: 2.1 mm × 1.4 mm) (board thickness: 1.6 t)	_	_	210		
Thermal resistance (junction to lead)	R <sub>th (j-ℓ)</sub>	_	_	_	16	°C/W	


Unit: mm

## <u>TOSHIBA</u>

#### Marking

Abbreviation Code	Part No.		
SG	CMS17		


#### **Standard Soldering Pad**




#### **Handling Precaution**

- 1) Schottky barrier diodes have reverse current characteristics compared to other diodes. SBDs can cause thermal runaway when used under high temperature or high voltage conditions. Be sure to take forward and reverse loss into consideration during design.
- 2) The maximum ratings denote the absolute maximum ratings, which are rated values that must not be exceeded during operation, even for an instant. The following are the general derating methods that we recommend for designing a circuit incorporating this device.
  - VRRM: Use this rating with reference to (1) above. VRRM has a temperature coefficient of 0.1%/°C. Take this temperature coefficient into account when designing a device for operation at low temperature.
  - $IF \mbox{ (AV)} \mbox{: We recommend that the worst case current be no greater than 80\% of the maximum rating of IF (AV) and that T_j be below 120°C. When using this device, take the margin into consideration by using an allowable Tamax-IF (AV) curve.}$
  - IFSM: This rating specifies the nonrepetitive peak current. This is applied only for abnormal operation, which seldom occurs during the lifespan of the device.
  - $\begin{array}{ll} T_j & \mbox{ Derate this rating when using the device to ensure high reliability.} \\ We recommend that the device be used at a T_j of below 120 ^{\circ} C. \end{array}$
- 3) Thermal resistance between junction and ambient fluctuates depending on the mounting condition of the device. When using the device, design the circuit board and soldering land size to match the appropriate thermal resistance value.
- 4) Refer to the Rectifiers databook for further information.

### TOSHIBA








Average forward current IF (AV) (A)





#### **RESTRICTIONS ON PRODUCT USE**

030619EAA

- The information contained herein is subject to change without notice.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of TOSHIBA or others.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.

In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..

- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- TOSHIBA products should not be embedded to the downstream products which are prohibited to be produced and sold, under any law and regulations.