



## DIMENSIONS™ | 24VDC In, 1,500W to 5,000W Out Single Phase, Pure Sine DC to AC Power Inverters

### Markets & Applications

- Recommended for 24VDC military applications requiring mobile AC power in a high dust, water intrusive, vibrating environment.

### Features & Highlights

- Cage code: 55YR1
- Pure sine wave, <5% THD typical
- Output: 1500W to 10000W, 120VAC  $\pm$  5%, 60Hz  $\pm$  0.05%
- Operating Temperature: -37°C to 50°C (-35°F to 122°F)
- Heavy-duty conformal coating on circuit boards
- Thermally-controlled cooling fan
- Optional NATO input receptacles
- Optional water fording capability
- Automatic electronic short circuit/overload protection
- Automatic high temperature shutdown
- Automatic low battery shutdown at 21 VDC (with in-rush delay)

### INVERTER SPECIFICATIONS

MODEL NUMBER	MIL-24XM15N	MIL-24FM30N	MIL-24DM50DN
Output Power (Watts Cont.)	1,500	3,000	5,000
Output Voltage (Volts AC)	120	120	120 / 240
Output Current (Amps AC)	Up to 12 @ 120VAC	Up to 25 @ 120VAC	Up to 21 @ 240VAC
Peak Output (Amps AC)	40	75	120
Output Rating (hp)	0.5	1.5	2.5
Input Current (Amps DC)	Up to 75	Up to 150	Up to 250
Weight (lbs)	52	81	134
Dimensions (LxWxH, inches)	15 x 17 x 7	17 x 18.5 x 10.5	20 x 19.5 x 13.25



The World Depends on Sensors and Controls

#### SENSATA TECHNOLOGIES

Power Controls White Bear  
4467 White Bear Parkway  
St. Paul, MN 55110 USA  
1-651-653-7000 (Main)  
1-651-653-7600 (Fax)  
<http://dimensions.sensata.com/>  
<http://www.sensata.com/>

Important Notice: Sensata Technologies (Sensata) reserves the right to make changes to or discontinue any product or service identified in this publication without notice. Sensata advises its customers to obtain the latest version of the relevant information to verify, before placing any orders, that the information being relied upon is current. Sensata assumes no responsibility for infringement of patents or rights of others based on Sensata applications assistance or product specifications since Sensata does not possess full access concerning the use or application of customers' products. Sensata also assumes no responsibility for customers' product designs.

Printed In U.S.A., February 2010

PCW # 130865