

FEATURES

- Fixed gain of 16 dB**
- Operation from 20 MHz to 1.0 GHz**
- Input and output internally matched to 50 Ω**
- Integrated bias control circuit**
- OIP3**
 - 45.5 dBm at 190 MHz**
 - 45.5 dBm at 380 MHz**
- Noise figure**
 - 3.2 dB at 190 MHz**
 - 3.3 dB at 380 MHz**
- P1dB of 18.9 dBm at 190 MHz**
- Single 5 V power supply**
- Low quiescent current of 97 mA**
- MSL-1 rated SOT-89 package**
- ESD rating of ±2 kV (Class 2)**
- Pin-compatible with the 20 dB gain ADL5536**

FUNCTIONAL BLOCK DIAGRAM




Figure 1.

08674-01

GENERAL DESCRIPTION

The ADL5535 is a 16 dB linear amplifier that operates at frequencies up to 1 GHz. The device can be used in a wide variety of cellular, CATV, military, and instrumentation equipment.

The ADL5535 provides the highest dynamic range available from an internally matched IF gain block. This is accomplished by providing extremely low noise figures and very high OIP3 specifications simultaneously across the entire 1 GHz frequency range. The ADL5535 also provides extremely flat gain and P1dB over frequency, which are stable over temperature, power supply, and from device to device.

The device is internally matched to 50 Ω at the input and output, making the ADL5535 very easy to implement in a wide variety of applications. Only input/output ac coupling capacitors, power supply decoupling capacitors, and an external inductor are required for operation.

The ADL5535 is fabricated on a GaAs HBT process and has an ESD rating of ±2 kV (Class 2). The device is assembled in an MSL-1 rated SOT-89 package that uses an exposed paddle for excellent thermal impedance.

The ADL5535 consumes only 97 mA on a single 5 V supply and is fully specified for operation from -40°C to +85°C.

The ADL5535 is also pin-compatible with the 20 dB gain [ADL5536](#). Fully populated evaluation boards are available for each amplifier.

Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
 Tel: 781.329.4700 www.analog.com
 Fax: 781.461.3113 ©2010 Analog Devices, Inc. All rights reserved.

TABLE OF CONTENTS

| | | | |
|--|---|---|----|
| Features | 1 | Basic Connections | 10 |
| Functional Block Diagram | 1 | Soldering Information and Recommended PCB | |
| General Description | 1 | Land Pattern..... | 10 |
| Revision History | 2 | ACPR Performance | 11 |
| Specifications..... | 3 | Error Vector Magnitude (EVM) Performance..... | 11 |
| Typical Scattering Parameters (S-Parameters) | 5 | ADC Driving Application | 12 |
| Absolute Maximum Ratings..... | 6 | Evaluation Board | 13 |
| ESD Caution..... | 6 | Outline Dimensions | 14 |
| Pin Configuration and Function Descriptions..... | 7 | Ordering Guide | 14 |
| Typical Performance Characteristics | 8 | | |

REVISION HISTORY

4/10—Revision 0: Initial Version

SPECIFICATIONS

$V_{CC} = 5 \text{ V}$ and $T_A = 25^\circ\text{C}$, unless otherwise noted.

Table 1.

| Parameter | Test Conditions/Comments | Min | Typ | Max | Unit |
|--------------------------------------|--|------------|------|------|------|
| OVERALL FUNCTION | | | | | |
| Frequency Range | | 20 | 1000 | | MHz |
| FREQUENCY = 20 MHz | | | | | |
| Gain | | 16.7 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 17.7 | | | dBm |
| Output Third-Order Intercept (OIP3) | $\Delta f = 1 \text{ MHz}$, output power (P_{OUT}) = 3 dBm per tone | 41.5 | | | dBm |
| Second Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -59.5 | | | dBc |
| Third Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -93 | | | dBc |
| Noise Figure | | 3.0 | | | dB |
| FREQUENCY = 70 MHz | | | | | |
| Gain | | 16.5 | | | dB |
| vs. Frequency | $\pm 50 \text{ MHz}$ | ± 0.33 | | | dB |
| vs. Temperature | $-40^\circ\text{C} \leq T_A \leq +85^\circ\text{C}$ | ± 0.16 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ± 0.04 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 18.9 | | | dBm |
| Output Third-Order Intercept (OIP3) | | 43.5 | | | dBm |
| Second Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -64 | | | dBc |
| Third Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -93 | | | dBc |
| Noise Figure | | 3.0 | | | dB |
| FREQUENCY = 190 MHz | | | | | |
| Gain | | 15.2 | 16.1 | 17.0 | dB |
| vs. Frequency | $\pm 50 \text{ MHz}$ | ± 0.06 | | | dB |
| vs. Temperature | $-40^\circ\text{C} \leq T_A \leq +85^\circ\text{C}$ | ± 0.17 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ± 0.04 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 17.8 | 18.9 | | dBm |
| Output Third-Order Intercept (OIP3) | | 45.5 | | | dBm |
| Second Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -60.2 | | | dBc |
| Third Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -84.3 | | | dBc |
| Noise Figure | | 3.2 | | | dB |
| FREQUENCY = 380 MHz | | | | | |
| Gain | | 15.0 | 15.8 | 16.5 | dB |
| vs. Frequency | $\pm 50 \text{ MHz}$ | ± 0.08 | | | dB |
| vs. Temperature | $-40^\circ\text{C} \leq T_A \leq +85^\circ\text{C}$ | ± 0.17 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ± 0.05 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 17.8 | 18.9 | | dBm |
| Output Third-Order Intercept (OIP3) | | 45.5 | | | dBm |
| Second Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -61.9 | | | dBc |
| Third Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -75 | | | dBc |
| Noise Figure | | 3.3 | | | dB |
| FREQUENCY = 748 MHz | | | | | |
| Gain | | 15.2 | | | dB |
| vs. Frequency | $\pm 50 \text{ MHz}$ | ± 0.10 | | | dB |
| vs. Temperature | $-40^\circ\text{C} \leq T_A \leq +85^\circ\text{C}$ | ± 0.20 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ± 0.06 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 18.9 | | | dBm |
| Output Third-Order Intercept (OIP3) | | 42.0 | | | dBm |
| Second Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -52.6 | | | dBc |
| Third Harmonic | $P_{OUT} = 0 \text{ dBm}$ | -68 | | | dBc |
| Noise Figure | | 3.2 | | | dB |

ADL5535

| Parameter | Test Conditions/Comments | Min | Typ | Max | Unit |
|--------------------------------------|---|-------|-----|-----|------|
| FREQUENCY = 900 MHz | | | | | |
| Gain | | 15.1 | | | dB |
| vs. Frequency | ±50 MHz | ±0.11 | | | dB |
| vs. Temperature | −40°C ≤ TA ≤ +85°C | ±0.20 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ±0.06 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 19.0 | | | dBm |
| Output Third-Order Intercept (OIP3) | Δf = 1 MHz, output power (P _{OUT}) = 3 dBm per tone | 40.0 | | | dBm |
| Second Harmonic | P _{OUT} = 0 dBm | −59.3 | | | dBc |
| Third Harmonic | P _{OUT} = 0 dBm | −64.6 | | | dBc |
| Noise Figure | | 3.2 | | | dB |
| FREQUENCY = 1000 MHz | | | | | |
| Gain | | 14.9 | | | dB |
| vs. Frequency | ±50 MHz | ±0.11 | | | dB |
| vs. Temperature | −40°C ≤ TA ≤ +85°C | ±0.21 | | | dB |
| vs. Supply Voltage | 4.75 V to 5.25 V | ±0.07 | | | dB |
| Output 1 dB Compression Point (P1dB) | | 18.9 | | | dBm |
| Output Third-Order Intercept (OIP3) | Δf = 1 MHz, output power (P _{OUT}) = 3 dBm per tone | 39.5 | | | dBm |
| Second Harmonic | P _{OUT} = 0 dBm | −51.4 | | | dBc |
| Third Harmonic | P _{OUT} = 0 dBm | −63.1 | | | dBc |
| Noise Figure | | 3.3 | | | dB |
| POWER INTERFACE | | | | | |
| Supply Voltage (V _{CC}) | | 4.5 | 5.0 | 5.5 | V |
| Supply Current | | 97 | 115 | | mA |
| vs. Temperature | −40°C ≤ TA ≤ +85°C | ±2.0 | | | mA |
| Power Dissipation | V _{CC} = 5 V | 0.5 | | | W |

TYPICAL SCATTERING PARAMETERS (S-PARAMETERS)

$V_{CC} = 5$ V, $T_A = 25^\circ\text{C}$, and the effects of the test fixture have been de-embedded up to the pins of the device.

Table 2.

| Frequency (MHz) | S11 | | S21 | | S12 | | S22 | |
|--------------------|----------------|-----------|----------------|-----------|----------------|-----------|----------------|-----------|
| | Magnitude (dB) | Angle (°) |
| 20 | -13.03 | -112.72 | 17.11 | 167.18 | -19.70 | +10.45 | -14.78 | -125.49 |
| 70 | -18.32 | -152.93 | 16.33 | 171.17 | -19.67 | +0.77 | -15.85 | -161.12 |
| 120 | -19.04 | -161.05 | 16.22 | 169.68 | -19.66 | -1.99 | -15.99 | -166.87 |
| 190 | -19.31 | -163.81 | 16.16 | 166.09 | -19.65 | -4.89 | -15.97 | -168.23 |
| 240 | -19.35 | -163.54 | 16.10 | 163.36 | -19.65 | -6.74 | -15.91 | -167.75 |
| 290 | -19.26 | -162.62 | 16.08 | 160.44 | -19.65 | -8.54 | -15.81 | -166.89 |
| 340 | -19.24 | -161.59 | 16.01 | 157.37 | -19.66 | -10.20 | -15.70 | -166.07 |
| 390 | -19.12 | -158.71 | 15.94 | 154.60 | -19.65 | -11.99 | -15.53 | -164.46 |
| 440 | -18.88 | -157.70 | 15.91 | 151.65 | -19.65 | -13.65 | -15.28 | -163.07 |
| 490 | -18.58 | -157.00 | 15.84 | 148.72 | -19.69 | -15.34 | -15.02 | -162.82 |
| 540 | -18.35 | -156.08 | 15.80 | 145.67 | -19.71 | -16.97 | -14.80 | -162.40 |
| 590 | -18.12 | -154.28 | 15.71 | 142.80 | -19.70 | -18.60 | -14.58 | -161.54 |
| 640 | -17.82 | -153.50 | 15.67 | 139.94 | -19.71 | -20.26 | -14.31 | -161.17 |
| 690 | -17.57 | -152.78 | 15.59 | 136.89 | -19.73 | -21.87 | -14.07 | -160.95 |
| 740 | -17.30 | -151.90 | 15.51 | 134.11 | -19.74 | -23.49 | -13.82 | -160.76 |
| 790 | -17.04 | -151.31 | 15.44 | 131.17 | -19.75 | -25.11 | -13.58 | -160.71 |
| 840 | -16.76 | -150.77 | 15.35 | 128.31 | -19.77 | -26.74 | -13.34 | -160.76 |
| 900 | -16.41 | -150.20 | 15.26 | 125.01 | -19.79 | -28.65 | -13.05 | -160.99 |
| 950 | -16.15 | -149.94 | 15.17 | 122.08 | -19.80 | -30.29 | -12.82 | -161.31 |
| 1000 | -15.87 | -149.69 | 15.08 | 119.42 | -19.82 | -31.88 | -12.59 | -161.67 |
| 1050 | -15.60 | -149.72 | 15.00 | 116.58 | -19.84 | -33.51 | -12.38 | -162.13 |
| 1100 | -15.35 | -149.61 | 14.89 | 113.89 | -19.86 | -35.10 | -12.17 | -162.71 |
| 1150 | -15.08 | -149.74 | 14.81 | 111.22 | -19.88 | -36.69 | -11.97 | -163.25 |
| 1200 | -14.86 | -149.84 | 14.70 | 108.43 | -19.90 | -38.29 | -11.79 | -163.86 |
| 1250 | -14.58 | -149.97 | 14.61 | 105.97 | -19.92 | -39.90 | -11.59 | -164.52 |
| 1300 | -14.35 | -150.33 | 14.52 | 103.20 | -19.94 | -41.52 | -11.41 | -165.22 |
| 1350 | -14.11 | -150.67 | 14.41 | 100.66 | -19.96 | -43.13 | -11.25 | -166.05 |
| 1400 | -13.90 | -151.10 | 14.32 | 98.10 | -19.99 | -44.68 | -11.08 | -166.79 |
| 1450 | -13.69 | -151.43 | 14.21 | 95.51 | -20.02 | -46.23 | -10.93 | -167.47 |
| 1500 | -13.46 | -151.86 | 14.11 | 93.03 | -20.04 | -47.82 | -10.78 | -168.33 |
| 1550 | -13.26 | -152.41 | 14.02 | 90.50 | -20.06 | -49.37 | -10.63 | -169.12 |

ABSOLUTE MAXIMUM RATINGS

Table 3.

| Parameter | Rating |
|--|-----------------|
| Supply Voltage, V_{CC} | 6.5 V |
| Input Power (Referred to 50 Ω) | 20 dBm |
| Internal Power Dissipation (Paddle Soldered) | 650 mW |
| θ_{JA} (Junction to Air) | 30.7°C/W |
| θ_{JC} (Junction to Paddle) | 5.0°C/W |
| Maximum Junction Temperature | 150°C |
| Lead Temperature (Soldering, 60 sec) | 240°C |
| Operating Temperature Range | -40°C to +85°C |
| Storage Temperature Range | -65°C to +150°C |


Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ESD CAUTION



ESD (electrostatic discharge) sensitive device.
Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS



NOTES
1. THE EXPOSED PADDLE IS
INTERNALLY CONNECTED TO GND
AND MUST BE SOLDERED TO A LOW
IMPEDANCE GROUND PLANE.

08874-002

Figure 2. Pin Configuration

Table 4. Pin Function Descriptions

| Pin No. | Mnemonic | Description |
|---------|----------------|---|
| 1 | RFIN | RF Input. This pin requires a dc blocking capacitor. |
| 2 | GND | Ground. Connect this pin to a low impedance ground plane. |
| 3 | RFOUT | RF Output and Supply Voltage. A dc bias is provided to this pin through an inductor that is connected to the external power supply. The RF path requires a dc blocking capacitor. |
| (2) | Exposed Paddle | Exposed Paddle. The exposed paddle is internally connected to GND and must be soldered to a low impedance ground plane. |

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 3. Noise Figure, Gain, P_{1dB}, and OIP₃ vs. Frequency




Figure 6. P_{1dB} and OIP₃ vs. Frequency and Temperature




Figure 4. Gain vs. Frequency and Temperature




Figure 7. OIP₃ vs. Output Power (P_{out}) and Frequency




Figure 5. Input Return Loss (S11), Output Return Loss (S22), and Reverse Isolation (S12) vs. Frequency




Figure 8. Noise Figure vs. Frequency and Temperature




Figure 9. Single-Tone Harmonics vs. Frequency, $P_{out} = 0 \text{ dBm}$ Figure 12. OIP3 Distribution at 190 MHz, $P_{out} = 3 \text{ dBm}$ 

Figure 10. Gain Distribution at 190 MHz




Figure 13. Noise Figure Distribution at 190 MHz




Figure 11. P1dB Distribution at 190 MHz




Figure 14. Supply Current vs. Temperature

BASIC CONNECTIONS

The basic connections for operating the ADL5535 are shown in Figure 15. Recommended components are listed in Table 5. The input and output should be ac-coupled with appropriately sized capacitors (device characterization was performed with $0.1\text{ }\mu\text{F}$ capacitors). A 5 V dc bias is supplied to the amplifier through the bias inductor connected to RFOUT (Pin 3). The bias voltage should be decoupled using a $1\text{ }\mu\text{F}$ capacitor, a 1.2 nF capacitor, and a 68 pF capacitor.




Figure 15. Basic Connections

SOLDERING INFORMATION AND RECOMMENDED PCB LAND PATTERN

Figure 16 shows the recommended land pattern for the ADL5535. To minimize thermal impedance, the exposed paddle on the package underside, along with Pin 2, should be soldered to a ground plane. If multiple ground layers exist, they should be stitched together using vias. For more information about land pattern design and layout, refer to the AN-772 Application Note, *A Design and Manufacturing Guide for the Lead Frame Chip Scale Package (LFCSP)*.




Figure 16. Recommended Land Pattern

Table 5. Recommended Components for Basic Connections

| Frequency | C1 | C2 | L1 | C4 | C5 | C6 |
|--------------------|--------------------------|--------------------------|---|----------------|-----------------|------------------------|
| 20 MHz to 1000 MHz | $0.1\text{ }\mu\text{F}$ | $0.1\text{ }\mu\text{F}$ | 470 nH (Coilcraft 0603LS-NX or equivalent) | 68 pF | 1.2 nF | $1\text{ }\mu\text{F}$ |

ACPR PERFORMANCE

Figure 17 shows a plot of the adjacent channel power ratio (ACPR) vs. P_{OUT} for the ADL5535. The signal type used is a single wideband code division multiple access (W-CDMA) carrier (Test Model 1-64). This signal is generated by a very low ACPR source. ACPR is measured at the output by a high dynamic range spectrum analyzer that incorporates an instrument noise-correction function. At an output power level of +8 dBm, ACPR is still very low at -65 dBc, making the device suitable for use in driver applications.




Figure 17. ACPR vs. P_{OUT} , Single W-CDMA Carrier (Test Model 1-64) at 190 MHz and 380 MHz

ERROR VECTOR MAGNITUDE (EVM) PERFORMANCE

Error vector magnitude (EVM) is a measure used to quantify the performance of a digital radio transmitter or receiver. A signal received by a receiver has all constellation points at their ideal locations; however, various imperfections in the implementation (such as magnitude imbalance, noise floor, and phase imbalance) cause the actual constellation points to deviate from their ideal locations. The ADL5535 shows excellent performance when used with higher-order modulation schemes, such as a 16 QAM.

Figure 18 illustrates the EVM performance of the ADL5535 when driven with a 16 QAM 10 Msym/s signal. Degradation of the EVM performance starts to occur at an output power of +12 dBm.




Figure 18. EVM Performance vs. P_{OUT} with a 16 QAM, 10 Msym/s Signal

ADL5535

ADC DRIVING APPLICATION

The ADL5535 is a high linearity, fixed gain IF amplifier suitable for use as an ADC driver. Figure 22 shows the schematic of the ADL5535 driving the [AD9268](#) 16-bit analog-to-digital converter (ADC). The ADL5535 has a single-ended input and output impedance of 50Ω . A 1:1 impedance transformer, along with termination resistors and series ferrite beads, are used to present a 50Ω load for the antialiasing filter interface. The filter interface between the ADL5535 and the AD9268 is a sixth-order Butterworth low-pass filter. The interface provides a 50 MHz, 1 dB bandwidth centered around 175 MHz. Following the sixth-order filter, a shunt LC tank circuit was inserted to further reduce the low frequency response of the filter, giving more of a band-pass response to the filter. The normalized wideband response is shown in Figure 19.




Figure 19. Normalized Response of the ADC Interface Shown in Figure 22




Figure 20. Measured Single-Tone Performance of the Circuit Shown in Figure 22

08674-019




Figure 21. Measured Two-Tone Performance of the Circuit Shown in Figure 22

08674-020




Figure 22. Schematic of the ADL5535 Driving the AD9268 16-Bit ADC

08674-022

EVALUATION BOARD

Figure 23 shows the evaluation board layout, and Figure 24 shows the schematic for the ADL5535 evaluation board. The board is powered by a single 5 V supply.

The components used on the board are listed in Table 6. Power can be applied to the board through clip-on leads (VCC and GND).




Figure 23. Evaluation Board Layout (Top)





Figure 24. Evaluation Board Schematic

Table 6. Evaluation Board Components

| Component | Description | Default Value |
|-----------|------------------------------------|--|
| C1, C2 | AC coupling capacitors | 0.1 μF, 0402 |
| L1 | DC bias inductor | 470 nH, 0603 (Coilcraft 0603LS-NX or equivalent) |
| VCC, GND | Clip-on terminals for power supply | |
| C4 | Power supply decoupling capacitor | 68 pF, 0603 |
| C5 | Power supply decoupling capacitor | 1.2 nF, 0603 |
| C6 | Power supply decoupling capacitor | 1 μF, 1206 |

OUTLINE DIMENSIONS



*COMPLIANT TO JEDEC STANDARDS TO-243 WITH THE EXCEPTION OF DIMENSIONS INDICATED BY AN ASTERISK.

12-18-2008-B

Figure 25. 3-Lead Small Outline Transistor Package [SOT-89]
(RK-3)
Dimensions shown in millimeters

ORDERING GUIDE

| Model ¹ | Temperature Range | Package Description | Package Option |
|--------------------|-------------------|---------------------------------|----------------|
| ADL5535ARKZ-R7 | -40°C to +85°C | 3-Lead SOT-89, 7" Tape and Reel | RK-3 |
| ADL5535-EVALZ | | Evaluation Board | |

¹ Z = RoHS Compliant Part.

NOTES

ADL5535

NOTES

©2010 Analog Devices, Inc. All rights reserved. Trademarks and registered trademarks are the property of their respective owners.
D08674-0-4/10(0)



www.analog.com